AVT Marlin

Technical Manual

For CCD models with serial numbers: xx/yy-6zzzzzzz
and all CMOS models

Allied Vision Technologies GmbH
Taschenweg 2a
D-07646 Stadtroda / Germany

ALLIED
Vision Technologies

Before operation

We place the highest demands for quality on our cameras. This technical manual is the guide to the installation and setting up of the camera for operation.

ⓘ This version 1.3 of the technical manual applies to Marlins, having serial numbers starting with 6 after the – eg. Xx/yy-6zzzzzzz and all CMOS versions, regardless of S/N.

ⓘ For CCD Marlins with different serial numbers the previous version 1.2 of the technical manual applies.

Please read through this manual carefully before operating the camera.

Legal notice

For customers in the U.S.A.

This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense. You are cautioned that any changes or modifications not expressly approved in this manual could void your authority to operate this equipment. The shielded interface cable recommended in this manual must be used with this equipment in order to comply with the limits for a computing device pursuant to Subpart J of Part 15 of FCC Rules.

For customers in Canada

This apparatus complies with the Class A limits for radio noise emissions set out in the Radio Interference Regulations.

Pour utilisateurs au Canada

Cet appareil est conforme aux normes classe A pour bruits radioélectriques, spécifiées dans le Règlement sur le brouillage radioélectrique.

Life support applications

These products are not designed for use in life support appliances, devices, or systems where malfunction of these products can reasonably be expected to result in personal injury. Allied customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Allied for any damages resulting from such improper use or sale.

Allied Vision Technologies GmbH 02/2005
All rights reserved.

Managing Director: Mr. Frank Grube
Tax-ID: DE 184383113

Support:
Taschenweg 2A
D-07646 Stadtroda, Germany

Tel.: +49/36428/6770
Fax: +49/36428/677-28
email: info@alliedvisiontec.com

Copyright

All texts, pictures and graphics are protected by copyright and other laws protecting intellectual property. It is not permitted to copy or modify them for trade use or transfer, nor may they be used on web sites.

Trademarks

Unless stated otherwise, all trademarks appearing in this document of Allied Vision Technologies are brands protected by law.

Warranty

The information supplied by Allied Vision Technologies is supplied without any guarantees or warranty whatsoever, be it specific or implicit. Also excluded are all implicit warranties concerning the negotiability, the suitability for specific applications or the non-breaking of laws and patents. Even if we assume that the information supplied to us is accurate, errors and inaccuracy may still occur.

Document History

Version	Date	Remarks
0.9	18.12.2003	First Issue
0.91	09.01.2004	Typos corrected, minor changes, spectral sens. of IR cut filter added
1.0	20.01.2004	Wording checked, Marlin W90/270 added
1.1	07.09.2004	F-131C added, added features to make docu. compliant w. FW 2.05, wording checked, impulse diagrams corrected
1.2	08.10.2004	Manual compliant to FW 2.06
1.3	23.02.2005	For Marlins w. ser.# xx/yy-6zzzzzzz
1.31	12.04.2005	Color: FW 2005032 CMOS included

Contents

1 Safety instructions 9
1.1 Environmental conditions 10
2 Marlin types and highlights 11
3 System components 12
4 Specifications 14
4.1 MF-033B 14
4.2 MF-033C 15
4.3 MF-046B 16
4.4 MF-046C 17
4.5 MF-080B (-30 fps*) 18
4.6 MF-080C (-30 fps*) 19
4.7 MF-145B2 20
4.8 MF-145C2 21
4.9 F-131B 22
4.10 F-131C 23
4.11 Spectral sensitivity 24
5 Quick start 29
6 Camera dimensions 30
6.1 Marlin standard housing 30
6.2 Marlin W90 31
6.3 Marlin W90 S90 32
6.4 Marlin W270 33
6.5 Marlin W270 S90 34
6.6 Tripod adapter 35
7 Camera interfaces 36
7.1 IEEE-1394 port pin assignment 36
7.2 HiRose jack pin assignment 37
7.3 Status LEDs 38
7.4 Operating the camera: 39
7.5 Control and video data signals 39
7.5.1 Inputs 39
7.5.2 Outputs 44
7.6 Pixel data 48
8 Description of the data path 50
8.1 Block diagrams of the cameras 50
8.1.1 Black and white cameras: 51
8.1.2 Color cameras: 52
8.2 Sensor 53
8.2.1 IBIS5A multiple slope (High Dynamic Range mode) 54
8.3 White balance 57
8.3.1 One Push automatic white balance 59
8.3.2 Automatic white balance 60
8.4 Manual gain 62

8.5 Auto gain 62
8.6 Setting the brightness (black level or offset) 65
8.7 Auto shutter 65
8.8 Lookup table (LUT) and Gamma function 67
8.8.1 Loading a LUT into the camera 68
8.9 Shading correction 70
8.9.1 Automatic generation of correction data 70
8.9.2 Loading a shading image into the camera 75
8.9.3 Loading a shading image out of the camera 76
8.10 DSNU & blemish correction (MF-131B only) 77
8.11 Horizontal mirror function 80
8.12 Binning (CCD b/w models) 81
8.12.1 Vertical binning 81
8.12.2 Horizontal binning 82
8.12.3 Full binning 82
8.13 Sub-sampling (CMOS) 83
8.14 Sharpness 84
8.15 Color interpolation and correction 85
8.15.1 Color interpolation (BAYER demosaicing) 85
8.15.2 Color correction 86
8.15.3 RGB → YUV conversion 86
8.15.4 Hue and Saturation 86
8.16 Serial interface 87
9 Controlling image capture 91
9.1 Trigger modi 91
9.1.1 Trigger delay 94
9.2 Exposure time 96
9.2.1 Extended shutter 96
9.3 One-Shot 97
9.3.1 One-Shot command on the bus to start of exposure 97
9.3.2 End of exposure to first packet on the bus 98
9.4 Multi-Shot 98
9.5 ISO_Enable / Free-Run 99
9.6 Asynchronous broadcast 99
9.7 Jitter at start of exposure 100
9.8 Frame memory and deferred image transport 101
9.8.1 HoldImg mode 102
9.8.2 FastCapture 103
9.9 Sequence mode 104
9.9.1 Changing the parameters within a sequence 107
10 Video formats, modes and bandwidth 109
10.1 MF-033B/ MF-033C 109
10.2 MF-046B/ MF-046C 110
10.3 MF-080B/ MF-080C (-30 fps) 111
10.4 MF-145B/ MF-145C 112
10.5 MF-131B/ MF-131C 113
10.6 Area of interest (AOI) 114

10.7 Frame rates 116
10.7.1 MF-033 120
10.7.2 MF-046 121
10.7.3 MF-080 122
10.7.4 MF-080-30 fps 123
10.7.5 MF-145 124
10.7.6 MF-131 125
11 How does bandwidth affect the frame rate? 126
11.1 Test images 127
12 Configuration of the camera 129
12.1 Camera_Status_Register 129
12.2 Configuration ROM 131
12.3 Implemented registers 134
12.3.1 Camera initialize register 134
12.3.2 Inquiry register for video format 134
12.3.3 Inquiry register for video mode 134
12.3.4 Inquiry register for video frame rate and base address 136
12.3.5 Inquiry register for basic function 142
12.3.6 Inquiry register for feature presence 142
12.3.7 Inquiry register for feature elements 145
12.3.8 Inquiry register for absolute value CSR offset address 148
12.3.9 Status and control register for feature 149
12.3.10 Feature control error status register 150
12.3.11 Video mode control and status registers for Format_7 150
12.4 Advanced features 151
12.4.1 Version information inquiry 153
12.4.2 Advanced feature inquiry 154
12.4.3 MaxResolution 154
12.4.4 Timebase 155
12.4.5 Extended shutter 156
12.4.6 Test images 157
12.4.7 Sequence control 158
12.4.8 Lookup tables (LUT) 159
12.4.9 Shading correction 160
12.4.10 Deferred image transport 162
12.4.11 Frame information 162
12.4.12 High dynamic range mode (MF-131B/C only) 163
12.4.13 DSNU control 163
12.4.14 Input/output pin control 165
12.4.15 Delayed Integration enable 166
12.4.16 Auto shutter 167
12.4.17 Auto gain 168
12.4.18 Auto function AOI 168
12.4.19 Color correction 169
12.4.20 Trigger delay 169
12.4.21 Mirror 169
12.4.22 GPDATA_BUFFER 170

12.4.23 Soft Reset 170
13 Firmware update 171
14 Declarations of conformity 172
15 Index 182

Conventions used in this manual

To give this manual an easily understood layout and to emphasize important information, the following typographical styles and symbols are used:

Styles

Style	Function	Example
`Courier`	Programs, inputs, etc.	"`Input`"
upper case	Register	REGISTER
italics	Modes, fields	*Mode*
parentheses and/or blue	Links	(Link)

Symbols:

ⓘ This symbol highlights important instructions that should be followed to avoid malfunctions.

1 Safety instructions

ⓘ There are no switches or parts inside the camera that require adjustment. The guarantee becomes void upon opening the camera casing.

ⓘ If the product is disassembled, reworked or repaired by other than a recommended service person, AVT or its suppliers will take no responsibility for the subsequent performance or quality of the camera.

ⓘ The camera does NOT generate dangerous voltages internally. However, because the IEEE-1394a standard permits cable power distribution at voltages higher than 24 V, various international safety standards apply. Reference documents applicable in the United States include:

- Information Processing and Business Equipment, UL 478
- National Electric Code, ANSI/NFPA 70
- Standard for the Protection of Electronic Computer/Data-Processing Equipment, ANSI/NFPA 75

Reference documents applicable in Europe include materials to secure the European Union CE marking as follows:

- Telecommunications Terminal Equipment (91/263/EEC)
- EMC Directive (89/339/EEC)
- CE Marking Directive (93/68/EEC)
- LOW Voltage Directive (73/23/EEC) as amended by the CE Marking

Reference documents applicable in Japan include:

- Electronic Equipment Technology Criteria by the Ministry of Trading and Industry (Similar to NFPA 70)
- Wired Electric Communication Detailed Law 17 by the Ministry of Posts and Telecom Law for Electric Equipment
- Dentori law issued by the Ministry of Trading and Industry
- Fire law issued by the Ministry of Construction

ⓘ Make sure NOT to touch the shield of the camera cable connected to a computer and the ground terminal of the lines at the same time.

ⓘ Use only DC-power supplies with insulated cases. These are identified by having only TWO power connectors.

ⓘ Although IEEE-1394a is functionally plug and play, the physical ports may be damaged by excessive ESD (electrostatic discharge), when connected under powered conditions. It is good practice to bring the metal part, which is the shield of the IEEE-1394 cable, in contact with the housing of the camera, before plugging it into the camera and on the other side in contact with metal parts of the computer, before plugging it into the port of the computer. This ensures that excessive charge can flow safely to ground.

ⓘ When you feel uncomfortable with the previous advice or when you do not know the connectivity of an installation at all, we strongly recommend to power all systems down before connecting or disconnecting a camera.

1.1 Environmental conditions

Ambient temperature:

when camera in use:	+ 5° C ... + 45° C
when being stored :	- 10° C ... + 60° C

Relative humidity:	20 % ... 80 % no condensed water
Protection:	IP 30

2 Marlin types and highlights

With Marlin cameras, entry into the world of digital image processing is simpler and more cost-effective than ever before.
With the new MARLIN, Allied Vision Technologies presents a whole series of attractive digital camera entry-level models of the FireWire ™type.
These products offer an unequalled price-performance relationship and make the decision to switch from using analogue to digital technology easier that ever before.
The AVT Marlin family consists of five very compact IEEE 1394 C-mount cameras, which are equipped with highly sensitive high-quality sensors (CCD,CMOS). Each of these cameras is available in black/white and color versions.
A large selection of different sensor sizes (1/2 ", 1/3 ", 2/3 ") and resolutions (VGA, SVGA, XGA, SXGA) ensures the suitability of the cameras for all applications.
The MARLIN family consists of the following models:

MARLIN F-033B/C
1/2 " Sony Progressive Scan CCD imager; (VGA) 656 (h) x 494 (v); up to 74 fps at full resolution.

MARLIN F-046B/C
1/2 " Sony Progressive Scan CCD imager; (SVGA) 780 (h) x 582 (v); up to 53 fps.

MARLIN F-080B/C
1/3 " Sony Progressive Scan CCD imager; (XGA) 1032 (h) x 778 (v); up to 20 fps.

MARLIN F-080B/C 30 fps
1/3 " Sony Progressive Scan CCD imager; (XGA) 1032 (h) x 778 (v); up to 30 fps.

MARLIN F-131B/C
2/3 " Global Shutter CMOS imager; (SXGA) 1280 (h) x 1024 (v); up to 25 fps.

MARLIN F-145B2/C2
1/2 " Sony Progressive Scan CCD; (SXGA) 1392 (h) x 1040 (v); up to 10 fps (15 fps available on request) at full resolution.

Operating in 8-bit and 10 Bit mode mode (CCD b/w only), the cameras ensure very high quality images under almost all circumstances. The MARLIN is equipped with an asynchronous trigger shutter as well as true partial scan, and integrates numerous useful and intelligent Smart Features for image processing.

- ⓘ All models are equipped with an optical filter to eliminate the influence of infra red light hitting the sensor. Please be advised that, as a side effect, this filter reduces the sensitivity in the visible spectrum.
- ⓘ For certain applications it may thus be recommended to take out the filter by means of a special tool which can be ordered from AVT under the following number: E9020001.
- ⓘ Taking out the filter requires special care. Ask your dealer to help you if you are not confident with the procedure.

3 System components

The following system components are included with each camera::

AVT Marlin

4.5m 1394 standard cable

Jenofilt 217 IR cut filter (built in)

Optional:

Tripod Adapter



4.5m latching cable

Driver and documentation

The following illustration shows the spectral sensitivity of the IR cut filter



Figure 1: Spectral sensitivity of Jenofilt 217

To demonstrate the properties of the camera, all examples in this manual are based on the "FirePackage" OHCI API software and the "SmartView" application.
These utilities can be obtained from Allied Vision Technologies. A free version of "SmartView" is available for download at www.alliedvisiontec.com.
The camera also works with all IIDC (formerly DCAM) compatible IEEE 1394 programs and image processing libraries.

AVT offers different lenses from a variety of manufacturers. The following table lists selected image formats depending on camera type, distance and the focal width of the lens.

Focal Width MF-033/046/145	**Distance = 0,5m**	**Distance = 1m**
4.8mm	0,5m x 0,67m	1,0m x 1,33m
8mm	0,3m x 0,4m	0,6m x 0,8m
12mm	0,195m x 0,26m	0,39m x 0,58m
16mm	0,145m x 0,19m	0,29m x 0,38m
25mm	9,1cm x 12,1cm	18,2cm x 24,2cm
35mm	6,4cm x 8,51cm	12,8cm x 17,02cm
50mm	4,4cm x 5,85cm	8,8cm x 11,7cm
Focal Width MF-080	**Distance = 0,5m**	**Distance = 1m**
4.8mm	0,375m x 0,5m	0,75m x 1m
8mm	0,22m x 0,29m	0,44m x 0,58m
12mm	0,145m x 0,19m	0,29m x 0,38m
16mm	11cm x 14,7cm	22cm x 29,4cm
25mm	6,9cm x 9,2cm	13,8cm x 18,4cm
35mm	4,8cm x 6,4cm	9,6cm x 12,8cm
50mm	3,3cm x 4,4cm	6,6cm x 8,8cm
Focal Width MF-131	**Distance = 0.5m**	**Distance = 1m**
4.8mm	0.7m x 0.93m	1.4m x 1.86m
8mm	0.4m x 0.53m	0.8m x 1.06m
12mm	0.27m x 0.36m	0.54m x 0.72m
16mm	0.2m x 0.27m	0.4m x 0.54m
25mm	12.5cm x 16.63cm	25cm x 33.25cm
35mm	8.8cm x 11.7cm	17.6cm x 23.4cm
50mm	6cm x 7.98cm	12cm x 15.96cm

Table 1: Focal Width vs. field of view

4 Specifications

4.1 MF-033B

Specification	
Image device	1/2 " (diag. 8 mm) type progressive scan SONY IT CCD
Effective Picture Elements	656 (H) x 494 (V)
Lens Mount	C-mount: 17.526 mm (in air); ∅ 25.4 mm (32 T.P.I.) Mechanical Flange Back to filter distance: 8.2 mm
Picture Sizes	640 x 480 pixels (Format_0) 656 x 494 pixels (Format_7 Mode_0) 328 x 494 pixels (Format_7 Mode_1) 656 x 246 pixels (Format_7 Mode_2) 328 x 246 pixels (Format_7 Mode_3)
Cell Size	9.9 µm x 9.9 µm
ADC	12 Bit
Data Path	8/10 Bit
Frame rates	3.75 Hz; 7.5 Hz; 15 Hz; 30 Hz; 60 Hz; up to 74 Hz in Format_7
Gain Control	Manual: 0–24 dB (0.035 dB/step); Auto gain (select. AOI)
Shutter Speed	20 …67.108.864 µs (~67s); Auto shutter (select. AOI)
External Trigger Shutter	Trigger_Mode_0, Trigger_Mode_1, Advanced feature: Trigger_Mode_15 (bulk); image transfer by command; Trigger delay
Internal FIFO-Memory	Up to 17 frames
# Look Up Tables	One, user programmable (10 Bit -> 8 Bit); Gamma (0.45)
Smart Functions	Real time shading correction image sequencing, two configurable inputs two configurable outputs, image mirror (L-R↔ R-L), binning, serial port (IIDC v. 1.31)
Transfer Rate	100 Mb/s, 200 Mb/s, 400 Mb/s
Digital Interface	IEEE 1394 IIDC v. 1.3
Power Requirements	DC 8 V – 36 V via IEEE 1394cable or 12-pin HIROSE
Power Consumption	Less than 3 Watts (@ 12 V d.c.)
Dimensions	58 mm x 44 mm x 29 mm (L x W x H); w/o tripod and lens
Mass	<120 g (without lens)
Operating Temperature	+5 – +45 ° Celsius
Storage Temperature	-10 – +60 ° Celsius
Regulations	EN 55022,EN61000,EN 55024,FCC Class A, DIN ISO 9022
Options	Removable IR-cut-filter, host adapter card, locking IEEE-1394 cable, API (FirePackage), TWAIN (WIA)- and WDM stream driver

Table 2: Specification MF-033B

The design and specifications for the products described above may change without notice.

4.2 MF-033C

Specification	
Image device	1/2 " (diag. 8 mm) type progressive scan SONY IT CCD
Effective Picture Elements	656 (H) x 494 (V)@Raw8 (492 @YUV)
Lens Mount	C-mount: 17.526 mm (in air); ∅ 25.4 mm (32 T.P.I.) Mechanical Flange Back to filter distance: 8.2 mm
Picture Sizes	640 x 480 pixels (Format_0) 656 x 492 pixels (Format_7 Mode_0) 656 x 494 pixels (Format_7 Mode_1)
Cell Size	9.9 µm x 9.9 µm
ADC	12 Bit
Color Modes	Raw8, YUV4:2:2, YUV4:1:1
Data Path	8 Bit
Frame rates	3.75 Hz; 7.5 Hz; 15 Hz; 30 Hz; up to 74 Hz in Format_7 (RAW); 68 Hz (YUV 4:1:1); up to 51 Hz in YUV 4:2:2
Gain Control	Manual: 0–16 dB (0.035 dB/step); Auto gain (select. AOI)
Color Control	Hue (-40°... +40°) and saturation (0...200%)
White Balance	Manual (U/V); One_Push; Auto (select. AOI)
Shutter Speed	20 ...67.108.864 µs (~67s); Auto shutter (select. AOI)
External Trigger Shutter	Trigger Mode_0, Trigger_Mode_1, Advanced feature: Trigger_Mode_15 (bulk); image transfer by command; Trigger delay
Internal FIFO-Memory	Up to 17 frames
# Look Up Tables	One, user programmable (10 Bit -> 8 Bit); Gamma (0.45)
Smart Functions	Real time shading correction image sequencing, two configurable inputs two configurable outputs, image mirror (L-R↔ R-L), serial port (IIDC v. 1.31)
Transfer Rate	100 Mb/s, 200 Mb/s, 400 Mb/s
Digital Interface	IEEE 1394 IIDC v. 1.3
Power Requirements	DC 8 V – 36 V via IEEE 1394 cable or 12-pin HIROSE
Power Consumption	Less than 3 Watts (@ 12 V d.c.)
Dimensions	58 mm x 44 mm x 29 mm (L x W x H); without tripod and lens
Mass	<120 g (without lens)
Operating Temperature	+5 – +45 ° Celsius
Storage Temperature	-10 – +60 ° Celsius
Regulations	EN 55022, EN 61000, EN 55024, FCC Class A, DIN ISO 9022
Options	Host adapter card, locking IEEE-1394 cable, API (FirePackage), TWAIN (WIA)- and WDM stream driver

Table 3: Specification MF-033C

The design and specifications for the products described above may change without notice.

4.3 MF-046B

Specification	
Image device	1/2 " (diag. 8 mm) type progressive scan SONY IT CCD
Effective Picture Elements	780 (H) x 582 (V)
Lens Mount	C-mount: 17.526 mm (in air); ∅ 25.4 mm (32 T.P.I.) Mechanical Flange Back to filter distance: 8.2 mm
Picture Sizes	640 x 480 pixels (Format_0); 780 x 582 (Format_7 Mode_0); 388 x 582 (Format_7 Mode_1); 780 x 290 (Format_7 Mode_2); 388 x 290 (Format_7 Mode_3)
Cell Size	8.3 µm x 8.3 µm
ADC	12 Bit
Data Path	8/10 Bit
Frame rates	3.75 Hz; 7.5 Hz; 15 Hz; 30 Hz; up to 53 Hz in Format_7
Gain Control	Manual: 0–24 dB (0.035 dB/step); Auto gain (select. AOI)
Shutter Speed	20 …67.108.864 µs (~67s); Auto shutter (select. AOI)
External Trigger Shutter	Trigger_Mode_0, Trigger_Mode_1, Advanced feature: Trigger_Mode_15 (bulk); image transfer by command; Trigger delay
Internal FIFO-Memory	Up to 13 frames
# Look Up Tables	One, user programmable (10 Bit -> 8 Bit); Gamma (0.45)
Smart Functions	Real time shading correction; image sequencing, two configurable inputs, two configurable outputs, image mirror (L-R↔ R-L), binning, serial port (IIDC v. 1.31)
Transfer Rate	100 Mb/s, 200 Mb/s, 400 Mb/s
Digital Interface	IEEE 1394 IIDC v. 1.3
Power Requirements	DC 8 V – 36 V via IEEE 1394 cable or 12-pin HIROSE
Power Consumption	Less than 3 Watts (@ 12 V d.c.)
Dimensions	58 mm x 44 mm x 29 mm (L x W x H); without tripod and lens
Mass	<120 g (without lens)
Operating Temperature	+5 – +45 ° Celsius
Storage Temperature	-10 – +60 ° Celsius
Regulations	EN 55022, EN 61000, EN 55024, FCC Class A, DIN ISO 9022
Options	Removable IR-cut-filter, host adapter card, locking IEEE-1394 cable, API (FirePackage), TWAIN (WIA)- and WDM stream driver

Table 4: Specification MF-046B

The design and specifications for the products described above may change without notice.

4.4 MF-046C

Specification	
Image device	1/2 " (diag. 8 mm) Type progressive scan SONY IT CCD
Effective Picture Elements	780 (H) x 582 (V)@Raw8; 780 (H) x 580 (V)@YUV
Lens Mount	C-mount: 17.526 mm (in air); ∅ 25.4 mm (32 T.P.I.) Mechanical Flange Back to filter distance: 8.2 mm
Picture Sizes	640 x 480 pixels (Format_0); 780 x 580 (Format_7 Mode_0); 780 x 582 (Format_7 Mode_1);
Cell Size	8.3 µm x 8.3 µm
ADC	12 Bit
Color Modes	Raw8, YUV4:2:2, YUV4:1:1
Data Path	8 Bit
Frame rates	3.75 Hz; 7.5 Hz; 15 Hz; 30 Hz; up to 53 Hz in Format_7 (Raw8) (36 Hz YUV4:2:2; 49Hz YUV4:1:1)
Gain Control	Manual: 0–16 dB (0.035 dB/step); Auto gain (select. AOI)
Color Control	Hue (-40°... +40°) and saturation (0...200%)
White Balance	Manual (U/V); One_Push; Auto (select. AOI)
Shutter Speed	20 ...67.108.864 µs (~67s); Auto shutter (select. AOI)
External Trigger Shutter	Trigger_Mode_0, Trigger_Mode_1, Advanced feature: Trigger_Mode_15 (bulk); image transfer by command; Trigger delay
Internal FIFO-Memory	Up to 13 frames
# Look Up Tables	One, user programmable (10 Bit -> 8 Bit); Gamma (0.45)
Smart Functions	Real time shading correction; image sequencing, two configurable inputs, two configurable outputs, image mirror (L-R↔ R-L), serial port (IIDC v. 1.31)
Transfer Rate	100 Mb/s, 200 Mb/s, 400 Mb/s
Digital Interface	IEEE 1394 IIDC v. 1.3
Power Requirements	DC 8 V – 36 V via IEEE 1394 cable or 12-pin HIROSE
Power Consumption	Less than 3 Watts (@ 12 V d.c.)
Dimensions	58 mm x 44 mm x 29 mm (L x W x H); without tripod and lens
Mass	<120 g (without lens)
Operating Temperature	+5 – +45 ° Celsius
Storage Temperature	-10 – +60 ° Celsius
Regulations	EN 55022, EN61000, EN 55024, FCC Class A, DIN ISO 9022
Options	Host adapter card, locking IEEE-1394 cable, API (FirePackage), TWAIN (WIA)- and WDM stream driver

Table 5: Specification MF-046C

The design and specifications for the products described above may change without notice.

4.5 MF-080B (-30 fps*)

Specification	
Image device	1/3 " (diag. 6 mm) type progressive scan SONY IT CCD
Effective Picture Elements	1032 (H) x 778 (V)
Lens Mount	C-mount: 17.526 mm (in air); ∅ 25.4 mm (32 T.P.I.) Mechanical Flange Back to filter distance: 8.2 mm, CS-mount on demand
Picture Sizes	1024 x 768 pixels (Format_1) supporting all smaller fixed formats; 1032 x 778 (Format_7 Mode_0) 516 x 778 (Format_7 Mode_1); 1032 x 388 (Format_7 Mode_2); 516 x 388 (Format_7 Mode_3)
Cell Size	4.65 µm x 4.65 µm
ADC	12 Bit
Data Path	8/10 Bit
Frame rates	3.75 Hz; 7.5 Hz; 15 Hz; 30 Hz*; up to 20 (30*) Hz in Format_7
Gain Control	Manual: 0–24 dB (0.035 dB/step); Auto gain (select. AOI)
Shutter Speed	20 …67.108.864 µs (~67s); Auto shutter (select. AOI)
External Trigger Shutter	Trigger_Mode_0, Trigger_Mode_1, Advanced feature: Trigger_Mode_15 (bulk); image transfer by command; Trigger delay
Internal FIFO-Memory	Up to 7 frames
# Look Up Tables	One, user programmable (10 Bit -> 8 Bit); Gamma (0.45)
Smart Functions	Real time shading correction; image sequencing, two configurable inputs, two configurable outputs, image mirror (L-R↔ R-L), binning, serial port (IIDC v. 1.31)
Transfer Rate	100 Mb/s, 200 Mb/s, 400 Mb/s
Digital Interface	IEEE 1394 IIDC v. 1.3
Power Requirements	DC 8 V – 36 V via IEEE 1394 cable or 12-pin HIROSE
Power Consumption	Less than 3 Watts (@ 12 V d.c.)
Dimensions	58 mm x 44 mm x 29 mm (L x W x H); without tripod and lens
Mass	<120 g (without lens)
Operating Temperature	+5 – +45 ° Celsius
Storage Temperature	-10 – +60 ° Celsius
Regulations	EN 55022, EN 61000,EN 55024,FCC Class A, DIN ISO 9022
Options	Removable IR-cut-filter, host adapter card, locking IEEE-1394 cable, API (FirePackage), TWAIN (WIA)- and WDM stream driver

Table 6: Specification MF-080B

The design and specifications for the products described above may change without notice.

*: Variant: F-080-30 fps only.

This variant offers higher speed at a slight expense in image quality.

4.6 MF-080C (-30 fps*)

Specification	
Image device	1/3 " (diag. 6 mm) type progressive scan SONY IT CCD
Effective Picture Elements	1032 (H) x 778 (V)@Raw8; 1032 (H) x 776 (V)@YUV
Lens Mount	C-mount: 17.526 mm (in air); ∅ 25.4 mm (32 T.P.I.) Mechanical Flange Back to filter distance: 8.2 mm, CS-mount on demand
Picture Sizes	1024 x 768 pixels (Format_1) supporting all smaller fixed formats; 1032 x 776 (Format_7 Mode_0); 1032 x 778 (Format_7 Mode_1);
Cell Size	4.65 µm x 4.65 µm
ADC	12 Bit
Color Modes	Raw8,YUV4:2:2,YUV4:1:1
Data Path	8 Bit
Frame rates	3.75 Hz; 7.5 Hz; 15 Hz; 30 Hz*; up to 20 (30*) Hz in Format_7 Raw8 (20 Hz at YUV4:1:1 /20 Hz YUV4:2:2)
Gain Control	Manual: 0–16 dB (0.035 dB/step); Auto gain (select. AOI)
Color Control	Hue (-40°… +40°) and saturation (0…200%)
White Balance	Manual (U/V); One_Push; Auto (select. AOI)
Shutter Speed	20 …67.108.864 µs (~67s); Auto shutter (select. AOI)
External Trigger Shutter	Trigger_Mode_0, Trigger_Mode_1, Advanced feature: Trigger_Mode_15 (bulk); image transfer by command; Trigger delay
Internal FIFO-Memory	Up to 7 frames
# Look Up Tables	One, user programmable (10 Bit -> 8 Bit); Gamma (0.45)
Smart Functions	Real time shading correction; image sequencing, two configurable inputs, two configurable outputs, image mirror (L-R↔ R-L), serial port (IIDC v. 1.31)
Transfer Rate	100 Mb/s, 200 Mb/s, 400 Mb/s
Digital Interface	IEEE 1394 IIDC v. 1.3
Power Requirements	DC 8 V – 36 V via IEEE 1394 cable or 12-pin HIROSE
Power Consumption	Less than 3 Watts (@ 12 V d.c.)
Dimensions	58 mm x 44 mm x 29 mm (L x W x H); without tripod and lens
Mass	<120 g (without lens)
Operating Temperature	+5 – +45 ° Celsius
Storage Temperature	-10 – +60 ° Celsius
Regulations	EN 55022, EN 61000, EN 55024, FCC Class A, DIN ISO 9022
Options	Host adapter card, locking IEEE-1394 cable, API (FirePackage), TWAIN (WIA)- and WDM stream driver

Table 7: Specification MF-080C

The design and specifications for the products described above may change without notice.
*: Variant: F-080C-30 fps (RAW-mode) only.

4.7 MF-145B2

Specification	
Image device	1/2 " (diag. 8 mm) type progressive scan SONY IT CCD
Effective Picture Elements	1392 (H) x 1040 (V)
Lens Mount	C-mount: 17.526 mm (in air); ∅ 25.4 mm (32 T.P.I.) Mechanical Flange Back to filter distance: 8.2 mm
Picture Sizes	Up to 1280 x 960 pixels (Format_2), supporting all smaller fixed formats; 1392 x 1040 pixels (Format_7 Mode_0); 696 x 1040 (Format_7 Mode_1); 1392 x 520 (Format_7 Mode_2); 696 x 520 (Format_7 Mode_3)
Cell Size	4.65 µm x 4.65 µm
ADC	12 Bit
Data Path	8/10 Bit
Frame rates	3.75 Hz; 7.5 Hz; 15 Hz*; up to 10 Hz (15 Hz)* in Format_7
Gain Control	Manual: 0–24 dB (0.035 dB/step); Auto gain (select. AOI)
Shutter Speed	20 …67.108.864 µs (~67s); Auto shutter (select. AOI)
External Trigger Shutter	Trigger_Mode_0, Trigger_Mode_1, Advanced feature: Trigger_Mode_15 (bulk); image transfer by command; Trigger delay
Internal FIFO-Memory	Up to 3 frames
# Look Up Tables	One, user programmable (10 Bit -> 8 Bit); Gamma (0.45)
Smart Functions	Real time shading correction; image sequencing, two configurable inputs, two configurable outputs, image mirror (L-R↔ R-L), binning, serial port (IIDC v. 1.31)
Transfer Rate	100 Mb/s, 200 Mb/s, 400 Mb/s
Digital Interface	IEEE 1394 IIDC v. 1.3
Power Requirements	DC 8 V – 36 V via IEEE 1394 cable or 12-pin HIROSE
Power Consumption	Less than 3 Watts (@ 12 V d.c.)
Dimensions	58 mm x 44 mm x 29 mm (L x W x H); without tripod and lens
Mass	<120 g (without lens)
Operating Temperature	+5 – +45 ° Celsius
Storage Temperature	-10 – +60 ° Celsius
Regulations	EN 55022, EN 61000, EN 55024, FCC Class A, DIN ISO 9022
Options	Removable IR-cut-filter, host adapter card, locking IEEE-1394 cable, API (FirePackage), TWAIN (WIA)- and WDM stream driver

Table 8: Specification MF145B2

The design and specifications for the products described above may change without notice.
*: Variant: F-145B2-15 only.
This variant offers higher speed at a slight expense in image quality.

4.8 MF-145C2

Specification	
Image device	1/2 " (diag. 8 mm) Type progressive scan SONY IT CCD
Effective Picture Elements	1392 (H) x 1040 (V)@Raw8; 1392 (H) x 1036 (V)@YUV
Lens Mount	C-mount: 17.526 mm (in air); ∅ 25.4 mm (32 T.P.I.) Mechanical Flange Back to filter distance: 8.2 mm
Picture Sizes	Up to 1280 x 960 pixels (Format_2) supporting all smaller fixed formats; 1392 x 1036 (Format_7 Mode_0); 1392 x 1040 (Format_7 Mode_1)
Cell Size	4.65 µm x 4.65 µm
ADC	12 Bit
Color Modes	Raw8, YUV4:2:2, YUV4:1:1
Data Path	8 Bit
Frame rates	3.75 Hz; 7.5 Hz, 15 Hz*; up to 10 Hz (15 Hz)* in Format_7
Gain Control	Manual: 0–16 dB (0.035 dB/step); Auto gain (select. AOI)
Color Control	Hue (-40°… +40°) and saturation (0…200%)
White Balance	Manual (U/V); One_Push; Auto (select. AOI)
Shutter Speed	20 …67.108.864 µs (~67s); Auto shutter (select. AOI)
External Trigger Shutter	Trigger_Mode_0, Trigger_Mode_1, Advanced feature: Trigger_Mode_15 (bulk); image transfer by command; Trigger delay
Internal FIFO-Memory	Up to 3 frames
# Look Up Tables	One, user programmable (10 Bit -> 8 Bit); Gamma (0.45)
Smart Functions	Real time shading correction; Image sequencing, two configurable inputs, two configurable outputs, image mirror (L-R↔ R-L), serial port (IIDC v. 1.31)
Transfer Rate	100 Mb/s, 200 Mb/s, 400 Mb/s
Digital Interface	IEEE 1394 IIDC v. 1.3
Power Requirements	DC 8 V – 36 V via IEEE 1394 cable or 12-pin HIROSE
Power Consumption	Less than 3 Watts (@ 12 V d.c.)
Dimensions	58 mm x 44 mm x 29 mm (L x W x H); without tripod and lens
Mass	<120 g (without lens)
Operating Temperature	+5 – +45 ° Celsius
Storage Temperature	-10 – +60 ° Celsius
Regulations	EN 55022, EN 61000, EN 55024, FCC Class A, DIN ISO 9022
Options	Host adapter card, locking IEEE-1394 cable, API (FirePackage), TWAIN (WIA) -and WDM stream driver

Table 9: Specification MF-145C2

The design and specifications for the products described above may change without notice.
*: Variant: F-145C2-15 only.
This variant offers higher speed at a slight expense in image quality.

4.9 F-131B

Specification	
Image device	2/3 " (diag. 11 mm) Type global shutter CMOS sensor
Effective Picture Elements	1280 (H) x 1024 (V)
Lens Mount	C-mount: 17.526 mm (in air); ∅ 25.4 mm (32 T.P.I.) Mechanical Flange Back to filter distance: 8.2 mm
Picture Sizes	Up to 1280 x 960 pixels (Format_2), supporting all smaller fixed formats; 1280 x 1024 pixels (Format_7 Mode_0); 640 x 1024 pixels (Format_7 Mode_1, sub-sampling) 1280 x 512 pixels (Format_7 Mode_2, sub-sampling) 640 x 512 pixels (Format_7 Mode_3, sub-sampling)
Cell Size	6.7 µm x 6.7 µm
ADC	10 Bit
Data Path	8 Bit
Frame rates	3.75 Hz; 7,5 Hz; 15 Hz; up to 25 Hz in Format_7; 30 Hz @ SVGA and smaller
Gain Control	Manual: 0– 16 dB (13 x 1.25 dB)
Shutter Speed	20 µs- 67s; Auto shutter (select. AOI)
External Trigger Shutter	Trigger_Mode_0, Trigger_Mode_1, Advanced feature: Trigger_Mode_15 (bulk); image transfer by command; Trigger delay
Internal FIFO-Memory	Up to 4 frames
# Look Up Tables	One, user programmable (10 Bit -> 8 Bit); separate Gamma (0.45) LUT
Smart Functions	Dark signal non uniformity (DSNU) correction, Real time shading correction; two configurable inputs, two configurable outputs, high dynamic range (HDR) mode, image mirror (L-R↔ R-L), sub-sampling, serial port (IIDC v. 1.31)
Transfer Rate	100 Mb/s, 200 Mb/s, 400 Mb/s
Digital Interface	IEEE 1394 IIDC v. 1.3
Power Requirements	DC 8 V – 36 V via IEEE 1394 cable or 12-pin HIROSE
Power Consumption	Less than 3 Watts (@ 12 V d.c.)
Dimensions	58 mm x 44 mm x 29 mm (L x W x H); without tripod and lens
Mass	<120 g (without lens)
Operating Temperature	+5 – +45 ° Celsius
Storage Temperature	-10 – +60 ° Celsius
Regulations	EN 55022, EN 61000, EN 55024, FCC Class A, DIN ISO 9022
Options	Host adapter card, locking IEEE-1394 cable, API (FirePackage), TWAIN (WIA) -and WDM stream driver

Table 10: Specification MF-131B

The design and specifications for the products described above may change without notice.

4.10 F-131C

Specification	
Image device	2/3 " (diag. 11 mm) Type global shutter CMOS sensor
Effective Picture Elements	1280 (H) x 1024 (V)
Lens Mount	C-mount: 17.526 mm (in air); ∅ 25.4 mm (32 T.P.I.) Mechanical Flange Back to filter distance: 8.2 mm
Picture Sizes	Up to 1280 x 960 pixels (Format_2), supporting all smaller fixed formats; 1280 x 1024 pixels (Format_7) 640 x 1024 pixels (Format_7 Mode_1, sub-sampling) 1280 x 512 pixels (Format_7 Mode_2, sub-sampling) 640 x 512 pixels (Format_7 Mode_3, sub-sampling)
Cell Size	6.7 µm x 6.7 µm
ADC	10 Bit
Data Path	8 Bit
Frame rates	3.75 Hz; 7,5 Hz; 15 Hz; up to 25 Hz in Format_7 Raw8; (12 fps @YUV4:2:2; 17 fps @YUV4:1:1)
Gain Control	Manual: 0–16 dB (13 x 1.25 dB))
White Balance	Manual (U/V); One_Push; Auto (select. AOI)
Shutter Speed	20 µs- 67s; Auto shutter (select. AOI)
External Trigger Shutter	Trigger_Mode_0, Trigger_Mode_1, Advanced feature: Trigger_Mode_15 (bulk); image transfer by command; Trigger delay
Internal FIFO-Memory	Up to 4 frames
# Look Up Tables	One, user programmable (10 Bit -> 8 Bit); separate Gamma (0.45) LUT
Smart Functions	Dark signal non uniformity (DSNU) correction, Real time shading correction; two configurable inputs, two configurable outputs, high dynamic range (HDR) mode, image mirror (L-R↔ R-L), sub-sampling, serial port (IIDC v. 1.31)
Transfer Rate	100 Mb/s, 200 Mb/s, 400 Mb/s
Digital Interface	IEEE 1394 IIDC v. 1.3
Power Requirements	DC 8 V – 36 V via IEEE 1394 cable or 12-pin HIROSE
Power Consumption	Less than 3 Watts (@ 12 V d.c.)
Dimensions	58 mm x 44 mm x 29 mm (L x W x H); without tripod and lens
Mass	<120 g (without lens)
Operating Temperature	+5 – +45 ° Celsius
Storage Temperature	-10 – +60 ° Celsius
Regulations	EN 55022, EN 61000, EN 55024, FCC Class A, DIN ISO 9022
Options	Host adapter card, locking IEEE-1394 cable, API (FirePackage), TWAIN (WIA) -and WDM stream driver

Table 11: Specification MF-131C

The design and specifications for the products described above may change without notice.

4.11 Spectral sensitivity



Figure 2: Spectral sensitivity of MF-033B without cut filter and optics.



Figure 3: Spectral sensitivity of MF-033C without cut filter and optics



Figure 4: Spectral sensitivity of MF-046B without cut filter and optics.



Figure 5: Spectral sensitivity of MF-046C without cut filter and optics.



Figure 6: Spectral sensitivity of MF-080B without cut filter and optics



Figure 7: Spectral sensitivity of MF-080C without cut filter and optics.



Figure 8: Spectral sensitivity of MF-145B2 without cut filter and optics



Figure 9: Spectral sensitivity of MF-145C2 without cut filter and optics



Figure 10: Spectral sensitivity of MF-131B without cut filter and optics



Figure 11: Spectral sensitivity of MF-131C without cut filter and optics

5 Quick start

To attach an IEEE-1394 camera to a PC or laptop, the target machine must be equipped with an IEEE-1394 port and have the appropriate driver and software installed. This IEEE-1394 port is already present in many modern PCs and laptops. Should this not be the case, you can upgrade by installing one or more IEEE-1394 ports in the form of a card for the PCI slot, or as a PC card (PCMCIA) for the PC card slot. AVT offers a wide range of adaptors for different requirements.

After starting the operating system, the plug and play mechanism on the PC should recognize the new hardware and prompt you to install the IEEE-1394 driver from Microsoft.
AVT supplies since 3Q/2004 an additional TWAIN (VIA) drivers and WDM stream software to integrate the images into third party software which has these interfaces.
Alternatively the FirePackage API SDK can be used. This replaces the MS-IEEE-1394 driver with the driver produced by the company Intek.

A more detailed description for these installation routines can be found in the "FirePackage" software manuals.

The latter driver works in conjunction with the "SmartView" program. This viewer enables not only quick and easy access to all integrated IEEE-1394 ports and all the connected IEEE-1394 cameras, but also supports almost all smart features of the AVT Marlin family of cameras.
After selecting a card and a camera an image of this camera will immediately displayed.

In the *Edit settings* dialog box you can adjust the settings for the standard registers according to the IIDC specification, e.g. exposure time or gain.
Direct access to the register level, e.g. to activate the advanced features of the camera, is carried out via the *Direct access* dialog box.
We refer to a separate description of this viewer and its capabilities.



Figure 12: SmartView

6 Camera dimensions

6.1 Marlin standard housing



Body size:	58 mm x 44 mm x 29 mm (l x w x h)
Weight:	120 g (without lens)

Figure 13: Camera dimensions

6.2 Marlin W90

This version has the sensor tilted by 90 degrees clockwise, so that it views upwards.



Figure 14: Marlin W90

6.3 Marlin W90 S90

This version has the sensor tilted by 90 degrees clockwise, so that it views upwards and additionally rotated by 90 degrees clockwise.



Figure 15: Marlin W90 S90

6.4 Marlin W270

This version has the sensor tilted by 270 degrees clockwise, so that it views downwards.
Consult your dealer, if you have inquiries for this version.



Figure 16: Marlin W270

6.5 Marlin W270 S90

This version has the sensor tilted by 270 degrees clockwise, so that it views downwards. Additionally the sensor is tilted by 90 degrees clockwise.



Figure 17: Marlin W270 S90

6.6 Tripod adapter



Figure 18: Tripod dimensions

7 Camera interfaces

In addition to the two status LEDs, there are two jacks located at the rear of the camera. The 12-pin HiRose plug provides different control inputs and output lines. The IEEE-1394 connector with lock mechanism provides access to the IEEE-1394 bus and thus makes it possible to control the camera and output frames.



Figure 19: Rear view of camera

7.1 IEEE-1394 port pin assignment

The IEEE-1394 plug is designed for industrial use and has the following pin assignment as per specification:



Figure 20: IEEE-1394 connector

Pin	Signal	Pin	Signal
1	Cable power	4	TPB+
2	Cable GND	5	TPA-
3	TPB-	6	TPA+

Table 12: IEEE-1394 pin assignment

Cables with latching connectors on one or both sides can be used and are available with lengths of 4.5m or 10m. Ask your local dealer for more details.

7.2 HiRose jack pin assignment

The HiRose plug is also designed for industrial use and in addition to providing access to the inputs and outputs on the camera, it also provides a serial interface for e.g. the firmware update. The following diagram shows the pinning as viewed in pin direction.
AVT supplies suitable I/O cables at different lengths (up to 10m) upon request.



Figure 21: HiRose connector pin assignment

Pin	Signal	Use	Pin	Signal	Use
1	External GND	GND for RS232 only	7	GPInput GND	Common GND for inputs
2	Power IN (CCD-models only)		8	RS232 RxD	
3			9	RS232 TxD	
4	GPInput 1 (default trigger)	TTL, Edge, progr.	10	OutVCC	Common VCC for outputs
5			11	GPInput 2	TTL
6	GP Output 1 (default IntEna)	Open emitter	12	GPOutput 2	Open emitter

Table 13: HiRose pinning

ⓘ Pin 1 is internally NOT bridged with pin 7 to avoid ground noise to be induced into the camera and prevent ground loops. Use pin 1 only when you want to connect to the serial interface of the camera in combination with pin 8 and 9.

7.3 Status LEDs

On LED

The green power LED indicates that the camera is being supplied with sufficient voltage and is ready for operation.

Status LED (yellow)

The following states are displayed via the LED:

Com	asynchronous and isochronous data transmission active (indicated asynchronously to transmission over the 1394 bus)
Trg	LED off – waiting for external trigger LED on – receiving external trigger

Table 14: LED indication

Blink codes are used to signal warnings or error states:

Class S1 / Error code S2	Warning 1 blink	DCAM 2 blinks	MISC 3 blinks	FPGA 4 blinks	Stack 5 blinks
FPGA Boot error				1-5 blinks	
Stack setup					1 blink
Stack start					2 blinks
No FLASH object			1 blink		
No DCAM object		1 blink			
Register mapping		2 blinks			
VMode_ERROR_STATUS	1 blink				
FORMAT_7_ERROR_1	2 blinks				
FORMAT_7_ERROR_2	3 blinks				

Table 15: Error Codes

The longer OFF-time of 3.5 sec signals the beginning of a new class period. The error codes follow after a shorter OFF-time of 1.5 sec.

Example: 3.5 sec ➔ one blink ➔ 1.5 sec ➔ 2 blinks

indicates a warning: Format_7_Error_1

7.4 Operating the camera:

Power for the camera is supplied either via the FireWire™ bus or the HiRose conector's pin 2 (CCD-models only).

The input voltage must be within the following range:
Vcc min.: +8 V
Vcc max.: +36 V

ⓘ An input voltage of 12 V is recommended to make most efficient use of the camera.
ⓘ As mentioned above for the CCD-models: The HiRose connector supplies power via a diode to the camera. This means that there is no power out at pin 2, when the camera is powered via the bus. Consult the factory, if you need power output at this pin instead of power in.

7.5 Control and video data signals

The camera has 2 inputs and 2 outputs. These can be configured by software. The different modes are described below.

7.5.1 Inputs

All inputs have been implemented as shown on the diagram below.



Figure 22: Input schematics

Flux voltage from LED type 1.5 V at 10 mA		Cycle delay of the optical coupler	
min. on-current:	5 mA		
max. off-current:	0.25 mA		
max. input current:	15 mA		
min. pulse width	2.2 µs	tpdHL: tpdLH:	2275 ns 2290 ns

Table 16: Input characteristics

The inputs can be connected directly to +5 V. If a higher voltage is used, an external resistor must be placed in series. Use @+12 V a 820 Ω and @+24 V a 2.2 kΩ resistor.

ⓘ Voltages above +45 V may damage the optical coupler

The optical coupler inverts all input signals. Polarity is controlled via the IO_INP_CTRL1..2 register.



Figure 23: Input block diagram

7.5.1.1 Triggers

All inputs configured as triggers are linked by AND. If several inputs are being used as triggers, a high signal must be present on all inputs in order to generate a trigger signal. The polarity for each signal can be set separately via the inverting inputs. The camera must be set to "external triggering" to trigger image capture by the trigger signal.
All input and output signals running over the HiRose plug are controlled by an advanced feature register.

Register	Name	Field	Bit	Description
0xF1000300	IO_INP_CTRL1	Presence_Inq	[0]	Indicates presence of this feature (read only)
		---	[1..6]	
		Polarity	[7]	0: low active, 1: high active
		---	[8..10]	
		InputMode	[11..15]	Mode
		---	[16..30]	
		PinState	[31]	RD: Current state of pin
0xF1000304	IO_INP_CTRL2	Same as IO_INP_CTRL1		

Table 17: Input configuration register

IO_INP_CTRL 1-2

The *Polarity* flag determines whether the input is low active (0) or high active (1). The *input mode* can be seen in the following table. The *PinState* flag is used to query the current status of the input.
For inputs the *PinState* bit refers to the inverted output side of the optical coupler. This signals that an open input sets the *PinState* bit to "1".

ID	Mode	Default
0x00	Off	
0x01	reserved	
0x02	Trigger input	Input 1
0x03	reserved	
0x04	reserved	
0x05	tbd (SPI external DCLK)	
0x06..0x0F	reserved	
0x10..0x1F	reserved	

Table 18: Input routing

7.5.1.2 Trigger delay

Since firmware version 2.03, the cameras feature various ways to delay image capture based on external trigger.
With 1V31 of IIDC spec. there is a standard CSR at Register F0F00534/834h to control a delay up to FFFh * timebase value. The following table explains the Inquiry register and the meaning of the various bits.

Register	Name	Field	Bit	Description
0xF0F00534	TRIGGER_DELAY_INQUIRY	Presence_Inq	[0]	Indicates presence of this feature (read only)
		Abs_Control_Inq	[1]	Capability of control with absolute value
		-	[2]	Reserved
		One_Push_Inq	[3]	One Push auto mode (Controlled automatically by the camera once)
		Readout_Inq	[4]	Capability of reading out the value of this feature
		ON_OFF	[5]	Capability of switching this feature ON and OFF
		Auto_Inq	[6]	Auto Mode (Controlled automatically by the camera)
		Manual_Inq	[7]	Manual Mode (Controlled by user)
		Min_Value	[8..19]	Min. value for this feature
		Max_Value	[20..31]	Max. value for this feature

Table 19: Trigger_Delay_Inquiry register

Register	Name	Field	Bit	Description
0xF0F00834	TRIGGER_DELAY	Presence_Inq	[0]	Presence of this feature: 0:N/A; 1:Available
		Abs_Control	[1]	Absolute value control 0: Control with value in the value field 1: Control with value in the absolute value CSR If this bit= 1 the value in the value field has to be ignored
		-	[2..5]	Reserved
		ON_OFF	[6]	Write ON or OFF this feature, ON=1 Read: Status of the feature; OFF=0
		-	[7..19]	Reserved
		Value	[20..31]	Value

Table 20: Trigger Delay CSR

In addition, the cameras have an advanced register which allows to even more precisely delay the image capture after receiving a hardware trigger.

Trigger delay advanced register

Register	Name	Field	Bit	Description
0xF1000400	TRIGGER_DELAY	Presence_Inq	[0]	Indicates presence of this feature (read only)
		---	[1..5]	-
		ON_OFF	[6]	Trigger delay on/off
		---	[7..10]	-
		DelayTime	[11..31]	Delay time in µs

Table 21: Trigger Delay Advanced CSR

The advanced register allows to delay the start of the integration by max. 2^{21} µs, which is max. 2.1s after a trigger edge was detected.

ⓘ Switching trigger delay to ON also switches external Trigger_Mode_0 to ON.

ⓘ This feature works with external Trigger_Mode_0 only.

7.5.2 Outputs

The camera has 2 non-inverting outputs with open emitters. These are shown in the following diagram:

Max. emitter current 500 mA
Max. collector emitter voltage 45 V

- Voltage above +45 V may damage the optical coupler.
- The output connection is different to the AVT Dolphin series to achieve higher output swing.
- Depending on the voltage applied at OutVCC and the type of input which you want to drive, it may be necessary to switch an external resistor in series between GPOutl and ground. The use of 1 kΩ@ 5V or 2.4 kΩ@ 12V can be recommended. Typical delay is not more than 40 µs.



Figure 24: Output schematics

Output features are configured by software. Any signal can be placed on any output.
The main features of output signals are described below:

IntEna (Integration Enable) Signal
This signal displays the time in which exposure was made. By using a register this output can be delayed by up to 1.05 seconds.
Fval (Frame valid) Signal
This feature signals readout from the sensor. This signal Fval follows IntEna.
Busy Signal
This indicator appears when the exposure is being made; the sensor is being read from or data transmission is active. The camera is busy.



Figure 25: Output block diagram

IO_OUTP_CTRL 1-2

The outputs are controlled via two advanced feature registers.

The *Polarity* flag determines whether the output is active low (0) or active high (1). The *output mode* can be viewed in the table below. The current status of the output can be queried and set via the *PinState* flag.

From firmware 2.03 onwards it is possible to read back the status of an output pin regardless of the output mode. This allows for example the host computer to determine if the camera is busy by simply polling the BUSY output.

Register	Name	Field	Bit	Description
0xF1000320	IO_OUTP_CTRL1	Presence_Inq	[0]	Indicates presence of this feature (read only)
		---	[1..6]	-
		Polarity	[7]	0: active low, 1: active high (inverting)
		---	[8..10]	
		Output mode	[11..15]	Mode
		---	[16..30]	
		PinState	[31]	RD: Current state of pin WR: New state of pin
0xF1000324	IO_OUTP_CTRL2	Same as IO_OUTP_CTRL1		

Table 22: Output configuration register

Output mode

ID	Mode	Default
0x00	Off	
0x01	Output state follows 'PinState' bit	
0x02	Integration enable	Output 1
0x04	reserved	
0x05	reserved	
0x06	FrameValid	
0x07	Busy	Output 2
0x08	Follow corresponding input (Inp1 • Out1, Inp2 • Out2, …)	
0x09..0x0F	reserved	
0x10..0x1F	reserved	

Table 23: Output routing

The "Polarity" setting refers to the input side of the optical coupler output, "PinState 0" switches off the output transistor and produces a low level over the resistor connected from the output to ground.

The following diagram illustrates the dependencies of the various output signals.



Figure 26: Output Impulse Diagram

- Note that the polarity of the signals can be changed.
- Firing a new trigger while IntEna is still active can result in image corruption due to double exposure occurring.
- Note that trigger delay in fact delays the image capture whereas the IntEna_Delay only delays the leading edge of the IntEna output signal but does not delay the image capture.

- As mentioned before, it is possible to set the outputs by software. Doing so, the achievable maximum frequency is strongly dependent on individual software capabilities. As a rule of thumb, the camera itself will limit the toggle frequency to not more than 700 Hz.

7.6 Pixel data

Pixel data are transmitted as isochronous data packets in accordance with the 1394 interface described in IIDC v. 1.3. The first packet of a frame is identified by the "1" in the sync bit (sy) of the packet header.



Isochronous Data Block Packet Format

Table 24: Isochronous data block packet format: Source: IIDC v. 1.3 specification

The video data for each pixel are outputted in either 8or 10-bit format. Each pixel has a range of 256 or 1024 shades of gray. The digital value 0 is black and 255 or 1023 is white. In 16 bit mode the data output is MSB aligned.

The following table provides a description of the video data format for the different modes. (Source: IIDC v. 1.3 specification)

<YUV (4: 2: 2) format >

U-(K+0)	Y-(K+0)	V-(K+0)	Y-(K+1)
U-(K+2)	Y-(K+2)	V-(K+2)	Y-(K+3)
U-(K+4)	Y-(K+4)	V-(K+4)	Y-(K+5)
U-(K+Pn-6)	Y-(K+Pn-6)	V-(K+Pn-6)	Y-(K+Pn-5)
U-(K+Pn-4)	Y-(K+Pn-4)	V-(K+Pn-4)	Y-(K+Pn-3)
U-(K+Pn-2)	Y-(K+Pn-2)	V-(K+Pn-2)	Y-(K+Pn-1)

<YUV (4: 1: 1) format >

U-(K+0)	Y-(K+0)	Y-(K+1)	V-(K+0)
Y-(K+2)	Y-(K+3)	U-(K+4)	Y-(K+4)
Y-(K+5)	V-(K+4)	Y-(K+6)	Y-(K+7)
U-(K+Pn-8)	Y-(K+Pn-8)	Y-(K+Pn-7)	V-(K+Pn-8)
Y-(K+Pn-6)	Y-(K+Pn-5)	U-(K+Pn-4)	Y-(K+Pn-4)
Y-(K+Pn-3)	V-(K+Pn-4)	Y-(K+Pn-2)	Y-(K+Pn-1)

Table 25: YUV 4:2:2 and YUV 4:1:1 format: Source: IIDC v. 1.3 specification

<Y (Mono) format >

Y-(K+0)	Y-(K+1)	Y-(K+2)	Y-(K+3)
Y-(K+4)	Y-(K+5)	Y-(K+6)	Y-(K+7)
Y-(K+Pn-8)	Y-(K+Pn-7)	Y-(K+Pn-6)	Y-(K+Pn-5)
Y-(K+Pn-4)	Y-(K+Pn-3)	Y-(K+Pn-2)	Y-(K+Pn-1)

< Y (Mono16) format >

High byte	Low byte

Y-(K+0)	Y-(K+1)
Y-(K+2)	Y-(K+3)
Y-(K+Pn-4)	Y-(K+Pn-3)
Y-(K+Pn-2)	Y-(K+Pn-1)

Table 26: Y8 and Y16 format: Source: IIDC v. 1.3 specification

<Y, R, G, B>

Each component has 8bit data. The data type is "Unsigned Char".

	Signal level (Decimal)	Data (Hexadecimal)
Highest	255	0xFF
	254	0xFE
	:	:
	1	0x01
Lowest	0	0x00

<U, V>

Each component has 8bit data. The data type is "Straight Binary".

	Signal level (Decimal)	Data (Hexadecimal)
Highest (+)	127	0xFF
	126	0xFE
	:	:
	1	0x81
Lowest	0	0x80
	-1	0x7F
	:	:
	-127	0x01
Highest (-)	-128	0x00

< Y(Mono16) >

Y component has 16bit data. The data type is "Unsigned Short (big-endian)".

Y	Signal level (Decimal)	Data (Hexadecimal)
Highest	65535	0xFFFF
	65534	0xFFFE
	:	:
	1	0x0001
Lowest	0	0x0000

Table 27: Data structure: Source: IIDC v. 1.3 specification

8 Description of the data path

8.1 Block diagrams of the cameras

The following diagrams illustrate the data flow and the bit resolution of image data after being read from the CCD or CMOS sensor chip in the camera. The individual blocks are described in more detail in the following paragraphs.

8.1.1 Black and white cameras:



Figure 27: Block diagram b/w camera

8.1.2 Color cameras:



Figure 28: Block diagram color camera

8.2 Sensor

The Marlin family is equipped with various sensor types and resolutions. Both CCD and CMOS types are available in color and monochrome.

The following table provides an overview:

Model	Techn.	Manu-facturer	Sensor Type	Sensor Size	Microlens	Chip Size [mm]	Pixel Size [µm]	Eff. Pixels
MF-033B	CCD	SONY	ICX-414AL	½" (8 mm)	Yes, HAD	7.48 x 6.15	9.9 x 9.9	659 x 494
MF-033C	CCD	SONY	ICX-414AQ	½" (8 mm)	Yes, HAD	7.48 x 6.15	9.9 x 9.9	659 x 494
MF-046B	CCD	SONY	ICX-415AL	½" (8 mm)	Yes, HAD	7,48 x 6.15	8.3 x 8.3	782 x 582
MF-046C	CCD	SONY	ICX-415AQ	½" (8 mm)	Yes, HAD	7.48 x 6.15	8.3 x 8.3	782 x 582
MF-080B	CCD	SONY	ICX-204AL	1/3" (6 mm)	Yes, HAD	5.8 x 4.92	4.65 x 4.65	1034 x 779
MF-080C	CCD	SONY	ICX-204AK	1/3" (6 mm)	Yes, HAD	5.8 x 4.92	4.65 x 4.65	1034 x 779
MF-145B2	CCD	SONY	ICX-205AL	½" (8 mm)	Yes, HAD	7.6 x 6.2	4.65 x 4.65	1392 x1040
MF-145C2	CCD	SONY	ICX-205AK	½" (8 mm)	Yes, HAD	7.6 x 6.2	4.65 x 4.65	1392 x1040
MF-131B	CMOS	FillFactory	IBIS5A	2/3"(11mm)	Not needed	8.6 x 6.9	6.7 x 6.7	1280 x1024
MF-131C	CMOS	FillFactory	IBIS5A	2/3"(11mm)	Not needed	8.6 x 6.9	6.7 x 6.7	1280 x1024

Table 28: Sensor data

8.2.1 IBIS5A multiple slope (High Dynamic Range mode)

The MF-131 sensor has a high dynamic range of about 60 dB. This can be extended to almost 100 dB by switching to a special mode.
This mode is called dual (in the case of rolling shutter) or multiple slope mode (in the case of global shutter).
The following diagram, taken from FillFactory's application notes, explains the functionality.



Figure 29: Multiple slope (high dynamic range) pixel charge as a function of time

The colored lines represent the analogue signal on the photodiode which decreases as a result of exposure. The slope is determined by the amount of light at each pixel (the more light, the steeper the slope). When the pixels reach the saturation level, the analogue signal will no longer change despite further light exposure. As shown in the diagram, without any dual or multiple slope pulse, pixels P3' and P4' reach saturation before the sample moment of the analogue values.

When dual slope is enabled, a second reset pulse will be given (blue line) at a certain time before the end of the integration time.
This dual slope reset pulse resets the analogue signal of the pixels below the dual slope reset level to this level. After the reset, the analogue signal starts to decrease with the same slope as before (pink P3 and yellow P4 lines).
This introduces a knee-point in the exposure function.
If the dual slope reset pulse is placed at the end of the integration time (90% for instance), the analogue signal which would have normally reached the saturation level is no longer saturated at read out. This effect increases the optical dynamic range of the sensor.

It is important to notice that pixel signals above the dual slope reset level will be left unaffected (green P1 and green P2).

The Marlin F131 offers up to three knee-points when in global shutter mode. This functionality is controlled via the following registers.

Register	Name	Field	Bit	Description
0xF1000280	HDR_CONTROL	Presence_Inq	[0]	Indicates presence of this feature (read only)
		---	[1..5]	
		ON_OFF	[6]	Enable/disable HDR mode
		---	[7..19]	
		MaxKneePoints	[20…23]	R: Number of knee-points possible in this mode
		---	[24..27]	
		KneePoints	[28..31]	W: Number of active knee-points
0xF1000284	KNEEPOINT_1	---	[0..15]	
0xF1000284		Kneepoint1	[16..31]	R/W: Time in µs
0xF1000288	KNEEPOINT_2	---	[0..15]	
0xF1000288		Kneepoint2	[16..31]	R/W: Time in µs
0xF100028C	KNEEPOINT_3	---	[0..15]	
0xF100028C		Kneepoint3	[16..31]	R/W: Time in µs

Table 29: High dynamic range configuration register

ⓘ It is recommended that knee-points be adjusted to 10 %, 5 % and 2.5 % of the total exposure or shutter time being applied at the end of the exposure.

Example:

Adjust image so that the dark areas are well displayed. Calculate the used shutter time. Activate HDR-Mode.
Assuming shutter time to be 40 ms = 40,000 µs:

⇨ Kneepoint_1 = 10 % * 40,000 µs = 4,000 µs = 0xFA0
⇨ Kneepoint_2 = 5 % * 40,000 µs = 2,000 µs = 0x7D0
⇨ Kneepoint_3 = 2.5 % * 40,000 µs = 1,000 µs = 0x3E8

The following needs to be written:
HDR_CONTROL: (Adress: 0xF1000280) 0x02000003
KNEEPOINT_1: (Adress: 0xF1000284) 0x00000FA0
KNEEPOINT_2: (Adress: 0xF1000288) 0x000007D0
KNEEPOINT_3: (Adress: 0xF100028C) 0x000003E8
For further tuning, readjust KNEEPOINT_X but maintain ratio KNEEPOINT_1 > KNEEPOINT_2 > KNEEPOINT_3.

The figure below, taken from the sensor's data sheet, illustrates the nonlinear behavior of the photo response curve in dual slope mode.



Figure 30: IBIS5A nonlinear photo response curve with two slopes

8.3 White balance

The color cameras have both manual and automatic white balance. White balance is applied so that non-colored image parts are displayed non-colored.
White balance does not use the so called PxGA® (Pixel Gain Amplifier) of the analog front end (AFE) but a digital representation in the FPGA in order to modify the gain of the two channels with lower output by +9.5dB (in 106 steps) relative to the channel with highest output.
The following screenshot is taken from the datasheet of the AFE and illustrates the details:
The analog color signal, coming in pulse amplitude modulation from the sensor is in the form of the BAYER™ color pattern sequence. It is initially processed in the CDS (correlated double sampler) then bypasses the PxGA before further amplification and digitization.



Figure 31: Block diagram of AFE (Source: Analog Devices)

From the user's point, the white balance settings are made in register 80Ch of IIDC v. 1.3. This register is described in more detail on the next page.

Register	Name	Field	Bit	Description
0xF0F0080C	WHITE_BALANCE	Presence_Inq	[0]	Presence of this feature: 0: N/A; 1: Available
		Abs_Control	[1]	Absolute value control 0: Control with value in the value field 1: Control with value in the absolute value CSR If this bit= 1 the value in the value field has to be ignored
		-	[2..4]	Reserved
		One_Push	[5]	Write: Set Bit high to start Read: Status of the feature: Bit high: WIP, Bit low: Ready
		ON_OFF	[6]	Write ON or OFF this feature, ON=1 Read: Status of the feature; OFF=0
		A_M_MODE	[7]	Set bit high for Auto feature Read for Mode; 0= MANUAL; 1= AUTO
		U/B_Value	[8..19]	U/B value; Write if not Auto; Read
		V/R_Value	[20..31]	V/R Value

Table 30: White balance register

The values in the *U/B_Value* field produce changes from green to blue; the *V/R_Value* field from green to red as illustrated below.



Figure 32: U/V slider range

8.3.1 One Push automatic white balance

It is activated by setting the "One Push" bit in the WHITE_BALANCE register (see WHITE-BALANCE). The camera automatically generates frames, based on the current settings of all registers (GAIN, OFFSET, SHUTTER, etc.).
For white balance, in total six frames are processed and a grid of at least 300 samples is equally spread over the work area. This area can be the field of view or a subset of it. The R-G-B component values of the samples are added and are used as actual values for both the One Push and the automatic white balance.
This feature uses the assumption that the R-G-B component sums of the samples shall be equal; i.e., it assumes that the average of the sampled grid pixels is to be monochrome.

The following ancillary conditions should be observed for successful white balance:

- There are no stringent or special requirements on the image content, it requires only the presence of monochrome pixels in the image.
- Automatic white balance can be started both during active image capture and when the camera is in idle state.

If the image capture is active (e.g. "IsoEnable" set in register 614h), the frames used by the camera for white balance are also outputted on the 1394 bus. Any previously active image capture is restarted after the completion of white balance.
Automatic white balance can also be enabled by using an external trigger. However, if there is a pause of >10 seconds between capturing individual frames this process is aborted.
The following flow diagram illustrates the automatic white balance sequence.


Pause Image Capture
Capture Image via One_shot
Repeat Steps six Times
Calculate and set Correction Values
Restart Image Capture if necessary

Figure 33: Automatic white balance sequence

Finally, the calculated correction values can be read from the WHITE_BALANCE register 80Ch.

8.3.2 Automatic white balance

There is also an Auto white balance feature realized, which continuously optimizes the color characteristics of the image.
As a reference, it uses a grid of at least 300 samples equally spread over the area of interest or a fraction of it. The position and size of the control area (Auto_Function_AOI) can be set via the following advanced registers.

Register	Name	Field	Bit	Description
0xF1000390	AUTOFNC_AOI	Presence_Inq	[0]	Indicates presence of this feature (read only)
			[1..3]	-
		ShowWorkArea	[4]	Show work area
			[5]	-
		ON_OFF	[6]	Enable/Disable AOI
			[7..31]	-
0xF1000394	AF_AREA_POSITION	Left	[0..15]	work area position
		Top	[16..31]	
0xF1000398	AF_AREA_SIZE	Width	[0..15]	work area size
		Height	[16..31]	

Table 31: Advanced register: AUTOFNC_AOI

AUTOFNC_AOI affects the auto shutter, auto gain and auto white balance features and is independent of the Format7 AOI settings. If this feature is switched off the work area position and size follow the current active image size.

The possible increment of this work-area position and size is 128 pixels. The camera automatically adjusts the settings to allowed values (see below for valid values):

`Left, Top`	0, 128, 256, 384, 512, 768, 1024...
`Width, Height`	128, 256, 384, 512, 768, 1024...

Table 32: Legal values for AF_AREA_SIZE

Due to the fact that the active image size might not be dividable by 128 without a remainder, the auto function AOI work-area size might be greater.
This allows for the positioning of the work-area to be at the bottom of the active image.
E.g. if the active image size is 640 x 480 pixel the camera accepts a maximum of 640 x 512 pixel as the auto function AOI work area (if the control area position is 0:0).

Another case is for outdoor applications: the sky will be excluded from the generation of the reference levels.

ⓘ If the adjustment fails and the work area size and/or position becomes invalid this feature is automatically switched off – make sure to read back the `ON_OFF` flag if this feature doesn't work as expected.

Within this area, the R-G-B component values of the samples are added and used as actual values for the feedback.

The following drawing illustrates the AUTOFNC_AOI settings in greater detail.



Figure 34: AUTOFNC_AOI positioning

The algorithm bases on the assumption that the R-G-B component sums of the samples shall be equal, i.e., it assumes that the mean of the sampled grid pixels is to be monochrome.

8.4 Manual gain

As shown in figure 29, all cameras are equipped with a gain setting, allowing the gain to be "manually" adjusted on the fly by means of a simple command register write.
The following ranges can be used when manually setting the gain for the analog video signal:

Type	Range	Range in dB
B/W CCD-cameras	0 ... 680	0 ... 24 dB
Color CCD-cameras	0 ... 450	0 ... 16 dB
CMOS camera	1 ... 14	0 ... 16 dB

Table 33: Manual gain range of the various Marlin types

The increment length is ~0.0354 dB/step for CCD-models and 1.25 dB for CMOS.

ⓘ Setting the gain does not change the offset (black value) for CCD models.
ⓘ A higher gain also produces greater image noise. This reduces image quality. For this reason, try first to increase the brightness, using the aperture of the camera optics and/or longer shutter settings.

8.5 Auto gain

In combination with auto white balance, all CCD- models are equipped with auto gain feature.
When enabled auto gain adjusts the gain within the default gain limits (see table 33) or within the limits set in advanced register F1000370h in order to reach the brightness set in auto exposure register as reference. Increasing the auto exposure value increases the average brightness in the image and vice versa.
The applied algorithm uses a proportional plus integral controller (PI controller) to achieve minimum delay with zero overshot.
The following table shows both the gain and auto exposure CSR.

Register	Name	Field	Bit	Description
0xF0F00820	GAIN	Presence_Inq	[0]	Presence of this feature: 0: N/A; 1: Available
		Abs_Control	[1]	Absolute value control 0: Control with value in the value field 1: Control with value in the absolute value CSR If this bit= 1 the

				value in the value field has to be ignored
		-	[2..4]	Reserved
		One_Push	[5]	Write: Set Bit high to start Read: Status of the feature: Bit high: WIP, Bit low: Ready
		ON_OFF	[6]	Write ON or OFF this feature, ON=1 Read: Status of the feature; OFF=0
		A_M_MODE	[7]	Set bit high for Auto feature Read for Mode; 0= MANUAL; 1= AUTO
		-	[8..19]	reserved
		Value	[20..31]	Read/Write Value; this field is ignored when writing the value in Auto or OFF mode; if readout capability is not available reading this field has no meaning
Register	**Name**	**Field**	**Bit**	**Description**
0xF0F00804	AUTO_EXPOSURE	Presence_Inq	[0]	Presence of this feature: 0: N/A; 1: Available
		Abs_Control	[1]	Absolute value control 0: Control with value in the value field 1: Control with value in the absolute value CSR If this bit= 1 the value in the value field has to be ignored
		-	[2..4]	Reserved
		One_Push	[5]	Write: Set Bit high to start Read: Status of the feature: Bit high: WIP, Bit low: Ready

		ON_OFF	[6]	Write ON or OFF this feature, ON=1 Read: Status of the feature; OFF=0
		A_M_MODE	[7]	Set bit high for Auto feature Read for Mode; 0= MANUAL; 1= AUTO
		-	[8..19]	reserved
		Value	[20..31]	Read/Write Value; this field is ignored when writing the value in Auto or OFF mode; if readout capability is not available reading this field has no meaning

Table 34: Gain and Auto_Exposure CSR

The table below illustrates the advanced auto gain control register.

Register	Name	Field	Bit	Description
0xF1000370	AUTOGAIN_CTRL	Presence_Inq	[0]	Indicates presence of this feature (read only)
			[1..3]	-
	MAXVALUE	Max Value	[4..15]	Max value
		-	[16..19]	-
	MINVALUE	Min value	[20..31]	Min value

Table 35: Advanced register for auto gain control

- ⓘ Values can only be changed within the limits of gain CSR.
- ⓘ Changes in auto exposure register only have an effect when auto gain is active.
- ⓘ Auto exposure limits are 50..205.
- ⓘ Auto gain is not possible with CMOS models due to coarse gain settings.

8.6 Setting the brightness (black level or offset)

It is possible to set the black level in the camera within the following ranges:

CCD-models: 0...+16 gray values (@ 8 bit). Increments are in 1/16 LSB (@ 8 bit).
CMOS-model: 0 ... +127 (@ 8 bit)
The formula for gain and offset setting is: Y`= G*Y+Offset

ⓘ Setting the gain does not change the offset (black value) for CCD models.
ⓘ Setting the gain changes the offset (black value) for CMOS models. This is due to the lack of black clamping circuitry in sensor.

The IIDC register brightness at offset 800h is used for this purpose. Description is identical to GAIN.

8.7 Auto shutter

In combination with auto white balance, all CCD- and CMOS models are equipped with auto-shutter feature.
When enabled, the auto shutter adjusts the shutter within the default shutter limits or within those set in advanced register F1000360h in order to reach the reference brightness set in auto exposure register. Increasing the auto exposure value increases the average brightness in the image and vice versa.
The applied algorithm uses a proportional plus integral controller (PI controller) to achieve minimum delay with zero overshot.
The following table shows the Shutter CSR.

Register	Name	Field	Bit	Description
0xF0F0081C	SHUTTER	Presence_Inq	[0]	Presence of this feature: 0: N/A; 1: Available
		Abs_Control	[1]	Absolute value control 0: Control with value in the value field 1: Control with value in the absolute value CSR If this bit= 1 the value in the value field has to be ignored
		-	[2..4]	Reserved
		One_Push	[5]	Write: Set Bit high to start

				Read: Status of the feature: Bit high: WIP, Bit low: Ready
		ON_OFF	[6]	Write ON or OFF this feature, ON=1 Read: Status of the feature; OFF=0
		A_M_MODE	[7]	Set bit high for Auto feature Read for Mode; 0= MANUAL; 1= AUTO
		-	[8..19]	reserved

Table 36: Shutter CSR

The table below illustrates the advanced register for auto shutter control. The purpose of this register is to limit the range within auto shutter is working.

Register	Name	Field	Bit	Description
0xF1000360	AUTOSHUTTER_CTRL	Presence_Inq	[0]	Indicates presence of this feature (read only)
			[1..31]	-
0xF1000364	AUTOSHUTTER_LO	Min Value	[0..31]	Min value
0xF1000368	AUTOSHUTTER_HI	Max Value	[0..31]	Max value

Table 37: Auto shutter ctrl. advanced register

- Values can only be changed within the limits of shutter CSR.
- Changes in auto exposure register only have an effect when auto shutter is enabled.
- Auto exposure limits are 50..205.

When both auto shutter and auto gain are enabled, priority is given to increasing shutter when brightness decreases. This is done to achieve the best image quality with lowest noise.
For increasing brightness, priority is given to lowering gain first for the same purpose.

8.8 Lookup table (LUT) and Gamma function

The AVT Marlin camera provides one user-defined lookup table (LUT). The use of this LUT allows any function (in the form Output = F(Input)T to be stored in the camera's RAM and to apply it on the individual pixels of an image at run-time.
The address lines of the RAM are connected to the incoming digital data, these in turn point to the values of functions which are calculated offline, e.g. with a spreadsheet program.
This function needs to be loaded into the camera's RAM before use.

One example of using a LUT is the Gamma LUT: Output = $(\text{Input})^{0.5}$. This is used with all CCD models. This is known as compensation for the nonlinear brightness response of many displays e.g. CRT monitors. The lookup table converts the 10 bits from the digitizer to 8 bits.



Figure 35: Gamma LUT

ⓘ The input value is the 10-bit value from the digitizer. The gamma LUT of the CCD models outputs the most significant 8 Bit as shown above.

ⓘ As gamma correction for the CCD models is also implemented via the lookup table, it is not possible to use a different LUT when gamma correction is enabled.

ⓘ With all CCD models, the user LUT will be overridden when Gamma is enabled.

ⓘ CMOS models have the gamma function built in the sensor, so that it wont be overridden.

ⓘ LUT content is volatile.

8.8.1 Loading a LUT into the camera

Loading the LUT is carried out through the data exchange buffer called GPDATA_BUFFER. As this buffer can hold a maximum of 2 kB, and a complete LUT at 1024 x 8 bit is 1 kB, programming can take place in a one block write step. The flow diagram below shows the sequence required to load data into the camera.


Query Limits from Register: LUT_INFO and GPDATA_INFO
Set EnableMemWR to true (1)
Set AddrOffset to 0
Write LUT data in GPDATA_BUFER
Set EnableMemWR to false (0)

Figure 36: Loading a LUT

The table below describes the registers required.

Register	Name	Field	Bit	Description
0xF1000240	LUT_CTRL	Presence_Inq	[0]	Indicates presence of this feature (read only).
		---	[1..5]	-
		ON_OFF	[6]	Enable/Disable this feature.
		---	[7..25]	-
		LutNo	[26..31]	Use Lookup table with number LutNo.
0xF1000244	LUT_MEM_CTRL	Presence_Inq	[0]	Indicates presence of this feature (read only).
		---	[1..4]	
		EnableMemWR	[5]	Enable write access.
		---	[6..7]	
		AccessLutNo	[8..15]	
		AddrOffset	[16..31]	byte
0xF1000248	LUT_INFO	Presence_Inq	[0]	Indicates presence of this feature (read only).
		---	[1..7]	
		NumOfLuts	[8..15]	Max. # of Lookup tables.
		MaxLutSize	[16..31]	Max. Lookup Table size (bytes).

Table 38: LUT configuration register

8.9 Shading correction

Shading correction is used to compensate for non-homogeneities caused by lighting or optical characteristics within specified ranges. To correct a frame, a multiplier from 1...2 is calculated for each pixel in 1/256 steps – this allows for shading to be compensated by up to 50 %.

Besides generating shading data off-line and downloading it to the camera, the camera allows correction data to be generated automatically in the camera itself.
Upon generation of the shading image in he camera, it can be uploaded to the host computer for nonvolatile storage purposes.
The following pictures describe the process of automatic generation of correction data. The line profiles were created using MVTEC's "ActivVision Tools".



Figure 37: Shading correction: Source image with non-uniform illumination

On the left you see the source image with non-uniform illumination. The graph on the right clearly shows the brightness level falling off to the right.

By defocusing the lens, high-frequency image data are removed from the source image, therefore its not included in the shading image.

8.9.1 Automatic generation of correction data

Requirements

Shading correction compensates for non-homogeneities by giving all pixels the same gray value as the brightest pixel. This means that only the background must be visible and the brightest pixel has a gray value of less than 255 when automatic generation of shading data is started.
It may be necessary to use a neutral white reference, e.g. a piece of paper, instead of the real image.

Algorithm

After the start of automatic generation, the camera pulls in the number of frames set in the GRAB_COUNT register. Recommended values are 4, 8 or 16. An arithmetic mean value is calculated from them (to reduce noise).

After this, a search is made for the brightest pixel in the mean value frame. A factor is then calculated for each pixel to be multiplied by, giving it the gray value of the brightest pixel.
All of these multipliers are saved in a “shading reference image“. The time required for this process depends on the number of frames to be calculated.
Correction alone can compensate for shading by up to 50 % and relies on 10 bit pixel data to avoid the generation of missing codes.

How to proceed:


Set GrabCount to # of desired frames
Set BuildImage Flag to true
Poll SHGD_Control Register until Busy and BuildImage Flag are resetted

Figure 38: Automatic generation of a shading image

The table below describes the registers required.

Register	Name	Field	Bit	Description
0xF1000250	SHDG_CTRL	Presence_Inq	[0]	Indicates presence of this feature (read only).
		BuildError	[1]	tbd
		---	[2..3]	
		ShowImage	[4]	Show shading data as image.
		BuildImage	[5]	Build a new ShadingImage.
		ON_OFF	[6]	Shading On/Off.
		Busy	[7]	Build in progress.
		---	[8..23]	
		GrabCount	[24..31]	Number of images
0xF1000254	SHDG_MEM_CTRL	Presence_Inq	[0]	Indicates presence of this feature (read only).
		---	[1..4]	
		EnableMemWR	[5]	Enable write access.
		EnableMemRD	[6]	Enable read access.
		---	[7]	
		AddrOffset	[8..31]	Bytes
0xF1000258	SHDG_INFO	Presence_Inq	[0]	Indicates presence of this feature (RD only).
		---	[1..7]	
		MaxImageSize	[8..31]	Max shading Img. size (Bytes).

Table 39: Shading control register

ⓘ The maximum value of GRAB_COUNT depends on the type of camera and the number of frame buffers that exist. GRAB_COUNT is also automatically corrected to the power of two.

ⓘ The SHDG_CTRL register should not be queried at very short intervals This is because each query delays the generation of the shading image. An optimal interval time is 500 ms.

The following pictures illustrate the sequence of commands for generating the shading image. The correction sequence controlled via “Directcontrol” uses the average of 16 frames (10H) to calculate the correction frame.
The top picture shows the input image (with lens out of focus). The bottom picture shows the shading corrected output image (unfocused lens).



Figure 39: Generation of shading image

ⓘ The calculation of shading data is always carried out at the current resolution setting. If the Area of Interest (AOI) is later larger than the window in which correction data was calculated, none of the pixels lying outside are corrected.
ⓘ For Format_7 it is advisable to generate the shading image in the largest displayable frame format. This ensures that any smaller AOI’s are completely covered by the shading correction.
ⓘ The automatic generation of shading data can also be enabled when image capture is already running. The camera then pauses the running image capture for the time needed for generation and resumes after generation is completed.

ⓘ Shading correction can be combined with the Image mirror, binning and gamma functionality (CCD models only). Using shading correction in combination with the gamma feature on the CMOS models may lead to improper results.

After the lens has been focused again the image below will be seen, but now with a considerably more uniform gradient. This is also made apparent in the graph on the right.



Figure 40: Example of shaded image

8.9.2 Loading a shading image into the camera

GPDATA_BUFFER is used to load a shading image into the camera. Because the size of a shading image is larger than GPDATA_BUFFER, input must be handled in several steps:


Query Limits from Register: SHDG_INFO and GPDATA_INFO
Set EnableMemWR to true (1)
Set AddrOffset to 0
Write n databytes in GPDATA_BUFER
Increase AddrOffset by n bytes
Repeat Steps until all data is written
Check EnableMemWR for no change
Set EnableMemWR to false (0)

Figure 41: Loading the shading reference image

8.9.3 Loading a shading image out of the camera

GPDATA_BUFFER is used to load a shading image out of the camera. Because the size of a shading image is larger than GPDATA_BUFFER, input must be handled in several steps:


Query Limits from Register: SHDG_INFO and GPDATA_INFO
Set EnableMemRD to true (1)
Set AddrOffset to 0
Read n databytes of GPDATA_BUFER
Increase AddrOffset by n bytes
Check EnableMemRD for no change
Repeat Steps until all data is read
Set EnableMemRD to false (0)

Figure 42: Uploding shading image to host

8.10 DSNU & blemish correction (MF-131B only)

In order to further reduce the dark signal non uniformity (DSNU) of the CMOS sensor to levels similar to CCD sensors, the MARLIN F-131B is equipped with a special DSNU reduction function, extending the shading correction.
The DSNU function applies an additive correction to every pixel in order to equalize the dark level of the pixels. This function also enables correction of single and double blemished pixels by replacing them with their neighbourhood pixels. DSNU and blemish pixel correction are generated simultaneously but can be switched on/off separately.

The following screenshots demonstrate how it works:
On the left picture (without correction) it can be seen that over the complete field of view there is a certain spread of the histogram, indicating non uniform dark pixels and blemished pixel(s) with brightness around 192(△). With pure DSNU correction the spread is considerably smaller.



Figure 43: Effect of DSNU correction

The table below shows the advanced register map, required to control this functionality.

Register	Name	Field	Bit	Description
0xF1000290	DSNU_CONTROL	Presence_Inq	[0]	Indicates presence of this feature (read only)
		ComputeError	[1]	tbd
		---	[2..3]	
		ShowImage	[4]	Show correction data as image
		ComputeData	[5]	Compute new DSNU correction data
		ON_OFF	[6]	DSNU correction On/Off OFF: High
		Busy	[7]	Computation in

				progress
		---	[8]	
		LoadData	[9]	load factory DSNU correction data
		ZeroData	[10]	zero DSNU correction data
		---	[11..23]	
		GrabCount	[24..31]	Number of images

Table 40: Register for controlling DSNU correction

Having generated the correction data it is possible to separately control the blemish pixel correction with the help of the following register:

Register	Name	Field	Bit	Description
0x1000294	BLEMISH_CONTROL	Presence_Inq	[0]	Indicates presence of this feature (read only)
		ComputeError	[1]	see DSNU_CONTROL
		---	[2..3]	
		ShowImage	[4]	see DSNU_CONTROL
		ComputeData	[5]	see DSNU_CONTROL
		ON_OFF	[6]	Blemish correction On/Off ON: High Default: OFF
		Busy	[7]	see DSNU_CONTROL
		---	[8]	
		LoadData	[9]	see DSNU_CONTROL
		ZeroData	[10]	see DSNU_CONTROL
		---	[11..23]	
		GrabCount	[24..31]	see DSNU_CONTROL

Table 41: Register for controlling blemish pixel correction

The effect of the additional blemish correction can be demonstrated with the next screenshot. Not only is the spread now smaller, there are also no pixels above a considerably lower grey level (△ at. app. 96 in this case).



Figure 44: Histogram with blemish correction

ⓘ For maximum efficiency, perform a new DSNU correction every time the shutter, gain or offset settings are changed. Generate the image by closing the lens to eliminate image information.

ⓘ DSNU correction feature is not available for the MF-131C. The FPN correction in former releases of the MF-131 worked different and is replaced by the DSNU correction.

ⓘ The use of DSNU correction should be accompanied with shading correction for both low level as well as high level corrected pixels.

ⓘ DSNU and blemish correction are volatile.

8.11 Horizontal mirror function

All Marlin cameras are equipped with an electronic mirror function, which mirrors pixels from the left side of the image to the right side and vice versa. The mirror is centered to the actual FOV center and can be combined with all image manipulation functions, like binning, shading and DSNU.
This function is especially useful when the camera is looking at objects with the help of a mirror or in certain microscopy applications.

Mirror can be controlled with the following advanced register:

Register	Name	Field	Bit	Description
0x1000410	MIRROR_CONTROL	Presence_Inq	[0]	Indicates presence of this feature (read only)
		-	[1..5]	
		-	[6]	ON/OFF this feature: HIGH for ON, default :OFF
		-	[7..31]	

Table 42: Mirror control register

ⓘ The use of the mirror function with color cameras and image output in RAW format has implications on the BAYER- ordering of the colors:

Mirror OFF: R-G-G-B  Mirror ON: G-R-B-G 

Figure 45: Mirror and Bayer order

ⓘ During switchover one image may be temporarily corrupted.

8.12 Binning (CCD b/w models)

Binning is the process of combining neighboring pixels while being read out from the CCD chip. All CCD equipped b/w Marlin models have this feature.

Binning is used primarily for 3 reasons:

- A reduction in the number of pixels and thus the amount of data while retaining the original image area angle,
- an increase in the frame rate (vertical binning only),
- an improvement in the signal to noise ratio of the image.

Signal to noise ratio (SNR) and signal to noise separation specify the quality of a signal with regard to its reproduction of intensities. The value signifies how high the ratio of noise is in regard to the maximum wanted signal intensity expected.
The higher this value, the better the signal quality. The unit of measurement used is generally known as the decibel (dB), a logarithmic power level. 6 dB is the signal level at approximately a factor of 2.
However, the advantages of increasing signal quality are accompanied by a reduction in resolution.

Binning is possible only in video Format_7. The type of binning used depends on the video mode.

ⓘ Changing binning modes involve the generation of new shading reference images due to a change in the image size.

In general a difference is made between two types of binning, that can also be combined:

8.12.1 Vertical binning

Vertical binning increases the light sensitivity of the camera by a factor of two by adding together the values of two adjoining vertical pixels output as a single pixel. At the same time this normally improves signal to noise separation by about 2 dB.



Figure 46: Vertical binning

This reduces vertical resolution, depending on the model.
If vertical binning is activated the image may appear to be over-exposed and must be corrected.
Use Format_7 Mode_2 to activate vertical binning.

ⓘ The image appears vertically compressed in this mode and does no longer show true aspect ratio.

8.12.2 Horizontal binning

In horizontal binning adjacent horizontal pixels in a line are combined in pairs.
This means that in horizontal binning the light sensitivity of the camera is also increased by a factor of two (6 dB). Signal to noise separation improves by approx. 3 dB. Horizontal resolution is lowered, depending on the model.
Use Format_7 Mode_1 to activate horizontal binning.



Figure 47: Horizontal binning

ⓘ The image appears horizontally compressed in this mode and does no longer show true aspect ratio.

8.12.3 Full binning

If horizontal and vertical binning are combined, every 4 pixels are consolidated into a single pixel. At first two horizontal pixels are put together and then combined vertically.
This increases light sensitivity by a total of a factor of 4 and at the same time signal to noise separation is improved by about 6 dB. Resolution is reduced, depending on the model.
Use Format_7 Mode_3 to activate full binning.



Figure 48: Full binning

8.13 Sub-sampling (CMOS)

Sub-sampling is the process of skipping neighboring pixels (with the same color) while being read out from the CMOS chip.
All CMOS equipped Marlin models, both color and b/w have this feature (FW > 2.03).

Sub-sampling is used primarily for 2 reasons:

- A reduction in the number of pixels and thus the amount of data while retaining the original image area angle,
- an increase in the frame rate.

Similar to binning mode the cameras support horizontal, vertical and h+v sub-sampling mode.

Use Format_7 Mode_1 to activate horizontal sub-sampling. The different sub-sampling patterns are shown below.



Figure 49: Left: Horizontal sub-sampling B/W; right: Color

ⓘ The image appears horizontally compressed in this mode and does no longer show true aspect ratio.

Use Format_7 Mode_2 to activate vertical sub-sampling. The different sub-sampling patterns are shown below.



Figure 50 Vertical sub-sampling B/W; right: Color

ⓘ The image appears vertically compressed in this mode and does no longer show true aspect ratio.

Use Format_7 Mode_3 to activate h+v sub-sampling. The different sub-sampling patterns are shown below.



Figure 51: H+V subsampling B/W; right: Color

ⓘ Changing sub-sampling modes involve the generation of new shading reference images due to a change in the image size.

8.14 Sharpness

All color models are equipped with a two step sharpness control, applying a discreet horizontal high pass in the green channel as shown in the next three line profiles.



Figure 52: Sharpness: left: 0, middle: 1, right: 2

8.15 Color interpolation and correction

The color sensors capture the color information via so called primary color (R-G-B) filters placed over the individual pixels in a "BAYER mosaic" layout. An effective Bayer -> RGB color interpolation already takes place in all Marlin color version cameras. Before converting to the YUV format, color correction is done after Bayer demosaicing.

Color processing can be bypassed by using the so called RAW image transfer.

RAW-mode is primarily used to

- save bandwidths on the IEEE-1394 bus
- achieve higher frame rates
- use different BAYER demosaicing algorithms on the PC

RAW-mode is accessible via Format_7 Mode_1.

ⓘ If the PC does not perform BAYER to RGB post-processing the b/w image will be superimposed with a checkerboard pattern.

8.15.1 Color interpolation (BAYER demosaicing)

In color interpolation a red, green or blue value is determined for each pixel. Only two lines are needed for this interpolation:



Figure 53: Bayer demosaicing (interpolation)

$$P1_{red} = R1 \qquad P2_{red} = R2 \qquad P3_{red} = R2$$

$$P1_{green} = \frac{G1+G3}{2} \qquad P2_{green} = \frac{G1+G4}{2} \qquad P3_{green} = \frac{G2+G4}{2}$$

$$P1_{blue} = B1 \qquad P2_{blue} = B1 \qquad P3_{blue} = B2$$

ⓘ Please note that on the color camera, a black border one pixel wide forms on the left and right image borders. This is also a consequence of BAYER demosaicing as the image width displayed on the color camera is not scaled down.

8.15.2 Color correction

Color correction is performed on all color CCD models before YUV conversion and mapped via a matrix as follows.

$$red^* = Crr \cdot red + Cgr \cdot green + Cbr \cdot blue$$
$$green^* = Crg \cdot red + Cgg \cdot green + Cbg \cdot blue$$
$$blue^* = Crb \cdot red + Cgb \cdot green + Cbb \cdot blue$$

Sensor specific coefficients C_{xy} are scientifically generated to ensure that GretagMacbeth™ ColorChecker®-colors are displayed with highest color fidelity and color balance.

ⓘ Color correction is deactivated in Mono8 mode (RAW image transport).
ⓘ Color correction can also be switched off in YUV mode with the help of the following register:

0xF10003A0	COLOR_CORR	Marlin C-type CCD cameras only: Write: 02000000h to switch Color correction OFF Write: 00000000h to switch Color correction ON (Default)

8.15.3 RGB → YUV conversion

The conversion from RGB to YUV is made using the following formulae:

$$Y = 0.3 \cdot R + 0.59 \cdot G + 0.11 \cdot B$$
$$U = -0.169 \cdot R - 0.33 \cdot G + 0.498 \cdot B + 128$$
$$V = 0.498 \cdot R - 0.420 \cdot G - 0.082 \cdot B + 128$$

ⓘ As mentioned above: Color processing can be bypassed by using the so called RAW image transfer.
ⓘ RGB -> YUV conversion can be bypassed by using RGB8 format and mode. This is advantageous from the edge color definition but needs more bandwidth (300% instead of 200% relative to b/w or RAW consumption) for the transmission, so that the maximal frame frequency will drop.

8.15.4 Hue and Saturation

Marlin CCD color models are equipped with hue and saturation registers.

The Hue register at offset 810h allows to change the color of objects without changing the white balance by +/- 40 steps (+/- 10°) from the nominal perception. Use this setting to manipulate the color appearance after having done the white balance.

The saturation register at offset 814h allows to change the intensity of the colors by +/-100%. This means a setting of zero changes the image to black and white and a setting of 511 doubles the color intensity compared to the nominal one at 256.

8.16 Serial interface

With FW > 2.03, all Marlin cameras are equipped with the SIO (serial input/output) feature as described in IIDC 1v31. This means that the Marlin's serial interface which is used for firmware upgrades can further be used as a general RS232 interface.
Data written to a specific address in the IEEE-1394 address range will be sent through the serial interface. Incoming data of the serial interface is put in a camera buffer and can be polled via simple read commands from this buffer. Controlling registers enable the settings of baud rates and the check of buffer sizes and serial interface errors.

ⓘ Note that hardware handshaking is not supported.
ⓘ Note that typical PC hardware is not supporting 230400 bps.

Base address for the function is: F0F02100h. The following registers give an overview:

Offset	Name	Field	Bit	Description
000h	SERIAL_MODE_REG	Baud_Rate	[0..7]	Baud rate setting WR: Set baud rate RD: Read baud rate 0: 300 bps 1: 600 bps 2: 1200 bps 3: 2400 bps 4: 4800 bps 5: 9600 bps 6: 19200 bps 7: 38400 bps 8: 57600 bps 9: 115200 bps 10: 230400 bps Other values reserved
		Char_Length	[8..15]	Character length setting WR: Set data length (7 or 8 bit) RD: Get data length 7: 7 bits 8: 8 bits Other values reserved
		Parity	[16..17]	Parity setting WR: Set parity RD: Get parity setting 0: None 1: Odd 2: Even
		Stop_Bit	[18..19]	Stop bits WR: Set stop bit

				RD: Get stop bit setting 0: 1; 1: 1.5; 2: 2
		-	[20..23]	Reserved
		Buffer_Size_Inq	[24..31]	Buffer Size (RD only) This field indicates the maximum size of receive/transmit data buffer If this field is 1, Buffer_Status_Control and SIO_Data_Reg. Char 1-3 should be ignored
0004h	SERIAL_CONTROL_REG	RE	[0]	Receive enable RD: Current status WR: 0: disable 1: Enable
		TE	[1]	Transmit enable RD: Current status WR: 0: disable 1: Enable
		-	[2..7]	Reserved
	SERIAL_STATUS_REG	TDRD	[8]	Transmit data buffer ready Read only 0: not ready; 1: ready
		-	[9]	Reserved
		RDRD	[10]	Receive data buffer ready Read only 0: not ready; 1: ready
		-	[11]	Reserved
		ORER	[12]	Receive data buffer overrun error Read: current status 0: no error WR: 0 to clear status (1: Ignored)
		FER	[13]	Receive data framing error Read: current status 0: no error WR: 0 to clear status (1: Ignored)
		PER	[14]	Receive data parity error

				Read: current status 0: no error WR: 0 to clear status (1: Ignored)
		-	[15..31]	Reserved
008h	RECEIVE_BUFFER_STATUS_CONTRL	RBUF_ST	[0..7]	SIO receive buffer status RD: Number of bytes pending in receive buffer; WR: Ignored
		RBUF_CNT	[8..15]	SIO receive buffer control WR: Number of bytes to be read from the receive FiFo RD: Number of bytes left for readout from the receive FiFo
		-	[16..31]	Reserved
00Ch	TRANSMIT_BUFFER_STATUS_CONTRL	TBUF_ST	[0..7]	SIO output buffer status RD: Space left in TX buffer; WR: Ignored
		TBUF_CNT	[8..15]	SIO output buffer control RD: Number of bytes written to transmit FiFo WR: Number of bytes to transmit
		-	[16..31]	Reserved
010h .. 0FFh		-		Reserved
100h	SIO_DATA_REGISTER	CHAR_0	[0..7]	Character_0 RD: Read char. from receive buffer WR: Write char. to transmit buffer
	SIO_DATA_REGISTER	CHAR_1	[8..15]	Character_1 RD/WR
	SIO_DATA_REGISTER	CHAR_2	[16..23]	Character_2 RD/WR
	SIO_DATA_REGISTER	CHAR_3	[24..31]	Character_3 RD/WR

Table 43: SIO CSR

Reading data requires the following series of actions:

- Query RDRD flag (buffer ready?) and write the number of bytes the host wants to read to RBUF_CNT.
- Read the number of bytes pending in the receive buffer RBUF_ST (more data in the buffer than the host wanted to read?) and the number of bytes left for reading from the receive FiFo in RBUF_CNT (more data the host wanted to read than were in the buffer?).
- Read received characters from SIO_DATA_REGISTER, beginning at char 0.
- To input more characters, repeat from step 1.

Writing data requires the following series of actions:

- Query TDRD flag (buffer ready?) and write the number of bytes to send (copied from SIO register to transmit FiFo) to TBUF_CNT.
- Read the available data space left in TBUF_ST (in the case the buffer can hold more bytes than are to transmit) and number of bytes written to transmit buffer in TBUF_CNT (in the case that more data is to transmit than fits in the buffer).
- Write character to SIO_DATA_REGISTER, beginning at char 0.
- To output more characters, repeat from step 1.

ⓘ Contact your local dealer if you require further information or additional test programs or software.
ⓘ AVT recommends the use of Hyperterminal™ or other communication programs to test the functionality of this feature.

9 Controlling image capture

The cameras support the SHUTTER_MODES specified in IIDC V1.3. For all models this shutter is a global shutter; meaning that all pixels are exposed to the light at the same moment and for the same time span.
In continuous modes the shutter is opened shortly before the vertical reset happens, thus acting in a frame-synchronous way.
Combined with an external trigger, it becomes asynchronous in the sense that it occurs whenever the external trigger occurs. Individual images are recorded when an external trigger impulse is present. This ensures that even fast moving objects can be grabbed with no image lag and with minimal image blur.
The external trigger is fed as a TTL signal through Pin 4 of the HiRose connector.
For CMOS sensors, a global shutter is not common. Normally a rolling curtain shutter is used to shorten the exposure or integration time. The curtain's width defines the integration time and the curtain sweeps with the frame readout time over the image. Although this is appropriate for still images, image distortion will be created with moving objects, because the upper image part is scanned earlier than the lower image part. For this reason the MF-131 features global shutter only. A side effect of global shutter is that the integration or shutter time is added to the readout time, thus affecting the frame rates to be achieved.

9.1 Trigger modi

The cameras support IIDC conforming Trigger_Mode_0 and Trigger_Mode_1 and special Trigger_Mode_15.
Trigger_Mode_0 sets the shutter time according to the value set in the shutter (or extended shutter) register. Trigger_Mode_1 sets the shutter time according to the active low time of the pulse applied (or active high time in the case of an inverting input).


External Trigger input, as applied at input pin
External Trigger input, after inverting opto coupler
Trigger_Mode_0, low_active setting in register F0F00830h
Shutter register value
External Trigger input, as applied at pin
External Trigger input, after inv. Opto.
Trigger_Mode_1, low_active setting
Integration Time

Figure 54: Trigger_mode_0 and 1

Trigger_Mode_15 is a bulk trigger, combining one external trigger event with continuous or oneshot or multishot internal trigger.
It is an extension to the IIDC trigger modes. One external trigger event can be used to trigger a multitude of internal image intakes.

This is especially useful for:

- Exactly grabbing one image based on the first external trigger.
- Filling the camera's internal image buffer with one external trigger without overriding images.
- Grab an unlimited amount of images after one external trigger (Surveillance)

The next image details this mode.


External Trigger input, after inverting optocoupler
Trigger_Mode_15 (Bulk trigger)
N x image; N: continuous, one_shot, multi_shot

Figure 55: Trigger_Mode_15

The functionality is controlled via bit [6] and bitgroup [12-15] of the DCAM register:

Register	Name	Field	Bit	Description
0xF0F00830	TRIGGER_MODE	Presence_Inq	[0]	Presence of this feature: 0:N/A; 1:Available
		Abs_Control	[1]	Absolute value control 0: Control with value in the value field 1: Control with value in the absolute value CSR If this bit= 1 the value in the value field has to be ignored
		-	[2..5]	Reserved
		ON_OFF	[6]	Write ON or OFF this feature, ON=1 Read: Status of the feature; OFF=0

		Trigger_Polarity	[7]	If Polarity_Inq = 1: W: 0 for low active input; 1 for high active input If Polarity_Inq = 0: Read only
		Trigger_Source	[8..10]	Select trigger source ID from trigger source ID_Inq.
		Trigger_Value	[11]	Trigger input raw signal value (read only)
		Trigger_Mode	[12..15]	Trigger_Mode (0-15)
		-	[16..19]	Reserved
		Parameter	[20..31]	Parameter for trigger function, if required

Table 44: Trigger_Mode_15

The screenshots below illustrate the use of Trigger_Mode_15 on a register level:
The first line switches continuous mode off, leaving viewer in listen mode.
The second line prepares 830h register for external trigger and Mode_15.

Left:
The last line switches camera back to cont. mode. Only one image is grabbed precisely with the first external trigger. To repeat rewrite line three.

Middle:
Toggle One_Shot Bit [0] of the One_Shot register 61C so that only one image is grabbed, based on the first external trigger. To repeat rewrite line three.

Right:
Toggle Multi_Shot bit [1] of the One_Shot register 61C so that Ah images are grabbed, starting with the first external trigger. To repeat rewrite line three.

Figure 56: Using Trigger_Mode_15; Continuous, oneshot, multishot

ⓘ Shutter for the images is controlled by shutter register.

9.1.1 Trigger delay

As already mentioned earlier, since firmware version 2.03, the cameras feature various ways to delay image capture based on external trigger.
With 1V31 of IIDC spec. there is a standard CSR at Register F0F00534/834h to control a delay up to FFFh * timebase value. The following table explains the Inquiry register and the meaning of the various bits.

Register	Name	Field	Bit	Description
0xF0F00534	TRIGGER_DELAY_INQUIRY	Presence_Inq	[0]	Indicates presence of this feature (read only)
		Abs_Control_Inq	[1]	Capability of control with absolute value
		-	[2]	Reserved
		One_Push_Inq	[3]	One Push auto mode (Controlled automatically by the camera once)
		Readout_Inq	[4]	Capability of reading out the value of this feature
		ON_OFF	[5]	Capability of switching this feature ON and OFF
		Auto_Inq	[6]	Auto Mode (Controlled automatically by the camera)
		Manual_Inq	[7]	Manual Mode (Controlled by user)
		Min_Value	[8..19]	Min. value for this feature
		Max_Value	[20..31]	Max. value for this feature

Table 45: Trigger_Delay_Inquiry register

	Name	Field	Bit	Description
0xF0F00834	TRIGGER_DELAY	Presence_Inq	[0]	Presence of this feature: 0:N/A; 1:Available
		Abs_Control	[1]	Absolute value control 0: Control with value in the value field

				1: Control with value in the absolute value CSR If this bit= 1 the value in the value field has to be ignored
		-	[2..5]	Reserved
		ON_OFF	[6]	Write ON or OFF this feature, ON=1 Read: Status of the feature; OFF=0
		-	[7..19]	Reserved
		Value	[20..31]	Value

Table 46: Trigger Delay CSR

In addition, the cameras have an advanced register which allows to even more precisely delay the image capture after receiving a hardware trigger.

Trigger delay advanced register

Register	Name	Field	Bit	Description
0xF1000400	TRIGGER_DELAY	Presence_Inq	[0]	Indicates presence of this feature (read only)
		---	[1..5]	-
		ON_OFF	[6]	Trigger delay on/off
		---	[7..10]	-
		DelayTime	[11..31]	Delay time in µs

Table 47: Trigger Delay Advanced CSR

The advanced register allows to delay the start of the integration by max. 2^{21} µs, which is max. 2.1s after a trigger edge was detected.

ⓘ Switching trigger delay to ON also switches external Trigger_Mode_0 to ON.
ⓘ This feature works with external Trigger_Mode_0 only.

9.2 Exposure time

The exposure (shutter) time for continuous mode and Trigger_Mode_0 is based on the following formula:

Shutter register value x timebase + offset

The register value is the value set in the corresponding IIDC register (SHUTTER [81Ch]). This number is in the range between 1 and 4095.
The shutter register value is multiplied by the time base register value (see TIMEBASE). The default value here is set to 20 µs.

A camera-specific offset of 24 to 43 µs is also added to this value.

Example

Camera: MF-033
Register value: 100
Timebase: 20 µs

100 x 20 µs + 24 µs = 2024 µs exposure time.
The minimum adjustable exposure time set by register is 10 µs. => the real minimum exposure time of an MF-033 is then 10 µs + 24 µs = 34 µs.

9.2.1 Extended shutter

The exposure time for long-term integration of up to 67 sec can be extended via the EXTENDED_SHUTTER register.

Register	Name	Field	Bit	Description
0xF100020C	EXTD_SHUTTER	Presence_Inq	[0]	Indicates presence of this feature (read only)
		---	[1.. 5]	
		ExpTime	[6..31]	Exposure time in µs

Table 48: Extended shutter configuration

The longest exposure time, 3FFFFFFh, corresponds to 67.11 sec.

- ⓘ Exposure times entered via the 81Ch register are mirrored in the extended register, but not vice versa.
- ⓘ Longer integration times not only increase sensitivity, but also may increase some unwanted effects such as noise and pixel-to-pixel non uniformity. Depending on the application, these effects may limit the longest useable integration time.
- ⓘ Changes in this register have immediate effect, even when the camera is transmitting.
- ⓘ Extended shutter becomes inactive after writing to a format/mode/frame rate register.

9.3 One-Shot

The camera can record an image by setting the "`OneShot bit`" in the 61Ch register. This bit is automatically cleared after the image is captured. If the camera is placed in *Iso_Enable* mode (see ISO_Enable / Free-Run), this flag is ignored.
If *OneShot mode* is combined with the external trigger, the "`OneShot`" command is used to arm it. The following screenshot shows the sequence of commands needed to put the camera into this mode. It enables the camera to grab exactly one image with an external trigger edge.
If there is no trigger impulse after the camera has been armed, OneShot can be cancelled by clearing the bit.



Figure 57: One_shot control

9.3.1 One-Shot command on the bus to start of exposure

The following sections describe the time response of the camera using a single frame (OneShot) command. As set out in the IIDC specification, this is a software command that causes the camera to record and transmit a single frame.

The following values apply only when the camera is idle and ready for use. Full resolution must also be set.

OneShot->Microcontroller-Sync: <=250 µs (processing time in the microcontroller)

µC-Sync/ExSync->Integration-Start 8 µs

Microcontroller-Sync is an internal signal. It is generated by the microcontroller to initiate a trigger. This can either be a direct trigger or a release for ExSync if the camera is externally triggered.

9.3.2 End of exposure to first packet on the bus

After the exposure, the CCD or CMOS-sensor is read out; some data is written into the FRAME_BUFFER before being transmitted to the bus.

The time from the end of exposure to the start of transport on the bus is:

500µs ± 62.5µs

This time 'jitters' with the cycle time of the bus (125µs).



Figure 58: Data flow and timing after end of exposure

9.4 Multi-Shot

Setting "`MultiShot`" and entering a quantity of images in *Count_Number* in the 61Ch register enables the camera to record a specified number of images.

The number is indicated in bits 16 to 31. If the camera is put into *Iso_Enable* mode (ISO_Enable / Free-Run), this flag is ignored and deleted automatically once all the images have been recorded.

If *MultiShot* mode is activated and the images have not yet all been captured, it can be cancelled by resetting the flag. The same result can be achieved by setting the number of images to "0".

Multi-Shot can also be combined with the external trigger in order to grab a certain number of images based on an external trigger. This is especially helpful in combination with the so called Deferred_Mode to limit the amount of grabbed images to the FIFO size.

9.5 ISO_Enable / Free-Run

Setting the MSB (bit 0) in the 614h register (ISO_ENA) puts the camera into *ISO_Enable mode* or *Continuous_Shot*. The camera captures an infinite series of images. This operation can be quit by deleting the "0" bit.

9.6 Asynchronous broadcast

The camera accepts asynchronous broadcasts. This involves asynchronous write requests that use node number 63 as the target node with no acknowledge.

This makes it possible for all cameras on a bus to be triggered by software simultaneously - e.g. by broadcasting a "`One_Shot`". All cameras receive the "`One_Shot`" command in the same IEEE-1394 bus cycle. This creates uncertainty for all cameras in the range of 125 µs.
Inter-camera latency is described in chapter 9.7.
The following screenshot shows an example of broadcast commands sent with the Firedemo example of FirePackage (version 1V51 or newer):
Line 1 shows the broadcast command, which stops **all** cameras connected to the same IEEE-1394 bus. It is generated by holding the <`shift`> key down while clicking on <`Write`>.
Line 2 generates a "`broadcast One_Shot`" in the same way, which forces all connected cameras to simultaneously grab one image.



Figure 59: Broadcast One_Shot

9.7 Jitter at start of exposure

The following chapter discusses the latency time which exists for all CCD-models when either a hardware or software trigger is generated, until the actual image exposure starts.
Owing to the well-known fact that an Interline Transfer CCD-sensor has both a light sensitive area and a separate storage area, it is common to interleave image exposure of a new frame and output that of the previous one. It makes continuous image flow possible, even with an external trigger.
This is different to the way the CMOS- sensor of the MF-131 works: the image sensitive area is also the storage area, which means that it cannot be used for the integration of the new frame until it has been read out.
Continuous image flow is thus only possible with the so-called rolling shutter.
Asynchronous image acquisition only makes sense with the global shutter; leading to a non-interleaving exposure – readout – exposure sequence. For every exposure cycle the sensor is completely reset so that the camera needs to be idle.
For the CCD's the uncertain time delay before the start of exposure depends on the state of the sensor. A distinction is made as follows:

FVal is active → the sensor is reading out, camera is busy

In this case the camera must not change horizontal timing so that the trigger event is synchronized with the current horizontal clock. This introduces a max. uncertainty which is equivalent to the line time. The line time depends on the sensor used and therefore can vary from model to model.

FVal is inactive → the sensor is ready, the camera is idle

In this case the camera can resynchronize the horizontal clock to the new trigger event, leaving only a very short uncertainty time of the master clock period.

Model	Camera idle	Camera busy
MF-033	33,33 ns	27,03 µs
MF-046	33,33 ns	32,17 µs
MF-080	50 ns	63,50 µs
MF-131	25 ns	Not applicable
MF-145	50 ns	92,25 µs

Table 49: Jitter at exposure start

- Jitter at the beginning of an exposure has no effect on the length of exposure, i.e. it is always constant.
- By default, the MF-131, the CMOS sensor uses global shutter, so it cannot be re-triggered until the previous image has been read out.

9.8 Frame memory and deferred image transport

An image is normally captured and transported in consecutive steps. The image is taken, read out from the sensor, digitized and sent over the 1394 bus.
As all Marlin cameras are equipped with built in image memory, this order of events can be paused or delayed by using the *deferred image transport* feature.
Marlin cameras are equipped with 8 MB of RAM. The table below shows how many frames can be stored by each model. The memory is arranged in a FiFo (First in First out) manner. This makes addressing for individual images unnecessary.

Model	Memory Size
MF-033	17 frames
MF-046	13 frames
MF-080	7 frames
MF-131	4 frames
MF-145	3 frames

Table 50: FiFo memory size

Deferred image transport is especially useful for multi camera applications where a multitude of cameras grab a certain number of images without having to take available bus bandwidth, DMA- and ISO-channels into account. Image transfer is controlled from the host computer by addressing individual cameras and reading out the desired number of images. Functionality is controlled by the following register:

Register	Name	Field	Bit	Description
0xF1000260	DEFERRED_TRANS	Presence_Inq	[0]	Indicates presence of this feature (read only)
		---	[1..4]	
		SendImage	[5]	Send NumOfImages now (auto reset)
		HoldImg	[6]	Enable/Disable deferred transport mode
		FastCapture	[7]	Enable/disable fast capture mode
		---	[8..15]	
		FiFoSize	[16..23]	Size of FiFo in number of images (read only)
		NumOfImages	[24..31]	W: Number of images to send R: Number of images in buffer

Table 51: Deferred mode configuration register

9.8.1 HoldImg mode

By setting the *HoldImg* flag, transport of the image over the 1394 bus is stopped completely. All captured images are stored in the internal ImageFiFo. The camera reports the maximum possible number of images in the FiFoSize variable.

- Pay attention to the maximum number of images that can be stored in FiFo. If you capture more images than the number in FiFoSize, the oldest images are overwritten.
- The extra *SendImage* flag is set to "true" to import the images from the camera. The camera sends the number of images that are entered in the *NumOfImages* parameter.
- If *NumOfImages* is "0" all images stored in FIFO are sent.
- If *NumOfImages* is not "0", the corresponding number of images is sent.
- If the *HoldImg* field is set to "false", all images in *ImageFIFO* are deleted. No images are sent.
- The last image in the FiFo will be corrupted, when simultaneously used as input buffer while being read out. Read out one image less than max. buffer size in this case.

The following screenshot displays the sequence of commands needed to work with deferred mode.



Figure 60: Example of controlling deferred mode

9.8.2 FastCapture

This mode can be activated only in Format_7.

When *FastCapture* is set to "false", the maximum frame rate both for image acquisition and read out is associated with the packet size set in the BYTE_PER_PACKET register. The lower this value is, the lower the attainable frame rate is.

By setting *FastCapture* to "true", all images are recorded at the highest possible frame rate, i.e. the setting above does not affect the frame rate for the image intake but only the read out. This mode is ideal for applications where a burst of images need to be recorded at the highest sensor speed but the output can be at a lower frame frequency to save bandwidth.

9.9 Sequence mode

Generally all AVT Marlin cameras enable certain image settings to be modified on the fly, e.g. gain and shutter can be changed by the host computer by writing into the gain and shutter register even while the camera is running. An uncertainty of one or two images remains because normally the host does not know (especially with external trigger) when the next image will arrive.
Sequence mode is a different concept where the camera holds a set of different image parameters for a sequence of images. The parameter set is stored volatile in the camera for each image to be recorded. This sequence of parameter sets is simply called a sequence. The advantage is that the camera can easily synchronize this parameter set with the images so that no uncertainty can occur. All CCD model AVT Marlin cameras support 32 different sequence params.

Examples:
For a sequence of images, each image can be recorded with a different shutter or gain to obtain different brightness effects.
The image area (AOI) of a sequence of images can automatically be modified, thus creating a panning or sequential split screen effect.

The following registers can be modified to affect the individual steps of the sequence.

All modes	Cur_V_Mode, Cur_V_Format, ISO_Channel, ISO_Speed, Brightness, White_Balance (color cameras only), Shutter, Gain, Lookup-Table, TestImage
Fixed modes only	Cur_V_Frm_Rate
Format_7 only	Image_Position, Image_Size, Color_Coding_ID, Byte_Per_Packet

Table 52: Registers to be modified within a sequence

ⓘ Sequence mode requires special care if changing image size and frame rate related parameters. This is because these changes not only affect settings in the camera but also require corresponding settings in the receiving software in the PC. Incorrect handling may lead to image corruption or loss of subsequent images. Please ask for detailed support when you want to use this feature.

How is sequence mode implemented?

There is a FIFO (first in first out) memory for each of the IIDC v. 1.3 registers listed above. The depth of each FIFO is fixed to 32(dez) complete sets. Functionality is controlled by the following advanced registers.

Register	Name	Field	Bit	Description
0xF1000220	SEQUENCE_CTRL	Presence_Inq	[0]	Indicates presence of this feature (read only)
		---	[1..4]	
		AutoRewind	[5]	
		ON_OFF	[6]	Enable/Disable this feature
		---	[7..15]	
		MaxLength	[16..23]	Max possible length of a sequence (read only)
		SeqLength	[24..31]	Length of the sequence (32dez for all CCD models)
0xF1000224	SEQUENCE_PARAM	---	[0..4]	
		ApplyParameters	[5]	Apply settings to selected image of sequence; auto-reset
		IncImageNo	[6]	Increment ImageNo after ApplyParameters has finished
		---	[7..23]	
		ImageNo	[24..31]	Number of image within a sequence

Table 53: Sequence configuration register

The following flow diagram shows how to set up a sequence.


Set SEQUENCE_CTRL ON_OFF Flag to true (1)
Set SeqLength to desired length (<=MaxLength)
Set ImageNo = 0 in SEQUENCE_PARAM
Assign image parameters in the corresp. registers
ApplyParameters = 1 (AutoReset)
Set Flag IncImageNo = 1
Start sequence in MultiShot or ISOEnable mode
Repeat Steps until Sequence is complete

Figure 61: Sequence mode flow diagram

During sequencing, the camera obtains the required parameters, image by image, from the corresponding FIFOs (e.g. information for exposure time).

Points to pay attention to when working with a sequence:

- If more images are recorded than defined in *SeqLength* ,the settings for the last image remain in effect.
- If *sequence* mode is cancelled, the camera can use the FIFO for other tasks. For this reason, a sequence must be loaded back into the camera after *sequence* mode has been cancelled.
- To repeat the sequence, stop the camera and send the “MultiShot” or “IsoEnable” command again. Each of these two commands resets the sequence.
- Using *SingleShot* mode in combination with a sequence does not make sense, because *SingleShot* mode restarts the sequence every time.
- The sequence may not be active when setting the *AutoRewind* flag. For this reason it is important to set the flag before the “MultiShot” or “ISO_Enable” commands.
- If the sequence is used with the *deferred transport* feature, the number of images entered in *Seq_Length* may not be exceeded.

The following screenshot shows an example of a sequence for eight different image settings. It uses the AVT program AVTFiretool as graphical representation. Please note the changes in the shutter time; that creates descending image brightness, and the change in the image position; which creates a panning effect.



Img.	VFormat	VMode	VFps	ISOChn	IsoSpd	Brightn.	WhiteBalVR	WhiteBalUB	Shutter	Gain	LUT	TestImg	ImgPosL	ImgPosT	ImgSizeW	ImgSizeH	ColorID	BytePacket
1	7	0	2			16	0	0	1000	1	0	0	0	0	640	480	0	200
2	7	0	2			16	0	0	900	1	0	0	100	0	640	480	0	200
3	7	0	2			16	0	0	800	1	0	0	200	0	640	480	0	200
4	7	0	2			16	0	0	700	1	0	0	300	0	640	480	0	200
5	7	0	2			16	0	0	600	1	0	0	300	100	640	480	0	200
6	7	0	2			16	0	0	500	1	0	0	300	200	640	480	0	200
7	7	0	2			16	0	0	400	1	0	0	300	300	640	480	0	200
8	7	0	2			16	0	0	300	1	0	0	300	400	640	480	0	200

Figure 62: Example of sequence mode settings

9.9.1 Changing the parameters within a sequence

To change the parameter set for one image, it is not necessary to modify the settings for the entire sequence. The image can simply be selected via the *ImageNo* field and it is then possible to change the corresponding IIDC v. 1.3 registers.

Points to pay attention to when changing the parameters:

- If the *ApplyParameters* flag is used when setting the parameters, all not-configured values are set to default values. As changing a sequence normally affects only the value of a specific register, and all other registers should not be changed, the *ApplyParameters* flag may not be used here.
- The values stored for individual images can no longer be read.
- If the camera is switched into *sequence mode*, the changes to the IIDC v. 1.3 registers for the image specified in *ImageNo* take immediate effect.
- Changes in the image size and the BytePacket settings need to be mirrored in the host computer when using e.g. FirePackage, as they affect the amount of data, and the number of packets to be sent for one image, and thus the creation of new image-events.
- Sequence mode requires special care if changing image size and frame rate related parameters. This is because these changes not only affect settings in the camera but also require corresponding settings in the receiving software in the PC. Incorrect handling may lead to image corruption or loss of subsequent images. Please ask for detailed support when you want to use this feature.

10 Video formats, modes and bandwidth

The different Marlin models support different video formats, modes and frame rates.
These formats and modes are standardized in the IIDC (formerly DCAM) specification.
Resolutions smaller than the generic sensor resolution are generated from the center of the sensor and without binning.

ⓘ The maximum frame rates can only be achieved with shutter settings lower than 1/framerate. This means that with default shutter time of 40ms, a camera will not achieve frame rates higher than 25 fr/s. In order to achieve higher frame rates, please reduce the shutter time proportionally.

10.1 MF-033B/ MF-033C

For-mat	Mode	Resolution	60 fps	30 fps	15 fps	7.5 fps	3.75 fps	1.875 fps
0	0	160 x 120 YUV444						
	1	320 x 240 YUV422						
	2	640 x 480 YUV411	x	x	x	x	x	x
	3	640 x 480 YUV422		x	x	x	x	x
	4	640 x 480 RGB8		x	x	x	x	x
	5	640 x 480 MONO8	x x*	x x*	x x*	x x*	x x*	x x*
	6	640 x 480 MONO16		x	x	x	x	x

7	0	656 x 492 MONO8 656 x 492 YUV	@74 fps @51(YUV:4:2:2)/68(YUV:4:1:1) fps
	1	328 x 492 MONO8 656 x 494 MONO8 (RAW)	@74 fps, H-binning @73 fps
	2	656 x 244 MONO8	@129 fps, V-binning
	3	328 x 244 MONO8	@129 fps, H+V binning

Table 54: Video formats MF-033

*: Color camera outputs RAW image, which needs to be converted outside of camera.

10.2 MF-046B/ MF-046C

For-mat	Mode	Resolution	60 fps	30 fps	15 fps	7.5 fps	3.75 fps	1.875 fps
0	0	160 x 120 YUV444						
	1	320 x 240 YUV422						
	2	640 x 480 YUV411		x	x	x	x	x
	3	640 x 480 YUV422		x	x	x	x	x
	4	640 x 480 RGB8		x	x	x	x	x
	5	640 x 480 MONO8		x x*	x x*	x x*	x x*	x x*
	6	640 x 480 MONO16		x	x	x	x	x

7	0	780 x 580 MONO8 780 x 580 YUV	@53 fps @36(YUV:4:2:2)/49(YUV:4:1:1) fps
	1	388 x 580 MONO8 780 x 582 MONO8 (RAW)	@53 fps, H-binning @52 fps
	2	780 x 288 MONO8	@93 fps, V-binning
	3	388 x 288 MONO8	@93 fps, H+V binning

Table 55: Video formats MF-046

*: Color camera outputs RAW image, which needs to be converted outside of camera.

10.3 MF-080B/ MF-080C (-30 fps)

For-mat	Mode	Resolution	60 fps	30 fps	15 fps	7.5 fps	3.75 fps	1.875 fps
0	0	160 x 120 YUV444						
	1	320 x 240 YUV422						
	2	640 x 480 YUV411		x	x	x	x	x
	3	640 x 480 YUV422		x	x	x	x	x
	4	640 x 480 RGB8		x	x	x	x	x
	5	640 x 480 MONO8		x x*	x x*	x x*	x x*	x x*
	6	640 x 480 MONO16		x	x	x	x	x
1	0	800 x 600 YUV422		x	x	x	x	x
	1	800 x 600 RGB8			x	x	x	x
	2	800 x 600 MONO8		x x*	x x*	x x*	x x*	x x*
	3	1024 x 768 YUV422			x	x	x	x
	4	1024 x 768 RGB8				x	x	x
	5	1024 x 768 MONO8		x	x x*	x x*	x x*	x x*
	6	800 x 600 MONO16		x	x	x	x	x
	7	1024 x 768 MONO16			x	x	x	x
7	0	1032 x 776 MONO8 1032 x 776 YUV	@20 fps (30 fps**) @20 fps					
	1	516 x 776 MONO8 1032 x 778 MONO8 (RAW)	@20 fps, H-binning (30 fps**) @20 fps (30 fps**)					
	2	1032 x 388 MONO8	@35 fps, V-binning (59 fps**)					
	3	516 x 388 MONO8	@35 fps, H+V binning (59 fps**)					

Table 56: Video formats MF-080

*: Color camera outputs RAW image, which needs to be converted outside of camera.
30 fps column applying to this variant only.
** applying to 30 fps variant only

10.4 MF-145B/ MF-145C

For-mat	Mode	Resolution	60 fps	30 fps	15 fps	7.5 fps	3.75 fps	1.875 fps
0	0	160 x 120 YUV444						
	1	320 x 240 YUV422						
	2	640 x 480 YUV411			x	x	x	x
	3	640 x 480 YUV422			x	x	x	x
	4	640 x 480 RGB8			x	x	x	x
	5	640 x 480 MONO 8			x x*	x x*	x x*	x x*
	6	640 x 480 MONO 16			x	x	x	x
1	0	800 x 600 YUV422			x	x	x	x
	1	800 x 600 RGB8			x	x	x	x
	2	800 x 600 MONO8			x x*	x x*	x x*	x x*
	3	1024 x 768 YUV422			x	x	x	x
	4	1024 x 768 RGB8				x	x	x
	5	1024 x 768 MONO 8			x x*	x x*	x x*	x x*
	6	800 x 600 MONO16			x	x	x	x
	7	1024 x 768 MONO16			x	x	x	x
2	0	1280 x 960 YUV422			x**	x	x	x
	1	1280 x 960 RGB8				x	x	x
	2	1280 x 960 MONO 8			x** x**	x x*	x x*	x x*
	3	1600 x 1200 YUV422						
	4	1600 x 1200 RGB8						
	5	1600 x 1200 MONO8						
	6	1280 x 960 MONO16			x**	x	x	x
	7	1600 x 1200 MONO16						

7	0	1392 x 1036 YUV411/422	@10 fps ; 15 fps**
	0	1392 x 1040 MONO8	Raw Bayer pattern @10 fps; 15 fps**
	1	696 x 1040 MONO8 1392 x 1038 MONO8 (RAW)	@10 fps; 15 fps**, H-binning @10 fps ; 15 fps**
	2	1392 x 520 MONO8	@17 fps; 24 fps**, V-binning
	3	696 x 520 MONO8	@17 fps; 24 fps**, H+V-binning

Table 57: Video formats MF-145

Owing to color interpolation, the maximum height is 1036 pixels in YUV modes and the first and last pixel columns contain no image information.
*: Color camera outputs RAW image, which needs to be converted outside of camera.
**: Applying for variant F-145B/C2-15 only.
This variant offers higher speed at a slight expense in image quality.

10.5 MF-131B/ MF-131C

For-mat	Mode	Resolution	60 fps	30 fps	15 fps	7.5 fps	3.75 fps	1.875 fps
0	0	160 x 120 YUV444						
	1	320 x 240 YUV422						
	2	640 x 480 YUV411			x	x	x	
	3	640 x 480 YUV422			x	x	x	
	4	640 x 480 RGB						
	5	640 x 480 MONO 8		x**	x	x	x	
	6	640 x 480 MONO 16						
1	0	800 x 600 YUV422			x	x	x	
	1	800 x 600 RGB						
	2	800 x 600 MONO8		x***	x	x	x	
	3	1024 x 768 YUV422			x	x	x	
	4	1024 x 768 RGB						
	5	1024 x 768 MONO 8			x	x	x	
	6	800 x 600 MONO16						
	7	1024 x 768 MONO16						
2	0	1280 x 960 YUV422				x	x	x
	1	1280 x 960 RGB						
	2	1280 x 960 MONO 8			x	x	x	x
	3	1600 x 1200 YUV422						
	4	1600 x 1200 RGB						
	5	1600 x 1200 MONO						
	6	1280 x 960 MONO16						
	7	1600 x 1200 MONO16						
7	0	1280 x 1024 MONO8 1280 x 1020 YUV	@25 fps* YUV 4:1:1 @ 17 fps*; YUV 4:2:2 @ 12 fps*					
	1	640 x 1024 MONO8 640 x 1020 YUV	@48 fps* YUV 4:1:1 @ 33 fps*; YUV 4:2:2 @ 25 fps*					
	2	1280 x 512 MONO8 1280 x 508 YUV	@50 fps* YUV 4:1:1 @ 33 fps*; YUV 4:2:2 @ 25 fps*					
	3	640 x 512 MONO8 640 x 508 YUV	@94 fps* YUV 4:1:1 @ 64 fps*; YUV 4:2:2 @ 50 fps*					

Table 58: Video formats MF-131

ⓘ *: With minimum shutter; Increasing shutter will decrease max. frame frequency proportionally due to global shutter principle.

ⓘ **: With shutter <= 23 ms only; ***: With shutter <= 18ms only.

ⓘ Generally full resolution mono frame rates are achievable only with shutter settings which fulfil the equation: Shutter <= 1/fps- 40ms

10.6 Area of interest (AOI)

The image sensor on the camera has a defined resolution. This indicates the maximum number of lines and pixels per line that the recorded image may have.

However, often only a certain section of the entire image is of interest. The amount of data to be transferred can be decreased by limiting the image to a section when reading it out from the camera. At a lower vertical resolution the sensor can be read out faster and thus the frame rate is increased.

ⓘ The setting of AOIs is supported only in video Format_7.

While the size of the image read out for most other video formats and modes is fixed by the IIDC specification, thereby determining the highest possible frame rate, in Format_7 mode the user can set the “upper left corner” and “width and height” of the section (Area of Interest) he is interested in to determine the size and thus the highest possible frame rate.

Setting the AOI is done in the IMAGE_POSITION and IMAGE_SIZE registers.
Attention should be paid to the increments entered in the UNIT_SIZE_INQ and UNIT_POSITION_INQ registers when configuring IMAGE_POSITION and IMAGE_SIZE.

IMAGE_POSITION and IMAGE_SIZE contain in the respective bits values for the column and line of the upper left corner and values for the width and height.



Figure 63: Area of Interest

ⓘ The left position + width and the upper position + height may not exceed the maximum resolution of the sensor.

ⓘ The coordinates for width and height must be divisible by 4.

In addition to the Area of Interest, some other parameters have an effect on the maximum frame rate:

- the time for reading the image from the sensor and transporting it into the FRAME_BUFFER
- the time for transferring the image over the FireWire™ bus
- the length of the exposure time.

10.7 Frame rates

An IEEE-1394 camera requires bandwidth to transport images.

The IEEE-1394a bus has very large bandwidth of at least 32 MB/s for transferring (isochronously) image data. Per cycle up to 4096 bytes (or around 1000 quadlets = 4 bytes) can thus be transmitted.
Depending on the video format settings and the configured frame rate, the camera requires a certain percentage of maximum available bandwidth. Clearly the bigger the image and the higher the frame rate, there is more data to be transmitted.
The following tables indicate the volume of data in various formats and modes to be sent within one cycle (125µs) at 400 Mb/s of bandwidth.
The tables are divided into three formats; F_0 up to VGA, F_1 up to XGA, and F_2 up to UXGA.
They enable you to calculate the required bandwidth and to ascertain the number of cameras that can be operated independently on a bus and in which mode.

Format	Mode	Resolution	60 fps	30 fps	15 fps	7.5 fps	3.75 fps
0	0	160 x 120 YUV (4:4:4) 24 bit/pixel		1/2H 80p 60q	1/4H 40p 30q	1/8H 20p 15q	
	1	320 x 240 YUV (4:2:2) 16 bit/pixel		1H 320p 160q	1/2H 160p 80q	1/4H 80p 40q	1/8H 40p 20q
	2	640 x 480 YUV (4:1:1) 12 bit/pixel		2H 1280p 480q	1H 640p 240q	1/2H 320p 120q	1/4H 160p 60q
	3	640 x 480 YUV (4:2:2) 16 bit/pixel		2H 1280p 640q	1H 640p 320q	1/2H 320p 160q	1/4H 160p 80q
	4	640 x 480 RGB 24 bit/pixel		2H 1280p 960q	1H 640p 480q	1/2H 320p 240q	1/4H 160p 120q
	5	640 x 480 (MONO8) 8 bit/pixel	4H 2560p 640q	2H 1280p 320q	1H 640p 160q	1/2H 320p 80q	1/4H 160p 40q
	6	640 x 480 Y (MONO16) 16 Bit/pixel		2H 1280p 640q	1H 640p 320q	1/2H 320p 160q	1/4H 160p 80q
	7	640 x 480 Y (MONO16) Reserved					

Table 59: Format_0

As an example, VGA MONO8 @ 60 fps requires four lines (640 x 4 = 2560 pixels/byte) to transmit every 125 µs: this is a consequence of the sensor's line time of about 30 µs, so that no data needs to be stored temporarily. It takes 120 cycles (120 x 125 µs = 15 ms) to transmit one frame, which arrives every 16.6 ms from the camera. Again no data need to be stored temporarily.
Thus around 64 % of the available bandwidth is used.

For-mat	Mode	Resolution	60 fps	30 fps	15 fps	7.5 fps	3.75 fps	1.875 fps
1	0	800 x 600 YUV (4:2:2) 16 bit/pixel		5/2H 2000p 1000q	5/4H 1000p 500q	5/8H 500p 250q	6/16H 250p 125q	
	1	800 x 600 RGB 24 Bit/pixel			5/4H 1000p 750q	5/8H 500p 375q		
	2	800 x 600 Y (MONO8) 8 bit/pixel	5H 4000p 1000q	5/2H 2000p 500q	5/4H 1000p 250q	5/8H 500p 125q		
	3	1024 x 768 YUV (4:2:2) 16 bit/pixel			3/2H 1536p 768q	3/4H 768p 384q	3/8H 384p 192q	3/16H 192p 96q
	4	1024 x 768 RGB 24 bit/pixel				3/4H 768p 576q	3/8H 384p 288q	3/16H 192p 144q
	5	1024 x 768 Y (MONO) 8 bit/pixel		3H 3072p 768q	3/2H 1536p 384q	3/4H 768p 192q	3/8H 384p 96q	3/16H 192p 48q
	6	800 x 600 (MONO16) 16 bit/pixel		5/2H 2000p 1000q	5/4H 1000p 500q	5/8H 500p 250q	5/16H 250p 125q	
	7	1024 x 768 Y (MONO16) 16 bit/pixel			3/2H 1536p 768q	3/4H 768p 384q	3/8H 384p 192q	3/16H 192p 96q

Table 60: Format_1

For-mat	Mode	Resolution	60 fps	30 fps	15 fps	7.5 fps	3.75 fps	1.875 fps
2	0	1280 x 960 YUV (4:2:2) 16 bit/pixel				1H 1280p 640q	1/2H 640p 320q	1/4H 320p 160q
	1	1280 x 960 RGB 24 bit/pixel				1H 1280p 960q	1/2H 640p 480q	1/4H 320p 240q
	2	1280 x 960 Y (MONO8) 8 bit/pixel			2H 2560p 640q	1H 1280p 320q	1/2H 640p 160q	1/4H 320p 80q
	3	1600 x 1200 YUV(4:2:2) 16 bit/pixel				5/4H 2000p 1000q	5/8H 1000p 500q	5/16H 500p 250q
	4	1600 x 1200 RGB 24 bit/pixel					5/8H 1000p 750q	5/16 500p 375q
	5	1600 x 1200 Y (MONO) 8 bit/pixel			5/2H 4000p 1000q	5/4H 2000p 500q	5/8H 1000p 250q	5/16H 500p 125q
	6	1280 x 960 Y (MONO16) 16 bit/pixel				1H 1280p 640q	1/2H 640p 320q	1/4H 320p 160q
	7	1600 x 1200Y(MONO16) 16 bit/pixel				5/4H 2000p 1000q	5/8H 1000p 500q	5/16H 500p 250q

Table 61: Format_2

As already mentioned, the recommended limit for transferring isochronous image data is 1000q (quadlets) per cycle or 4096 bytes (with 400 Mb/s of bandwidth).

The third table shows that a MF-145B2 @ 7.5 fps has to send 1280 pixels or 1 line of video per cycle. The camera thus uses 32 % of available bandwidth. This allows up to three cameras with these settings to be operated independently on the same bus.

ⓘ If the cameras are operated with an external trigger the maximum trigger frequency may not exceed the highest continuous frame rate, so preventing frames from being dropped or corrupted.

ⓘ IEEE-1394 adapter cards with PCILynx™ chipsets have a limit of 4000 bytes per cycle.

The frame rates in video modes 0 to 2 are specified and set fixed by IIDC V. 1.3.

In video Format_7 frame rates are no longer fixed but can be varied dynamically by the parameters described below.

The following formula is used to calculate for the CCD models the highest frame rate in Format_7:

$$FPS_{In} = FPS_{CCD} = \frac{1}{T_{Charge Trans} + T_{Dummy} + T_{Dump} + T_{Scan}}$$

Formula 1: Frame rate calculation

It assumes that the maximum frame rate is the inverse of the sum of all events in a CCD, which take time such as:

- The time to transfer the storage to the vertical shift register (Charge transfer time)
- The time to shift out the dummy lines
- The time to dump the lines outside the AOI
- The time to shift out the lines of the AOI. (Scanning time)

For the different sensors, different values apply.
Frame rates may be further limited by bandwidth limitation from the IEEE-1394 bus.
Details are described in the next chapter.

10.7.1 MF-033

Different parameters apply for the different models.

$$fps = \frac{1}{T_{Charge Trans} + T_{Dummy} + T_{Dump} + T_{Scan}}$$

$$fps = \frac{1}{30\mu s + 68.5\mu s + (494 - AOI\_HEIGHT) \cdot 3.45\mu s + AOI\_HEIGHT \cdot 27.1\mu s}$$

Formula 2: Frame rate calculation MF-033



AOI_HEIGHT	fps	Tf/ms
494	74,15	13,49
480	76,02	13,15
400	88,79	11,26
320	106,71	9,37
240	133,71	7,48
120	215,48	4,64
20	439,41	2,28

Table 62: Frame rates MF-033

10.7.2 MF-046

$$fps = \frac{1}{T_{Charge Trans} + T_{Dummy} + T_{Dump} + T_{Scan}}$$

$$fps = \frac{1}{31\mu s + 88\mu s + (582 - AOI\_HEIGHT) \cdot 4.15\mu s + AOI\_HEIGHT \cdot 32.2\mu s}$$

Formula 3: Frame rate calculation MF-046



AOI_HEIGHT	fps	Tf/ms
582	53,02	18,86
480	62,51	16,00
400	72,70	13,75
320	86,88	11,51
300	91,33	10,95
240	107,92	9,27
120	169,48	5,90
20	323,07	3,10

Table 63: Frame rates MF-046

10.7.3 MF-080

$$fps = \frac{1}{T_{ChargeTrans} + T_{Dummy} + T_{Dump} + T_{Scan}}$$

$$fps = \frac{1}{71.93\mu s + 129.48\mu s + (779 - AOI\_HEIGHT) \cdot 8.24\mu s + AOI\_HEIGHT \cdot 63.48\mu s}$$

Formula 4: Frame rate calculation MF-080



AOI_HEIGHT	fps	Tf/ms
778	20,16	49,60
770	20,34	49,16
768	**20,39**	49,04
760	20,57	48,60
500	29,21	34,24
490	29,68	33,69
480	**30,18**	33,14
470	30,69	32,58
460	31,22	32,03
450	31,77	31,48
240	**50,31**	19,88
120	75,48	13,25
110	78,76	12,70
100	82,34	12,14
90	86,27	11,59
80	90,58	11,04

Table 64: Frame rates MF-080

10.7.4 MF-080-30 fps

$$fps = \frac{1}{T_{ChargeTrans} + T_{Dummy} + T_{Dump} + T_{Scan}}$$

$$fps = \frac{1}{47.96\mu s + 86.32\mu s + (779 - AOI\_HEIGHT) \cdot 5.5\mu s + AOI\_HEIGHT \cdot 42.32\mu s}$$

Formula 5: Frame rate calculation MF-080



AOI_HEIGHT	fps	Tf/ms
778	30,24	33,06
768	30,58	32,70
600	37,72	26,51
480	45,26	22,09
240	75,44	13,26
120	113,16	8,84
60	150,88	6,63
30	181,05	5,52

Table 65: Frame rates of MF-080-30f ps

10.7.5 MF-145

$$fps = \frac{1}{T_{Ch\arg eTrans} + T_{Dummy} + T_{Dump} + T_{Scan}}$$

$$fps = \frac{1}{105\mu s + 288\mu s + (1040 - AOI\_HEIGHT)\cdot 19.6\mu s + AOI\_HEIGHT \cdot 92.3\mu s}$$

Formula 6: Frame rate calculation MF-145



AOI_HEIGHT	fps	Tf/ms
1040	10,38	96,39
960	11,04	90,57
600	15,53	64,40
480	17,96	55,67
240	26,16	38,23
120	33,90	29,50
60	39,78	25,14

Table 66: Frame rates MF-145

10.7.6 MF-131

This model uses a CMOS sensor with global shutter. As mentioned earlier for the global shutter, the integration time must be added to the readout time to define the maximum frame rate. The next table gives an example: (it assumes full horizontal width and an integration time of 1 ms). Limiting the field of view in both vertical as well as horizontal direction gives a proportional increase in speed. This is in contrary to CCD sensors where the horizontal image limit does not increase the frame rate.

AOI_HEIGHT	fps
1024	24,42
960	26,01
600	40,97
480	50,69
240	96,46
120	175,84
60	298,78
format7, global-shutter	
1ms integration-time	

Table 67: Frame rates MF-131

In order to calculate the maximum achievable frame rate (with certain shutter time) the following equation can be used:

$$fps = \frac{1}{Width \bullet Height \bullet 0.00000003\,[s] + Shutter\,[s]}$$

Formula 7: Equation for fps @ F-131

11 How does bandwidth affect the frame rate?

In some modes the IEEE-1394a bus limits the attainable frame rate. According to the 1394a specification on isochronous transfer, the largest data payload size of 4096 bytes per 125 µs cycle is possible with bandwidth of 400 Mb/s. In addition, because of a limitation in an IEEE-1394 module (GP2Lynx), only a maximum number of 4095 packets per frame are allowed.

The following formula establishes the relationship between the required Byte_Per_Packet size and certain variables for the image. It is valid only for Format_7.

$$BYTE\_PER\_PACKET = fps \bullet AoiWidth \bullet AoiHeight \bullet ByteDepth \bullet 125\mu s$$

Formula 7: Byte_per_Packet calculation

If the value for "BYTE_PER_PACKET" is greater than 4096 (the maximum data payload), the sought-after frame rate cannot be attained. The attainable frame rate can be calculated using this formula:

(Provision: "BYTE_PER_PACKET" is divisible by 4):

$$fps \approx \frac{BYTE\_PER\_PACKET}{AoiWidth \cdot AoiHeight \cdot ByteDepth \cdot 125\ \mu s}$$

Formula 8: Max. fps Calculation

ByteDepth based on the following values:

Mono8	=> 8 bits/pixel	= 1	byte per pixel
Mono16	=> 16 bits/pixel	= 2	bytes per pixel
YUV4:2:2	=> 16 bits/pixel	= 2	bytes per pixel
YUV4:1:1	=> 12 bits/pixel	= 1.5	bytes per pixel

Example formula for the b/w camera:

Mono16, 1392 x 1040 – 15 fps desired

$$BYTE\_PER\_PACKET = 15 \cdot 1392 \cdot 1040 \cdot 2 \cdot 125\mu s = 5428 > 4096$$

$$\Rightarrow fps_{reachable} \approx \frac{4096}{1392 \cdot 1040 \cdot 2 \cdot 125\mu s} = 11{,}32$$

Formula 9: Example max. fps calculation

11.1 Test images

The b/w cameras have two test images that look the same. Both images show a gray bar running diagonally. One test image is static, the other moves upwards by 1 pixel/frame.

Figure 64: Gray bar test image

Formula for calculating the gray value:

Gray value = (x+y) MOD256 (8-bit mode)

The color cameras have the following test image :

YUV4:2:2 mode

Figure 65: Color test image

Mono8 (raw data):

Figure 66: Bayer-coded test image

The color camera outputs Bayer-coded raw data in Mono8 instead of – as described in IIDC v. 1.3 – a real Y signal. The first pixel of the image is always the red pixel from the sensor.

12 Configuration of the camera

All camera settings are made by writing specific values into the corresponding registers. This applies to both values for general operating states such as video formats and modes, exposure times, etc. and to all extended features of the camera that are turned on and off and controlled via corresponding registers.

12.1 Camera_Status_Register

The interoperability of cameras from different manufacturers is ensured by IIDC, formerly DCAM (Digital Camera Specification), published by the IEEE-1394 Trade Association.
IIDC is primarily concerned with setting memory addresses (e.g. CSR: Camera_Status_Register) and their meaning.

In principle all addresses in IEEE-1394 networks are 64 bits long.

The first 10 bits describe the Bus_Id, the next 6 bits the Node_Id.
Of the subsequent 48 bits, the first 16 are is always FFFFh, leaving the description for the Camera_Status_Register in the last 32 bits.

If in the following, mention is made of a CSR F0F00600h, this means in full:

Bus_Id, Node_Id, FFFF F0F00600h

Writing and reading to and from the register can be done with programs such as “FireView” or by other programs that are developed using an API library(e.g. FirePackage).

Every register is 32 bit (Big Endian) and implemented as follows:



Figure 67: 32-bit register

This requires, for example, that to enable *ISO_Enabled* mode (ISO_Enable / Free-Run), (bit 0 in register 614h), the value 80000000 h must be written in the corresponding register.



Figure 68: Configuration of the camera

Sample program:

The following sample code in C shows how the register is set for frame rate, video mode/format and trigger mode using the FireCtrl DLL from the FirePackage API. Also shown is how the camera is switched into ISO_Enabled mode:

```
...
WriteQuad(m_cmdRegBase + CCR_FRAME-RATE, Frame-Rate << 29);
WriteQuad(m_cmdRegBase + CCR_VMODE, mode << 29);
WriteQuad(m_cmdRegBase + CCR_VFORMAT, format << 29);
WriteQuad(m_cmdRegBase + CCR_TRGMODE, extTrigger ? 0x82000000 : 0);
Sleep(100);
WriteQuad(m_cmdRegBase + CCR_ISOENABLE, 0x80000000);
...
```

12.2 Configuration ROM

The information in the Configuration ROM is needed to identify the node, its capabilities and which drivers are required.

The base address for the "configuration ROM" for all registers is FFFF F0000000h.
The ConfigRom is divided into the

- Bus info block: providing critical information about the bus-related capabilities,
- Root directory: specifying the rest of the content and organization, such as:
  - Node unique ID leaf
  - Unit directory and
  - Unit dependant info

The base address of the camera control register is calculated as follows based on the camera-specific base address:

	Offset	0-7	8-15	16-23	24-31
Bus info block	400h	04	24	45	EE
	404h	31	33	39	34
	408h	20	00	A0	00
	40Ch	00	0A	47	01
	410h	00	00	Serial number	
Root directory	414h	00	04	B7	85
	418h	03	00	0A	47
	41Ch	0C	00	83	C0
	420h	8D	00	00	02
	424h	D1	00	00	04

.... ASCII for 1394

.... Bus capabilities

.... Node_Vendor_Id, Chip_id_hi

.... Chip_id_lo

According to IEEE1212, the root directory may have another length. The keys (e.g. 8D) point to the offset factors rather than the offset (e.g.420h) itself.

Table 68: Config Rom

The entry with key 8D in the root directory (420h in this case) provides the offset for the unique ID leaf node as follows: 420h + 000002 * 4 = 428h

	Offset	0-7	8-15	16-23	24-31
Node unique ID leaf	428h	00	02	CA	71
	42Ch	00	0A	47	01
	430h	00	00	Serial number	

The entry with key D1 in the root directory (424h in this case) provides the offset for the unit directory as follows: 424h + 000004 * 4 = 434h

	Offset	0-7	8-15	16-23	24-31
Unit directory	434h	00	03	93	7D
	438h	12	00	A0	2D
	43Ch	13	00	01	02
	440h	D4	00	00	01

The entry with key D4 in the unit directory (440h in this case) provides the offset for unit dependent info: 440h + 000001 * 4 = 444h

	Offset	0-7	8-15	16-23	24-31
	444h	00	03	7F	89

Unit dependent info	448h	40	3C	00	00
	44Ch	81	00	00	02
	450h	82	00	00	06

Table 69: ConfigRom cont.

And finally, the entry with key 40 (448h in this case) provides the offset for the camera control register:

FFFF F0000000h + 3C0000h * 4 = FFFF F0F00000h

The base address of the camera control register is thus
FFFF F0F00000h.

The offset entered in the table always refers to the base address of F0F00000h.

ⓘ This means that if you want to use the "DirectControl" program to read or write to a register, the following value must be entered in the *Address* field:

"F0F00000h + Offset"

12.3 Implemented registers

The following tables show how standard registers from IIDC v. 1.3 are implemented in the camera. Base address is F0F00000h. Differences and explanations can be found in the third column.

12.3.1 Camera initialize register

Offset	Name	Notes
000h	INITIALIZE	Assert MSB = 1 for Init.

Table 70: Camera initialize register

12.3.2 Inquiry register for video format

Offset	Name	Field	Bit	Description
100h	V_FORMAT_INQ	Format_0	[0]	Up to VGA (non compressed)
		Format_1	[1]	SVGA to XGA
		Format_2	[2]	SXGA to UXGA
		Format_3	[3..5]	Reserved
		Format_6	[6]	Still Image Format
		Format_7	[7]	Partial Image Fomat
		-	[8..31]	Reserved

Table 71: Format inquiry register

12.3.3 Inquiry register for video mode

Offset	Name	Field	Bit	Description
180h	V_MODE_INQ (Format_0)	Mode_0	[0]	160 x 120 YUV 4:4:4
		Mode _1	[1]	320 x 240 YUV 4:2:2
		Mode _2	[2]	640 x 480 YUV 4:1:1
		Mode _3	[3]	640 x 480 YUV 4:2:2
		Mode _4	[4]	640 x 480 RGB
		Mode _5	[5]	640 x 480 MONO8
		Mode _6	[6]	640 x 480 MONO16
		Mode _X	[7]	Reserved
		-	[8..31]	Reserved zero)
184h	V_MODE_INQ (Format_1)	Mode_0	[0]	800 x 600 YUV 4:2:2
		Mode _1	[1]	800 x 600 RGB
		Mode _2	[2]	800 x 600 MONO8
		Mode _3	[3]	1024 x 768 YUV 4:2:2
		Mode _4	[4]	1024 x 768 RGB

		Mode _5	[5]	1024 x 768 MONO8
		Mode _6	[6]	800 x 600 MONO16
		Mode _7	[7]	1024 x 768 MONO16
		-	[8..31]	Reserved (zero)
188h	V_MODE_INQ (Format_2)	Mode_0	[0]	1280 x 960 YUV 4:2:2
		Mode _1	[1]	1280 x 960 RGB
		Mode _2	[2]	1280 x 960 MONO8
		Mode _3	[3]	1600 x 1200 YUV 4:2:2
		Mode _4	[4]	1600 x 1200 RGB
		Mode _5	[5]	1600 x 1200 MONO8
		Mode _6	[6]	1280 x 960 MONO16
		Mode _7	[7]	1600 x 1200 MONO16
		-	[8..31]	Reserved (zero)
18Ch … 197h	Reserved for other V_MODE_INQ_x for Format_x.			always 0
198h	V_MODE_INQ_6 (Format_6)			always 0
19Ch	V_MODE_INQ (Format_7)	Mode_0	[0]	Format_7 Mode_0
		Mode _1	[1]	Format_7 Mode_1
		Mode _2	[2]	Format_7 Mode_2
		Mode _3	[3]	Format_7 Mode_3
		Mode _4	[4]	Format_7 Mode_4
		Mode _5	[5]	Format_7 Mode_5
		Mode _6	[6]	Format_7 Mode_6
		Mode _7	[7]	Format_7 Mode_7
		-	[8..31]	Reserved (zero)

Table 72: Video mode inquiry register

12.3.4 Inquiry register for video frame rate and base address

Offset	Name	Field	Bit	Description
200h	V_RATE_INQ (Format_0, Mode_0)	FrameRate_0	[0]	Reserved
		FrameRate _1	[1]	Reserved
		FrameRate _2	[2]	7.5 fps
		FrameRate _3	[3]	15 fps
		FrameRate _4	[4]	30 fps
		FrameRate _5	[5]	60 fps
		FrameRate _6	[6]	120 fps (v1.31)
		FrameRate _7	[7]	240 fps (v1.31)
		-	[8..31]	Reserved (zero)
204h	V_RATE_INQ (Format_0, Mode_1)	FrameRate_0	[0]	1.875 fps
		FrameRate _1	[1]	3.75 fps
		FrameRate _2	[2]	7.5 fps
		FrameRate _3	[3]	15 fps
		FrameRate _4	[4]	30 fps
		FrameRate _5	[5]	60 fps
		FrameRate _6	[6]	120 fps (v1.31)
		FrameRate _7	[7]	240 fps (v1.31)
		-	[8..31]	Reserved (zero)
208h	V_RATE_INQ (Format_0, Mode_2)	FrameRate_0	[0]	1.875 fps
		FrameRate _1	[1]	3.75 fps
		FrameRate _2	[2]	7.5 fps
		FrameRate _3	[3]	15 fps
		FrameRate _4	[4]	30 fps
		FrameRate _5	[5]	60 fps
		FrameRate _6	[6]	120 fps (v1.31)
		FrameRate _7	[7]	240 fps (v1.31)
		-	[8..31]	Reserved (zero)
20Ch	V_RATE_INQ (Format_0, Mode_3)	FrameRate_0	[0]	1.875 fps
		FrameRate _1	[1]	3.75 fps
		FrameRate _2	[2]	7.5 fps
		FrameRate _3	[3]	15 fps
		FrameRate _4	[4]	30 fps
		FrameRate _5	[5]	60 fps
		FrameRate _6	[6]	120 fps (v1.31)
		FrameRate _7	[7]	240 fps (v1.31)
		-	[8..31]	Reserved (zero)

Offset	Name	Field	Bit	Description
210h	V_RATE_INQ (Format_0, Mode_4)	FrameRate_0	[0]	1.875 fps
		FrameRate _1	[1]	3.75 fps
		FrameRate _2	[2]	7.5 fps
		FrameRate _3	[3]	15 fps
		FrameRate _4	[4]	30 fps
		FrameRate _5	[5]	60 fps
		FrameRate _6	[6]	120 fps (v1.31)
		FrameRate _7	[7]	240 fps (v1.31)
		-	[8..31]	Reserved (zero)
214h	V_RATE_INQ (Format_0, Mode_5)	FrameRate_0	[0]	1.875 fps
		FrameRate _1	[1]	3.75 fps
		FrameRate _2	[2]	7.5 fps
		FrameRate _3	[3]	15 fps
		FrameRate _4	[4]	30 fps
		FrameRate _5	[5]	60 fps
		FrameRate _6	[6]	120 fps (v1.31)
		FrameRate _7	[7]	240 fps (v1.31)
		-	[8..31]	Reserved (zero)
218h	V_RATE_INQ (Format_0, Mode_6)	FrameRate_0	[0]	1.875 fps
		FrameRate _1	[1]	3.75 fps
		FrameRate _2	[2]	7.5 fps
		FrameRate _3	[3]	15 fps
		FrameRate _4	[4]	30 fps
		FrameRate _5	[5]	60 fps
		FrameRate _6	[6]	120 fps (v1.31)
		FrameRate _7	[7]	240 fps (v1.31)
		-	[8..31]	Reserved (zero)
21Ch ... 21Fh	Reserved V_RATE_INQ_0_x (for other Mode_x of Format_0)			always 0
220h	V_RATE_INQ (Format_1, Mode_0)	FrameRate_0	[0]	Reserved
		FrameRate _1	[1]	3.75 fps
		FrameRate _2	[2]	7.5 fps
		FrameRate _3	[3]	15 fps
		FrameRate _4	[4]	30 fps
		FrameRate _5	[5]	60 fps
		FrameRate _6	[6]	120 fps (v1.31)
		FrameRate _7	[7]	240 fps (v1.31)
		-	[8..31]	Reserved (zero)

Offset	Name	Field	Bit	Description
224h	V_RATE_INQ (Format_1, Mode_1)	FrameRate_0	[0]	Reserved
		FrameRate _1	[1]	Reserved
		FrameRate _2	[2]	7.5 fps
		FrameRate _3	[3]	15 fps
		FrameRate _4	[4]	30 fps
		FrameRate _5	[5]	60 fps
		FrameRate _6	[6]	120 fps (v1.31)
		FrameRate _7	[7]	240 fps (v1.31)
		-	[8..31]	Reserved (zero)
228h	V_RATE_INQ (Format_1, Mode_2)	FrameRate_0	[0]	Reserved
		FrameRate _1	[1]	Reserved
		FrameRate _2	[2]	7.5 fps
		FrameRate _3	[3]	15 fps
		FrameRate _4	[4]	30 fps
		FrameRate _5	[5]	60 fps
		FrameRate _6	[6]	120 fps (v1.31)
		FrameRate _7	[7]	240 fps (v1.31)
		-	[8..31]	Reserved (zero)
22Ch	V_RATE_INQ (Format_1, Mode_3)	FrameRate_0	[0]	1.875 fps
		FrameRate _1	[1]	3.75 fps
		FrameRate _2	[2]	7.5 fps
		FrameRate _3	[3]	15 fps
		FrameRate _4	[4]	30 fps
		FrameRate _5	[5]	60 fps
		FrameRate _6	[6]	120 fps (v1.31)
		FrameRate _7	[7]	240 fps (v1.31)
		-	[8..31]	Reserved (zero)
230h	V_RATE_INQ (Format_1, Mode_4)	FrameRate_0	[0]	1.875 fps
		FrameRate _1	[1]	3.75 fps
		FrameRate _2	[2]	7.5 fps
		FrameRate _3	[3]	15 fps
		FrameRate _4	[4]	30 fps
		FrameRate _5	[5]	60 fps
		FrameRate _6	[6]	120 fps (v1.31)
		FrameRate _7	[7]	240 fps (v1.31)
		-	[8..31]	Reserved (zero)
234h	V_RATE_INQ (Format_1, Mode_5)	FrameRate_0	[0]	1.875 fps
		FrameRate _1	[1]	3.75 fps
		FrameRate _2	[2]	7.5 fps

Offset	Name	Field	Bit	Description
		FrameRate _3	[3]	15 fps
		FrameRate _4	[4]	30 fps
		FrameRate _5	[5]	60 fps
		FrameRate _6	[6]	120 fps (v1.31)
		FrameRate _7	[7]	240 fps (v1.31)
		-	[8..31]	Reserved (zero)
238h	V_RATE_INQ (Format_1, Mode_6)	FrameRate_0	[0]	1.875 fps
		FrameRate _1	[1]	3.75 fps
		FrameRate _2	[2]	7.5 fps
		FrameRate _3	[3]	15 fps
		FrameRate _4	[4]	30 fps
		FrameRate _5	[5]	60 fps
		FrameRate _6	[6]	120 fps (v1.31)
		FrameRate _7	[7]	240 fps (v1.31)
		-	[8..31]	Reserved (zero)
23Ch	V_RATE_INQ (Format_1, Mode_7)	FrameRate_0	[0]	1.875 fps
		FrameRate _1	[1]	3.75 fps
		FrameRate _2	[2]	7.5 fps
		FrameRate _3	[3]	15 fps
		FrameRate _4	[4]	30 fps
		FrameRate _5	[5]	60 fps
		FrameRate _6	[6]	120 fps (v1.31)
		FrameRate _7	[7]	Reserved
		-	[8..31]	Reserved (zero)
240h	V_RATE_INQ (Format_2, Mode_0)	FrameRate_0	[0]	1.875 fps
		FrameRate _1	[1]	3.75 fps
		FrameRate _2	[2]	7.5 fps
		FrameRate _3	[3]	15 fps
		FrameRate _4	[4]	30 fps
		FrameRate _5	[5]	60 fps
		FrameRate _6	[6]	Reserved
		FrameRate _7	[7]	Reserved
		-	[8..31]	Reserved (zero)
244h	V_RATE_INQ (Format_2, Mode_1)	FrameRate_0	[0]	1.875 fps
		FrameRate _1	[1]	3.75 fps
		FrameRate _2	[2]	7.5 fps
		FrameRate _3	[3]	15 fps
		FrameRate _4	[4]	30 fps
		FrameRate _5	[5]	60 fps
		FrameRate _6	[6]	Reserved

		FrameRate _7	[7]	Reserved
		-	[8..31]	Reserved (zero)
Offset	**Name**	**Field**	**Bit**	**Description**
248h	V_RATE_INQ (Format_2, Mode_2)	FrameRate_0	[0]	1.875 fps
		FrameRate _1	[1]	3.75 fps
		FrameRate _2	[2]	7.5 fps
		FrameRate _3	[3]	15 fps
		FrameRate _4	[4]	30 fps
		FrameRate _5	[5]	60 fps
		FrameRate _6	[6]	120 fps (v1.31)
		FrameRate _7	[7]	Reserved
		-	[8..31]	Reserved (zero)
24Ch	V_RATE_INQ (Format_2, Mode_3)	FrameRate_0	[0]	1.875 fps
		FrameRate _1	[1]	3.75 fps
		FrameRate _2	[2]	7.5 fps
		FrameRate _3	[3]	15 fps
		FrameRate _4	[4]	30 fps
		FrameRate _5	[5]	60 fps
		FrameRate _6	[6]	Reserved
		FrameRate _7	[7]	Reserved
		-	[8..31]	Reserved (zero)
250h	V_RATE_INQ (Format_2, Mode_4)	FrameRate_0	[0]	1.875 fps
		FrameRate _1	[1]	3.75 fps
		FrameRate _2	[2]	7.5 fps
		FrameRate _3	[3]	15 fps
		FrameRate _4	[4]	30 fps
		FrameRate _5	[5]	Reserved
		FrameRate _6	[6]	Reserved
		FrameRate _7	[7]	Reserved
		-	[8..31]	Reserved (zero)
254h	V_RATE_INQ (Format_2, Mode_5)	FrameRate_0	[0]	1.875 fps
		FrameRate _1	[1]	3.75 fps
		FrameRate _2	[2]	7.5 fps
		FrameRate _3	[3]	15 fps
		FrameRate _4	[4]	30 fps
		FrameRate _5	[5]	60 fps
		FrameRate _6	[6]	Reserved
		FrameRate _7	[7]	Reserved
		-	[8..31]	Reserved (zero)
258h	V_RATE_INQ (Format_2, Mode_6)	FrameRate_0	[0]	1.875 fps
		FrameRate _1	[1]	3.75 fps

		FrameRate _2	[2]	7.5 fps
		FrameRate _3	[3]	15 fps
		FrameRate _4	[4]	30 fps
		FrameRate _5	[5]	60 fps
		FrameRate _6	[6]	Reserved
		FrameRate _7	[7]	Reserved
		-	[8..31]	Reserved (zero)
Offset	**Name**	**Field**	**Bit**	**Description**
25Ch	V_RATE_INQ (Format_2, Mode_7)	FrameRate_0	[0]	1.875 fps
		FrameRate _1	[1]	3.75 fps
		FrameRate _2	[2]	7.5 fps
		FrameRate _3	[3]	15 fps
		FrameRate _4	[4]	30 fps
		FrameRate _5	[5]	60 fps
		FrameRate _6	[6]	Reserved
		FrameRate _7	[7]	Reserved
		-	[8..31]	Reserved
260h ... 2BFh	Reserved V_RATE_INQ_y_x (for other Format_y, Mode_x)			
2C0h	V_REV_INQ_6_0 (Format_6, Mode0)			always 0
2C4h .. 2DFh	Reserved V_REV_INQ_6_x (for other Mode_x of Format_6)			always 0
2E0h	V-CSR_INQ_7_0		[0..31]	CSR_quadlet offset for Format_7 Mode_0
2E4h	V-CSR_INQ_7_1		[0..31]	CSR_quadlet offset for Format_7 Mode_1
2E8h	V-CSR_INQ_7_2		[0..31]	CSR_quadlet offset for Format_7 Mode_2
2ECh	V-CSR_INQ_7_3		[0..31]	CSR_quadlet offset for Format_7 Mode_3
2F0h	V-CSR_INQ_7_4		[0..31]	CSR_quadlet offset for Format_7 Mode_4
2F4h	V-CSR_INQ_7_5		[0..31]	CSR_quadlet offset for Format_7 Mode_5
2F8h	V-CSR_INQ_7_6		[0..31]	CSR_quadlet offset for Format_7 Mode_6
2FCh	V-CSR_INQ_7_7		[0..31]	CSR_quadlet offset for Format_7 Mode_7

Table 73: Frame rate inquiry register

12.3.5 Inquiry register for basic function

Offset	Name	Field	Bit	Description
400h	BASIC_FUNC_INQ	Advanced_Feature_Inq	[0]	Inquiry for advanced features (Vendor unique Features)
		Vmode_Error_Status_Inq	[1]	Inquiry for existence of Vmode_Error_Status register
		Feature_Control_Error_Status_Inq	[2]	Inquiry for existence of Feature_Control_Error_Status
		Opt_Func_CSR_Inq	[3]	Inquiry for Opt_Func_CSR
		-	[4..7]	
		1394b_mode_Capability	[8]	Inquiry for 1394b_mode_Capability
		-	[9..15]	Reserved
		Cam_Power_Cntl	[16]	Camera process power ON/OFF capability
		-	[17..18]	Reserved
		One_Shot_Inq	[19]	One Shot transmission capability
		Multi_Shot_Inq	[20]	Multi Shot transmission capability
		-	[21..27]	Reserved
		Memory_Channel	[28..31]	Maximum memory channel number (N) If 0000, no user memory available

Table 74: Basic function inquiry register

12.3.6 Inquiry register for feature presence

Offset	Name	Field	Bit	Description
404h	FEATURE_HI_INQ	Brightness	[0]	Brightness Control
		Auto_Exposure	[1]	Auto_Exposure Control
		Sharpness	[2]	Sharpness Control
		White_Balance	[3]	White_Balance Control
		Hue	[4]	Hue Control
		Saturation	[5]	Saturation Control
		Gamma	[6]	Gamma Control
		Shutter	[7]	Shutter Control
		Gain	[8]	Gain Control
		Iris	[9]	Iris Control
		Focus	[10]	Focus Control
		Temperature	[11]	Temperature Control
		Trigger	[12]	Trigger Control
		Trigger_Delay	[13]	Trigger_Delay Control

		White_Shading	[14]	White_Shading Control
		Frame_Rate	[15]	Frame_Rate Control
			[16..31]	Reserved
408h	FEATURE_LO_INQ	Zoom	[0]	Zoom Control
		Pan	[1]	Pan Control
		Tilt	[2]	Tilt Control
		Optical_Filter	[3]	Optical_Filter Control
			[4..15]	Reserved
		Capture_Size	[16]	Capture_Size for Format_6
		Capture_Quality	[17]	Capture_Quality for Format_6
			[16..31]	Reserved
40Ch	OPT_FUNCTION_INQ	-	[0]	Reserved
		PIO	[1]	Parallel Input/Output control
		SIO	[2]	Serial Input/Output control
		Strobe_out	[4..31]	Strobe signal output
410h .. 47Fh		Reserved		Address error on access
Offset	**Name**	**Field**	**Bit**	**Description**
480h	Advanced_Feature_Inq	Advanced_Feature_Quadlet_Offset	[0..31]	Quadlet offset of the advanced feature CSR's from the base address of initial register space (Vendor unique) This register is the offset for the Access_Control_Register and thus the base address for Advanced Features. Access_Control_Register does not prevent access to advanced features. In some programs it should still always be activated first. "Advanced Feature Set Unique Value" is 7ACh and CompanyID is A47h.

484h	PIO_Control_CSR_Inq	PIO_Control_Quadlet_Offset	[0..31]	Quadlet offset of the PIO_Control CSR's from the base address of initial register space (Vendor unique)
488h	SIO_Control_CSR_Inq	SIO_Control_Quadlet_Offset	[0..31]	Quadlet offset of the SIO_Control CSR's from the base address of initial register space (Vendor unique)
48Ch	Strobe_Output_CSR_Inq	Strobe_Output_Quadlet_Offset	[0..31]	Quadlet offset of the Strobe_Output signal CSR's from the base address of initial register space (Vendor unique)

Table 75: Feature presence inquiry register

12.3.7 Inquiry register for feature elements

Register	Name	Field	Bit	Description
0xF0F00500	BRIGHTNESS_INQUIRY	Presence_Inq	[0]	Indicates presence of this feature (read only)
		Abs_Control_Inq	[1]	Capability of control with absolute value
		-	[2]	Reserved
		One_Push_Inq	[3]	One Push auto mode (Controlled automatically by the camera once)
		Readout_Inq	[4]	Capability of reading out the value of this feature
		ON_OFF	[5]	Capability of switching this feature ON and OFF
		Auto_Inq	[6]	Auto Mode (Controlled automatically by the camera)
		Manual_Inq	[7]	Manual Mode (Controlled by user)
		Min_Value	[8..19]	Min. value for this feature
		Max_Value	[20..31]	Max. value for this feature
504h	AUTO_EXPOSURE_INQ	Same definition as Brightness_inq.		
508h	SHARPNESS_INQ	Same definition as Brightness_inq.		
50Ch	WHITE_BAL_INQ	Same definition as Brightness_inq.		
510h	HUE_INQ	Same definition as Brightness_inq.		
514h	SATURATION_INQ	Same definition as Brightness_inq.		
518h	GAMMA_INQ	Same definition as Brightness_inq.		
51Ch	SHUTTER_INQ	Same definition as Brightness_inq.		
520h	GAIN_INQ	Same definition as Brightness_inq.		
524h	IRIS_INQ	always 0		
528h	FOCUS_INQ	always 0		
52Ch	TEMPERATURE_INQ	Same definition as Brightness_inq.		

Offset	Name	Field	Bit	Description
530h	TRIGGER_INQ	Presence_Inq	[0]	Indicates presence of this feature (read only)
		Abs_Control_Inq	[1]	Capability of control with absolute value
		-	[2..3	Reserved
		Readout_Inq	[4]	Capability of reading out the value of this feature
		ON_OFF	[5]	Capability of switching this feature ON and OFF
		Polarity_Inq	[6]	Capability of changing the polarity of the rigger input
			[7..15]	Reserved
		Trigger_Mode0_Inq	[16]	Presence of Trigger_Mode 0
		Trigger_Mode1_Inq	[17]	Presence of Trigger_Mode 1
		Trigger_Mode2_Inq	[18]	Presence of Trigger_Mode 2
		Trigger_Mode3_Inq	[19]	Presence of Trigger_Mode 3
			[20..31	Reserved
Offset	**Name**	**Field**	**Bit**	**Description**
534h	TRIGGER_DELAY_INQUIRY	Presence_Inq	[0]	Indicates presence of this feature (read only)
		Abs_Control_Inq	[1]	Capability of control with absolute

				value
		-	[2]	Reserved
		One_Push_Inq	[3]	One Push auto mode Controlled automatically by the camera once)
		Readout_Inq	[4]	Capability of reading out the value of this feature
		ON_OFF	[5]	Capability of switching this feature ON and OFF
		Auto_Inq	[6]	Auto Mode (Controlled automatically by the camera)
		Manual_Inq	[7]	Manual Mode (Controlled by user)
		Min_Value	[8..19]	Min. value for this feature
		Max_Value	[20..31]	Max. value for this feature
538..57Ch	Reserved for other FEATURE_HI_INQ			
580h	ZOOM_INQ	always 0		
584h	PAN_INQ	always 0		
588h	TILT_INQ	always 0		
58Ch	OPTICAL_FILTER_INQ	always 0		
590 .. 5BCh	Reserved for other FEATURE_LO_INQ	always 0		
5C0h	CAPTURE_SIZE_INQ	always 0		
5C4h	CAPTURE_QUALITY_INQ	always 0		
5C8h .. 5FCh	Reserved for other FEATURE_LO_INQ	always 0		
600h	CUR-V-Frm_RATE/Revision	Bits [0..2] for the frame rate		
604h	CUR-V-MODE	Bits [0..2] for the current video mode		
608h	CUR-V-FORMAT	Bits [0..2] for the current video format		
60Ch	ISO-Channel	Bits [0..3] for channel, [6..7] for ISO-speed		

610h	Camera_Power	always 0
614h	ISO_EN/Continuous_Shot	Bit 0: 1 for Cont. Shot; 0 for stop
618h	Memory_Save	always 0
61Ch	One_Shot, Multi_Shot, Count Number	See text
620h	Mem_Save_Ch	always 0
624	Cur_Mem_Ch	always 0
628h	Vmode_Error_Status	Error in combination of Format/Mode/ISO Speed: Bit(0): No error; Bit(0)=1: error

Table 76: Feature elements inquiry register

12.3.8 Inquiry register for absolute value CSR offset address

Offset	Name	Notes
700h	ABS_CSR_HI_INQ_0	always 0
704h	ABS_CSR_HI_INQ_1	always 0
708h	ABS_CSR_HI_INQ_2	always 0
70Ch	ABS_CSR_HI_INQ_3	always 0
710h	ABS_CSR_HI_INQ_4	always 0
714h	ABS_CSR_HI_INQ_5	always 0
718h	ABS_CSR_HI_INQ_6	always 0
71Ch	ABS_CSR_HI_INQ_7	always 0
720h	ABS_CSR_HI_INQ_8	always 0
724h	ABS_CSR_HI_INQ_9	always 0
728h	ABS_CSR_HI_INQ_10	always 0
72Ch	ABS_CSR_HI_INQ_11	always 0
730h	ABS_CSR_HI_INQ_12	always 0
734 .. 77Fh	Reserved	always 0
780h	ABS_CSR_LO_INQ_0	always 0
784h	ABS_CSR_LO_INQ_1	always 0
788h	ABS_CSR_LO_INQ_2	always 0
78Ch	ABS_CSR_LO_INQ_3	always 0
790h .. 7BFh	Reserved	always 0
7C0h	ABS_CSR_LO_INQ_16	always 0
7C4h	ABS_CSR_LO_INQ_17	always 0
7C8h .. 7FFh	Reserved	always 0

Table 77: Absolute value inquiry register

12.3.9 Status and control register for feature

The *OnePush* feature, WHITE_BALANCE, is currently implemented. If this flag is set, the feature becomes immediately active, even if no images are being input (see One Push automatic white balance).

Offset	Name	Notes
800h	BRIGHTNESS	See above
804h	AUTO-EXPOSURE	See above
808h	SHARPNESS	See above
80Ch	WHITE-BALANCE	See above always 0 for Mono
810h	HUE	See above always 0 for Mono
814h	SATURATION	See above always 0 for Mono
818h	GAMMA	See above
81Ch	SHUTTER	see Advanced Feature Timebase
820h	GAIN	See above
824h	IRIS	always 0
828h	FOCUS	always 0
82Ch	TEMPERATURE	always 0
830h	TRIGGER-MODE	Can be effected via Advanced Feature IO_INP_CTRLx.
834h .. 87C	Reserved for other FEATURE_HI	always 0
880h	Zoom	always 0
884h	PAN	always 0
888h	TILT	always 0
88Ch	OPTICAL_FILTER	always 0
890 .. 8BCh	Reserved for other FEATURE_LO	always 0
8C0h	CAPTURE-SIZE	always 0
8C4h	CAPTURE-QUALITY	always 0
8C8h .. 8FCh	Reserved for other FEATURE_LO	always 0

Table 78: Feature control register

12.3.10 Feature control error status register

Offset	Name	Notes
640h	Feature_Control_Error_Status_HI	always 0
644h	Feature_Control_Error_Status_LO	always 0

Table 79: Feature control error register

12.3.11 Video mode control and status registers for Format_7

The offset to the base address is in V-CSR_INQ_7_x. The offset 100h must be added for *Mode 1*, 200h for *Mode 2* 200h and 300h for *Mode 3*.

Offset	Name	Notes
000h	MAX_IMAGE_SIZE_INQ	
004h	UNIT_SIZE_INQ	
008h	IMAGE_POSITION	
00Ch	IMAGE_SIZE	See above
010h	COLOR_CODING_ID	See above
014h	COLOR_CODING_INQ	See above
034h	PIXEL_NUMER_INQ	
038h	TOTAL_BYTES_HI_INQ	
03Ch	TOTAL_BYTES_LO_INQ	
040h	PACKET_PARA_INQ	See above
044h	BYTE_PER_PACKET	See above

Table 80: Format_7 control and status register

ⓘ For all modes in Format_7, *ErrorFlag_1* and *ErrorFlag_2* are refreshed on each access to the Format_7 Register.

ⓘ Contrary to IIDC DCAM v. 1.3, registers relevant to Format_7 are refreshed on each access. The “Setting_1” bit is automatically cleared after each access.

ⓘ When *ErrorFlag_1* or *ErrorFlag_2* are set and Format_7 is configured, no image capture is started.

ⓘ Contrary to IIDC v.1.3, COLOR_CODING_ID is set to a default value after an INITIALIZE or “reset”.

ⓘ Contrary to IIDC DCAM v.1.3, the *UnitBytePerPacket* field is already filled in with a fixed value in the PACKET_PARA_INQ register.

12.4 Advanced features

The camera has a variety of extended features going beyond the possibilities described in IIDC v. 1.3. The following chapter summarizes all available advanced features in ascending register order. The following table gives an overview of all available registers:

Register	Register name	Remarks
0XF1000010	VERSION_INFO	
0XF1000040	ADV_INQ_1	
0XF1000044	ADV_INQ_2	
0XF1000200	MAX_RESOLUTION	
0XF1000208	TIMEBASE	
0XF100020C	EXTD_SHUTTER	
0XF1000210	TEST_IMAGE	
0XF1000220	SEQUENCE_CTRL	except MF131x
0XF1000224	SEQUENCE_PARAM	except MF131x
0XF1000240	LUT_CTRL	
0XF1000244	LUT_MEM_CTRL	
0XF1000248	LUT_INFO	
0XF1000250	SHDG_CTRL	
0XF1000254	SHDG_MEM_CTRL	
0XF1000258	SHDG_INFO	
0XF1000260	DEFERRED_TRANS	
0XF1000270	FRAMEINFO	
0XF1000274	FRAMECOUNTER	
0XF1000280	HDR_CONTROL	MF131x only
0XF1000284	KNEEPOINT_1	MF131x only
0XF1000288	KNEEPOINT_2	MF131x only
0XF100028C	KNEEPOINT_3	MF131x only
0XF1000290	DSNU_CONTROL	MF131B only; Firmware 2.02
0XF1000294	BLEMISH_CONTROL	MF131x only; Firmware 2.02
0XF1000300	IO_INP_CTRL1	
0XF1000304	IO_INP_CTRL2	
0XF1000308	IO_INP_CTRL3	Dolphin series only
0XF1000320	IO_OUTP_CTRL1	
0XF1000324	IO_OUTP_CTRL2	
0XF1000328	IO_OUTP_CTRL3	Dolphin series only
0XF1000340	IO_INTENA_DELAY	
0XF1000360	AUTOSHUTTER_CTRL	Marlin/Oscar series only
0XF1000364	AUTOSHUTTER_LO	Marlin/Oscar series only
0XF1000368	AUTOSHUTTER_HI	Marlin/Oscar series only
0XF1000370	AUTOGAIN_CTRL	Marlin/Oscar series only
0XF1000390	AUTOFNC_AOI	Marlin/Oscar series only
0XF10003A0	COLOR_CORR	Marlin/Oscar CCD type Color cameras only

0XF1000400	TRIGGER_DELAY	
0XF1000410	MIRROR_IMAGE	Marlin/Oscar series only
0XF1000414	MNR	
0XF1000510	SOFT_RESET	
0XF1000FFC	GPDATA_INFO	
0XF1001000	GPDATA_BUFFER	

Table 81: Advanced Registers Summary

Advanced features should always be activated before accessing them.

ⓘ Currently all registers can be written without being activated. This makes it easier to operate the camera using “Directcontrol”.

ⓘ AVT reserves the right to require activation in future versions of the software.

12.4.1 Version information inquiry

The presence of each of the following features can be queried by the "0" bit of the corresponding register.

Register	Name	Field	Bit	Description
F1000010	VERSION_INFO1	µC type ID	[0..15]	Reserved
		µC version	[16..31]	Bcd-coded vers.#
F1000014			[0..31]	Reserved
F1000018	VERSION_INFO3	Camera type ID	[0..15]	See below
		FPGA version	[16..31]	Bcd-coded vers.#
F100001C			[0..31]	Reserved

Table 82: Version information register

This register holds information about the node_hw_version, the node_sw_version and the node_spec_ID (camera type). µC version and FPGA version are bcd-coded, which means that e.g. firmware version 0.85 is read as 0x0085. The FPGA type ID identifies the camera type with the help of the following list:

ID	camera type
1	F145b
2	F145c
3	F201b
4	F201c
5	F145b-1
6	F145c-1
7	F201b-1
8	F201c-1
9	MF033B
10	MF033C
11	MF046B
12	MF046C
13	MF080B
14	MF080C
15	MF145B2
16	MF145C2
17	MF131B
18	MF131C
19	MF145B2-15fps
20	MF145C2-15fps

ID	camera type
21	M2F033B
22	M2F033C
23	M2F046B
24	M2F046C
25	M2F080B
26	M2F080C
27	M2F145B2
28	M2F145C2
31	M2F145B2-15fps
32	M2F145C2-15fps
38	OF320C
40	OF510C
42	OF810C
43	M2F080B-30fps
44	M2F080C-30fps

Table 83: Camera type ID list

ⓘ Marlins with serial numbers beginning with 6xx identify itself as M2F...

12.4.2 Advanced feature inquiry

Register	Name	Field	Bit	Description
0xF1000040	ADV_INQ_1	MaxResolution	[0]	
		TimeBase	[1]	
		ExtdShutter	[2]	
		TestImage	[3]	
		FrameInfo	[4]	
		Sequences	[5]	
		VersionInfo	[6]	
		-	[7]	
		Lookup Tables	[8]	
		Shading	[9]	
		DeferredTrans	[10]	
		HDR mode	[11]	MF-131B/C only
		DSNU	[12]	MF-131B only
		Blemish correction	[13]	MF-131B only
		TriggerDelay	[14]	
		Misc. features	[15]	
		Soft Reset	[16]	
		High SNR	[17]	Oscar only
		Color Correction	[18]	
		-	[19..30]	
		GP_Buffer	[31]	
0xF1000044	ADV_INQ_2	Input_1	[0]	
		Input_2	[1]	
		-	[2]	
		-	[3..7]	
		Output_1	[8]	
		Output_2	[9]	
		-	[10]	
		-	[11..15]	
		IntEnaDelay	[16]	
		-	[17]	
		-	[18..31]	
0xF1000048	ADV_INQ_3	-	[0..31]	
0xF100004C	ADV_INQ_4	-	[0..31]	

Table 84: Advanced feature inquiry register

12.4.3 MaxResolution

This register indicates the highest resolution for the sensor and is read-only.
This register normally outputs the MAX_IMAGE_SIZE_INQ Format_7 Mode_0 value.

Register	Name	Field	Bit	Description
0xF1000200	MAX_RESOLUTION	MaxHeight	[0..15]	Sensor height (rd only)
		MaxWidth	[16..31]	Sensor width (rd only)

Table 85: Max. resolution inquiry register

12.4.4 Timebase

Corresponding to IIDC, exposure time is set via a 12-bit value in the corresponding register (SHUTTER_INQ [51Ch] and SHUTTER [81Ch]).
This means that a value in the range of 1 to 4095 can be entered.

Marlin cameras use a time-base which is multiplied by the shutter register value. This multiplier is configured as the time base via the TIMEBASE register.

Register	Name	Field	Bit	Description
0xF1000208	TIMEBASE	Presence_Inq	[0]	Indicates presence of this feature (read only)
		---	[1..27]	
		Timebase_ID	[28..31]	

Table 86: Timebase configuration register

IDs 0-9 are in bits 28 to 31. Refer to the following table for code. Default time-base is 20µs.

This means that the integration time can be changed in 20 µs increments with the shutter control.

ⓘ Time-base can only be changed when the camera is in idle state and becomes active only after setting the shutter value.

ID	Timebase			ID	Timebase	
0	1	µs		5	50	µs
1	2	µs		6	100	µs
2	5	µs		7	200	µs
3	10	µs		8	500	µs
4	20	µs		9	1000	µs

Table 87: Timbease ID

ⓘ The ABSOLUTE VALUE CSR register, introduced in IIDC v. 1.3, is not implemented.

12.4.5 Extended shutter

The exposure time for long-term integration of up to 67 sec can be entered with µs- precision via the EXTENDED_SHUTTER register.

Register	Name	Field	Bit	Description
0xF100020C	EXTD_SHUTTER	Presence_Inq	[0]	Indicates presence of this feature (read only)
		---	[1.. 5]	
		ExpTime	[6..31]	Exposure time in µs

Table 88: Extended shutter configuration register

The longest exposure time, 3FFFFFFh, corresponds to 67.11 sec.

- ⓘ Exposure times entered via the 81Ch register are mirrored in the extended register, but not vice versa.
- ⓘ Changes in this register have immediate effect, even when camera is transmitting.
- ⓘ Extended shutter becomes inactive after writing to a format/mode/framerate register.
- ⓘ Extended shutter setting will thus be overwritten by the normal timebase/shutter setting after Stop/Start of FireView or FireDemo.

12.4.6 Test images

Bits 8-14 indicate which test images are saved. Setting bits “28-31” activates or deactivates existing test images.

Register	Name	Field	Bit	Description
0xF1000210	TEST_IMAGE	Presence_Inq	[0]	Indicates presence of this feature (read only)
		---	[1..7	
		Image_Inq_1	[8]	Presence of test image 1 0: N/A 1: Available
		Image_Inq_2	[9]	Presence of test image 2 0: N/A 1: Available
		Image_Inq_3	[10]	Presence of test image 3 0: N/A 1: Available
		Image_Inq_4	[11]	Presence of test image 4 0: N/A 1: Available
		Image_Inq_5	[12]	Presence of test image 5 0: N/A 1: Available
		Image_Inq_6	[13]	Presence of test image 6 0: N/A 1: Available
		Image_Inq_7	[14]	Presence of test image 7 0: N/A 1: Available
		---	[15..27]	
		TestImage_ID	[28..31]	0: No test image active 1: Image 1 active 2: Image 2 active …

Table 89: Test image configuration register

12.4.7 Sequence control

It is possible to make certain settings for a sequence of images beforehand by using this register.

Register	Name	Field	Bit	Description
0xF1000220	SEQUENCE_CTRL	Presence_Inq	[0]	Indicates presence of this feature (read only)
		---	[1..4]	
		AutoRewind	[5]	
		ON_OFF	[6]	Enable/Disable this feature
		---	[7..15]	
		MaxLength	[16..23]	Max. possible length of a sequence (read only)
		SeqLength	[24..31]	Length of the sequence
0xF1000224	SEQUENCE_PARAM	---	[0..4]	
		ApplyParameters	[5]	Apply settings to selected image of sequence; auto-reset
		IncImageNo	[6]	Increment ImageNo after ApplyParameters has finished
		---	[7..23]	
		ImageNo	[24..31]	Number of image within a sequence

Table 90: Sequence control register

12.4.8 Lookup tables (LUT)

The LUT_CTRL register activates this feature and enables certain LUTs. The LUT_INFO register indicates how many LUTs the camera can store and the maximum size of the individual LUTs.

Register	Name	Field	Bit	Description
0xF1000240	LUT_CTRL	Presence_Inq	[0]	Indicates presence of this feature (read only)
		---	[1..5]	-
		ON_OFF	[6]	Enable/Disable this feature
		---	[7..25]	-
		LutNo	[26..31]	Use lookup table with number LutNo
0xF1000244	LUT_MEM_CTRL	Presence_Inq	[0]	Indicates presence of this feature (read only)
		---	[1..4]	
		EnableMemWR	[5]	Enable write access
		---	[6..7]	
		AccessLutNo	[8..15]	
		AddrOffset	[16..31]	
0xF1000248	LUT_INFO	Presence_Inq	[0]	Indicates presence of this feature (read only)
		---	[1..7]	
		NumOfLuts	[8..15]	Max. # of lookup tables
		MaxLutSize	[16..31]	Max. lookup table size

Table 91: LUT control register

12.4.9 Shading correction

Owing to technical circumstances, the interaction of recorded objects with one another, optical effects and lighting non-homogeneities may occur in the images.

Because these effects are normally not desired, they should be eliminated as far as possible in subsequent image editing. The camera has automatic shading correction to do this.

Provided that a shading image is present in the camera, the *on/off* bit can be used to enable shading correction.

The “on/off” and “ShowImage” bits must be set for saved shading images to be displayed.

ⓘ Always make sure that the shading image is saved at the highest resolution of the camera. If a lower resolution is chosen and *ShowImage* is set to “true”, the image will not be displayed correctly.

Register	Name	Field	Bit	Description
0xF1000250	SHDG_CTRL	Presence_Inq	[0]	Indicates presence of this feature (read only)
		BuildError	[1]	tbd
		---	[2..3]	
		ShowImage	[4]	Show shading data as image
		BuildImage	[5]	Build a new ShadingImage
		ON_OFF	[6]	Shading On/Off
		Busy	[7]	Build in progress
		---	[8..23]	
		GrabCount	[24..31]	Number of images
0xF1000254	SHDG_MEM_CTRL	Presence_Inq	[0]	Indicates presence of this feature (read only)
		---	[1..4]	
		EnableMemWR	[5]	Enable write access
		EnableMemRD	[6]	Enable read access
		---	[7]	
		AddrOffset	[8..31]	In bytes
0xF1000258	SHDG_INFO	Presence_Inq	[0]	Indicates presence of this feature (read only)
		---	[1..7]	
		MaxImageSize	[8..31]	Max. ShadingImage size (Bytes)

Table 92: Shading control register

12.4.10 Deferred image transport

Using the register, the sequence of recording and the transfer of the images can be paused. Setting “HoldImg” prevents transfer of the image. The images are stored in *ImageFIFO*.

The images indicated by *NumOfImages* are sent by setting the “SendImage” bit.

When “FastCapture” is set (in Format_7 only), images are recorded at the highest possible frame rate.

Register	Name	Field	Bit	Description
0xF1000260	DEFERRED_TRANS	Presence_Inq	[0]	Indicates presence of this feature (read only)
		---	[1..4]	
		SendImage	[5]	Send NumOfImages now (auto reset)
		HoldImg	[6]	Enable/Disable deferred transport mode
		FastCapture	[7]	Enable/disable fast capture mode
		---	[8..15]	
		FiFoSize	[16..23]	Size of FiFo in number of images (read only)
		NumOfImages	[24..31]	W: Number of images to send R: Number of images in buffer

Table 93: Deferred image configuration register

12.4.11 Frame information

This register can be used to double check the number of images received by the host computer against the number of images which were transmitted by the camera. The camera increments this counter with every FrameValid signal.

Register	Name	Field	Bit	Description
0xF1000270	FRAMEINFO	Presence_Inq	[0]	Indicates presence of this feature (read only)
		ResetFrameCnt	[1]	Reset frame counter
		---	[2..31]	
0xF1000274	FRAMECOUNTER	FrameCounter	[0..31]	Number of captured frames since last reset

Table 94: Frame information register

12.4.12 High dynamic range mode (MF-131B/C only)

The CMOS sensor of the MF-131 offers a special mode by which various nonlinearity points, the so-called knee-points, can be freely adjusted. This enables the high dynamic range of the sensor to be compressed into 8 Bit, preserving interesting details of the image. This mode is also known as multiple slope (dual slope).

Register	Name	Field	Bit	Description
0xF1000280	HDR_CONTROL	Presence_Inq	[0]	Indicates presence of this feature (read only)
		---	[1..5]	
		ON_OFF	[6]	Enable/disable HDR mode
		---	[7..19]	
		MaxKneePoints	[20…23]	Number of knee-points possible in this mode
		---	[24..27]	
		KneePoints	[28..31]	Number of active knee-points
0xF1000284	KNEEPOINT_1	---	[0..15]	
0xF1000284		Kneepoint1	[16..31]	Time in µs
0xF1000288	KNEEPOINT_2	---	[0..15]	
0xF1000288		Kneepoint2	[16..31]	Time in µs
0xF100028C	KNEEPOINT_3	---	[0..15]	
0xF100028C		Kneepoint3	[16..31]	Time in µs

Table 95: High dynamic range configuration register

12.4.13 DSNU control

The table below shows the advanced register map, required to control this functionality.

Register	Name	Field	Bit	Description
0xF1000290	DSNU_CONTROL	Presence_Inq	[0]	Indicates presence of this feature (read only)
		ComputeError	[1]	tbd
		---	[2..3]	
		ShowImage	[4]	Show correction data as image
		ComputeData	[5]	Compute new DSNU correction data
		ON_OFF	[6]	DSNU correction On/Off OFF: High
		Busy	[7]	Computation in progress

		---	[8]	
		LoadData	[9]	load factory DSNU correction data
		ZeroData	[10]	zero DSNU correction data
		---	[11..23]	
		GrabCount	[24..31]	Number of images

Table 96: Register for controlling DSNU correction

Having generated the correction data it is possible to separately control the blemish pixel correction with the help of the following register:

Register	Name	Field	Bit	Description
0xF1000294	BLEMISH_CONTROL	Presence_Inq	[0]	Indicates presence of this feature (read only)
		ComputeError	[1]	see DSNU_CONTROL
		---	[2..3]	
		ShowImage	[4]	see DSNU_CONTROL
		ComputeData	[5]	see DSNU_CONTROL
		ON_OFF	[6]	blemish correction On/Off ON: High Default: OFF
		Busy	[7]	see DSNU_CONTROL
		---	[8]	
		LoadData	[9]	see DSNU_CONTROL
		ZeroData	[10]	see DSNU_CONTROL
		---	[11..23]	
		GrabCount	[24..31]	see DSNU_CONTROL

Table 97: Blemish Control

12.4.14 Input/output pin control

All input and output signals running over the HiRose plug are controlled by this register.

Register	Name	Field	Bit	Description
0xF1000300	IO_INP_CTRL1	Presence_Inq	[0]	Indicates presence of this feature (read only)
		---	[1..6]	
		Polarity	[7]	0: low active, 1: high active
		---	[8..10]	
		InputMode	[11..15]	Mode
		---	[16..30]	
		PinState	[31]	RD: Current state of pin
0xF1000304	IO_INP_CTRL2	Same as IO_INP_CTRL1		

Table 98: Input control configuration register

IO_INP_CTRL 1-2

The *Polarity* flag determines whether the input is low active (0) or high active (1). The *input mode* can be seen in the following table. The *PinState* flag is used to query the current status of the input.

For inputs, the *PinState* bit refers to the inverted output side of the optical coupler. This means that an open input sets the *PinState* bit to "1".

ID	Mode	Default
0x00	Off	
0x01	reserved	
0x02	Trigger input	Input 1
0x03	reserved	
0x04	reserved	
0x05	tbd (SPI external DCLK)	
0x06..0x0F	reserved	
0x10..0x1F	reserved	

Table 99: Input routing

Trigger

If more than one input is being operated in *trigger mode*, these inputs are logically linked by AND.

IO_OUTP_CTRL 1-2

The *Polarity* flag determines whether the output is low active (0) or high active (1). The *output mode* can be seen in the following table. The current status of the output and be queried and set via the *PinState* flag.

Register	Name	Field	Bit	Description
0xF1000320	IO_OUTP_CTRL1	Presence_Inq	[0]	Indicates presence of this feature (read only)
		---	[1..6]	-
		Polarity	[7]	0: low active, 1: high active
		---	[8..10]	
		Output mode	[11..15]	Mode
		---	[16..30]	
		PinState	[31]	RD: Current state of pin WR: New state of pin
0xF1000324	IO_OUTP_CTRL2	Same as IO_OUTP_CTRL1		

Table 100: Output control configuration register

Output mode

ID	Mode	Default
0x00	Off	
0x01	Output state follows 'PinState' bit	
0x02	Integration enable	Output 1
0x03	reserved	
0x04	tbd (SPI internal DCLK)	
0x05	tbd (SPI external DCLK)	
0x06	FrameValid	
0x07	Busy	
0x08	Follow corresponding input (Inp1 → Out1, Inp2 → Out2, …)	Output 2
0x09..0x0F	reserved	
0x10..0x1F	reserved	

Table 101: Output ID

The "Polarity" setting refers to the input side of the inverting optical coupler output, "PinState 0" switches off the output transistor and produces high level over the resistor.

12.4.15 Delayed Integration enable

A delay time between initiating exposure on the sensor and the activation edge of the IntEna signal can be set using this register. The *on/off* flag activates/deactivates integration delay. The time can be set in µs in *DelayTime*.

ⓘ Please note that only one edge is delayed.
ⓘ If *IntEna_Out* is used to control an exposure, it is possible to have a variation in brightness or to precisely time a flash.



Figure 69: Delayed integration timing

Register	Name	Field	Bit	Description
0xF1000340	IO_INTENA_DELAY	Presence_Inq	[0]	Indicates presence of this feature (read only)
		---	[1..5]	
		ON_OFF	[6]	Enable/Disable integration enable delay
		---	[7..11]	
		DELAY_TIME	[12..31]	Delay time in µs

Table 102: Delayed integration configuration register

12.4.16 Auto shutter

The table below illustrates the advanced register for auto shutter control. Purpose of this register is to limit the range within auto shutter is working.

Register	Name	Field	Bit	Description
0xF1000360	AUTOSHUTTER_CTRL	Presence_Inq	[0]	Indicates presence of this feature (read only)
			[1..31]	-
0xF1000364	AUTOSHUTTER_LO	Min Value	[0..31]	Min value
0xF1000368	AUTOSHUTTER_HI	Max Value	[0..31]	Max value

TableTable 103: Auto shutter ctrl. advanced register

12.4.17 Auto gain

The table below illustrates the advanced auto gain control register.

Register	Name	Field	Bit	Description
0xF1000370	AUTOGAIN_CTRL	Presence_Inq	[0]	Indicates presence of this feature (read only)
			[1..3]	-
	MAXVALUE	Max Value	[4..15]	Max value
		-	[16..19]	-
	MAXVALUE	Min value	[20..31]	Min value

Table 104: Advanced register for auto gain control

12.4.18 Auto function AOI

AUTOFNC_AOI affects the auto shutter, auto gain and auto white balance features and is independent of the Format7 AOI settings. If this feature is switched off the work area position and size follow the current active image size.
As a reference it uses a grid of at least 300 samples equally spread over the area of interest or a fraction of it. The position and size of the control area (Auto_Function_AOI) can be set via the following advanced registers.

Register	Name	Field	Bit	Description
0xF1000390	AUTOFNC_AOI	Presence_Inq	[0]	Indicates presence of this feature (read only)
			[1..3]	-
		ShowWorkArea	[4]	Show work area
			[5]	-
		ON_OFF	[6]	Enable/Disable AOI
			[7..31]	-
0xF1000394	AF_AREA_POSITION	Left	[0..15]	work area position
		Top	[16..31]	
0xF1000398	AF_AREA_SIZE	Width	[0..15]	work area size
		Height	[16..31]	

Table 105: Advanced registe: AUTOFNC_AOI

The possible increment of the work area position and size is 128 pixel. The camera automatically adjusts your settings to allowed values.

12.4.19 Color correction

Color correction can also be switched off in YUV mode with the help of the following register.

Register	Name	Field	Bit	Description
0xF10003A0	COLOR_CORR	Marlin C-type CCD cameras only: Write: 02000000h to switch Color correction OFF Write: 00000000h to switch Color correction ON (Default)		

Table 106: Color correction

12.4.20 Trigger delay

Register	Name	Field	Bit	Description
0xF1000400	TRIGGER_DELAY	Presence_Inq	[0]	Indicates presence of this feature (read only)
		---	[1..5]	-
		ON_OFF	[6]	Trigger delay on/off
		---	[7..10]	-
		DelayTime	[11..31]	Delay time in µs

Table 107: Trigger Delay Advanced CSR

The advanced register allows to delay the start of the integration by max. 2^{21} µs, which is max. 2.1s after a trigger edge was detected.

12.4.21 Mirror

All Marlin cameras are equipped with an electronic mirror function, which mirrors pixels from the left side of the image to the right side and vice versa. The mirror is centered to the actual FOV center and can be combined with all image manipulation functions, like binning, shading and DSNU.

Register	Name	Field	Bit	Description
0xF1000410	MIRROR_CONTROL	Presence_Inq	[0]	Indicates presence of this feature (read only)
		-	[1..5]	
		-	[6]	ON/OFF this feature: HIGH for ON, default :OFF
		-	[7..31]	

Table 108: Mirror control register

12.4.22 GPDATA_BUFFER

GPDATA_BUFFER is a register that regulates the exchange of data between camera and host for programming the LUT and the upload/download of the shading image.

GPDATA_INFO Buffer size query
GPDATA_BUFFER indicates the actual storage range

Register	Name	Field	Bit	Description
0xF1000FFC	GPDATA_INFO	---	[0..15]	
		BufferSize	[16..31]	Size of GPDATA_BUFFER (byte)
0xF1001000	GPDATA_BUFFER			
…				
0xF10017FC				

Table 109: GPData buffer register

ⓘ GPDATA_BUFFER can be used by only one function at a time.

12.4.23 Soft Reset

Register	Name	Field	Bit	Description
0xF1000510	SOFT_RESET	Presence Inquiry	[0]	Read only
			[1..5]	Reserved
		Reset	[6]	Initiate reset
			[7..19]	Reserved
	DELAY		[20..31]	Delay reset in 10ms steps

The SOFT_RESET feature is similar to the INITIALIZE register, with the following differences:

- 1 or more bus reset will occur
- the FPGA will be rebooted

The reset can be delayed by setting the Delay to a value unequal to 0 – the delay is defined in 10ms steps.

ⓘ Once the SOFT_RESET is issued the camera further responds to read or write requests, but will not process these requests!

13 Firmware update

Firmware updates are possible without opening the camera.

You need:

- Programming cable E 1000666
- Software “AVTCamProg”
- PC or laptop with serial Interface (RS 232)
- Documentation for firmware update

ⓘ Please make sure that the new Marlin firmware matches with the serial numbering. This means Marlins with serial numbers xx/yy-6zzzzzzz need different firmware than Marlins with other serial numbers.

ⓘ Any mixture may result in an nonfunctional or even damaged camera.

Please contact your local dealer for further information.

14 Declarations of conformity

Allied Vision Technologies GmbH · Taschenweg 2a · 07646 Stadtroda

Telefon: 03 64 28 / 677-0
Telefax
Zentrale: 03 64 28 / 6 77 - 24
Vertrieb: 03 64 28 / 6 77 - 28
eMail: info@alliedvisiontec.com
Internet: www.alliedvisiontec.com
Zertifiziert nach DIN ISO 9001
Zertifikat EN 1994 - 08

DECLARATION OF CONFORMITY

We Allied Vision Technologies GmbH

Taschenweg 2a, 07646 Stadtroda, Germany

declare under our sole responsibility that the product

Category Name	Digital black/white Camera (IEEE 1394)
Model Name:	Marlin F-033B

to which this declaration relates is in conformity with the following standard(s) or other normative document(s)

EN 55022; EN 55024; EN 61000; FCC Class A

Following the provisions of 89/336/EEC directive(s) , amended by Directive 91/263 EEC, 92/31/EEC and 93/68/EEC

Stadtroda, November 20th, 2003

Frank Grube
Managing Director

Allied Vision Technologies GmbH · Taschenweg 2a · 07646 Stadtroda

Telefon: 03 64 28 / 677-0
Telefax
Zentrale: 03 64 28 / 6 77 - 24
Vertrieb: 03 64 28 / 6 77 - 28
eMail: info@alliedvisiontec.com
Internet: www.alliedvisiontec.com
Zertifiziert nach DIN ISO 9001
Zertifikat EN 1994 - 08

DECLARATION OF CONFORMITY

We Allied Vision Technologies GmbH

Taschenweg 2a, 07646 Stadtroda, Germany

declare under our sole responsibility that the product

Category Name	Digital color Camera (IEEE 1394)
Model Name:	Marlin F-033C

to which this declaration relates is in conformity with the following standard(s) or other normative document(s)

EN 55022; EN 55024; EN 61000; FCC Class A

Following the provisions of 89/336/EEC directive(s) , amended by Directive 91/263 EEC, 92/31/EEC and 93/68/EEC

Stadtroda, November 20th, 2003

Frank Grube
Managing Director

Allied Vision Technologies GmbH · Taschenweg 2a · 07646 Stadtroda

Telefon: 03 64 28 / 677-0
Telefax
Zentrale: 03 64 28 / 6 77 - 24
Vertrieb: 03 64 28 / 6 77 - 28
eMail: info@alliedvisiontec.com
Internet: www.alliedvisiontec.com
Zertifiziert nach DIN ISO 9001
Zertifikat EN 1994 - 08

DECLARATION OF CONFORMITY

We Allied Vision Technologies GmbH

Taschenweg 2a, 07646 Stadtroda, Germany

declare under our sole responsibility that the product

Category Name	Digital black/white Camera (IEEE 1394)
Model Name:	Marlin F-046B

to which this declaration relates is in conformity with the following standard(s) or other normative document(s)

EN 55022; EN 55024; EN 61000; FCC Class A

Following the provisions of 89/336/EEC directive(s) , amended by Directive 91/263 EEC, 92/31/EEC and 93/68/EEC

Stadtroda, November 20th, 2003

Frank Grube
Managing Director

Allied Vision Technologies GmbH · Taschenweg 2a · 07646 Stadtroda

Telefon: 03 64 28 / 677-0
Telefax
Zentrale: 03 64 28 / 6 77 - 24
Vertrieb: 03 64 28 / 6 77 - 28
eMail: info@alliedvisiontec.com
Internet: www.alliedvisiontec.com
Zertifiziert nach DIN ISO 9001
Zertifikat EN 1994 - 08

DECLARATION OF CONFORMITY

We Allied Vision Technologies GmbH

Taschenweg 2a, 07646 Stadtroda, Germany

declare under our sole responsibility that the product

Category Name	Digital color Camera (IEEE 1394)
Model Name:	Marlin F-046C

to which this declaration relates is in conformity with the following standard(s) or other normative document(s)

EN 55022; EN 55024; EN 61000; FCC Class A

Following the provisions of 89/336/EEC directive(s) , amended by Directive 91/263 EEC, 92/31/EEC and 93/68/EEC

Stadroda, November 20th, 2003

Frank Grube
Managing Director

Allied Vision Technologies GmbH · Taschenweg 2a · 07646 Stadtroda

Telefon: 03 64 28 / 677-0
Telefax
Zentrale: 03 64 28 / 6 77 - 24
Vertrieb: 03 64 28 / 6 77 - 28
eMail: info@alliedvisiontec.com
Internet: www.alliedvisiontec.com
Zertifiziert nach DIN ISO 9001
Zertifikat EN 1994 - 08

DECLARATION OF CONFORMITY

We Allied Vision Technologies GmbH

Taschenweg 2a, 07646 Stadtroda, Germany

declare under our sole responsibility that the product

Category Name	Digital black/white Camera (IEEE 1394)
Model Name:	Marlin F-080B

to which this declaration relates is in conformity with the following standard(s) or other normative document(s)

EN 55022; EN 55024; EN 61000; FCC Class A

Following the provisions of 89/336/EEC directive(s) , amended by Directive 91/263 EEC, 92/31/EEC and 93/68/EEC

Stadroda, November 20th, 2003

Frank Grube
Managing Director

Allied Vision Technologies GmbH · Taschenweg 2a · 07646 Stadtroda

Telefon: 03 64 28 / 677-0
Telefax
Zentrale: 03 64 28 / 6 77 - 24
Vertrieb: 03 64 28 / 6 77 - 28
eMail: info@alliedvisiontec.com
Internet: www.alliedvisiontec.com
Zertifiziert nach DIN ISO 9001
Zertifikat EN 1994 - 08

DECLARATION OF CONFORMITY

We Allied Vision Technologies GmbH

Taschenweg 2a, 07646 Stadtroda, Germany

declare under our sole responsibility that the product

Category Name	Digital color Camera (IEEE 1394)
Model Name:	Marlin F-080C

to which this declaration relates is in conformity with the following standard(s) or other normative document(s)

EN 55022; EN 55024; EN 61000; FCC Class A

Following the provisions of 89/336/EEC directive(s) , amended by Directive 91/263 EEC, 92/31/EEC and 93/68/EEC

Stadtroda, November 20th, 2003

Frank Grube
Managing Director

Allied Vision Technologies GmbH · Taschenweg 2a · 07646 Stadtroda

Telefon: 03 64 28 / 677-0
Telefax
Zentrale: 03 64 28 / 6 77 - 24
Vertrieb: 03 64 28 / 6 77 - 28
eMail: info@alliedvisiontec.com
Internet: www.alliedvisiontec.com
Zertifiziert nach DIN ISO 9001
Zertifikat EN 1994 - 08

DECLARATION OF CONFORMITY

We Allied Vision Technologies GmbH

Taschenweg 2a, 07646 Stadtroda, Germany

declare under our sole responsibility that the product

Category Name	Digital black/white Camera (IEEE 1394)
Model Name:	Marlin F-145B2

to which this declaration relates is in conformity with the following standard(s) or other normative document(s)

EN 55022; EN 55024; EN 61000; FCC Class A

Following the provisions of 89/336/EEC directive(s) , amended by Directive 91/263 EEC, 92/31/EEC and 93/68/EEC

Stadtroda, November 20th, 2003

Frank Grube
Managing Director

Allied Vision Technologies GmbH · Taschenweg 2a · 07646 Stadtroda

Telefon: 03 64 28 / 677-0
Telefax
Zentrale: 03 64 28 / 6 77 - 24
Vertrieb: 03 64 28 / 6 77 - 28
eMail: info@alliedvisiontec.com
Internet: www.alliedvisiontec.com
Zertifiziert nach DIN ISO 9001
Zertifikat EN 1994 - 08

DECLARATION OF CONFORMITY

We Allied Vision Technologies GmbH

Taschenweg 2a, 07646 Stadtroda, Germany

declare under our sole responsibility that the product

Category Name	Digital color Camera (IEEE 1394)
Model Name:	Marlin F-145C2

to which this declaration relates is in conformity with the following standard(s) or other normative document(s)

EN 55022; EN 55024; EN 61000; FCC Class A

Following the provisions of 89/336/EEC directive(s) , amended by Directive 91/263 EEC, 92/31/EEC and 93/68/EEC

Stadtroda, November 20th, 2003

Frank Grube
Managing Director

Allied Vision Technologies GmbH · Taschenweg 2a · 07646 Stadtroda

Telefon: 03 64 28 / 677-0
Telefax
Zentrale: 03 64 28 / 6 77 - 24
Vertrieb: 03 64 28 / 6 77 - 28
eMail: info@alliedvisiontec.com
Internet: www.alliedvisiontec.com
Zertifiziert nach DIN ISO 9001
Zertifikat EN 1994 - 08

DECLARATION OF CONFORMITY

We Allied Vision Technologies GmbH

Taschenweg 2a, 07646 Stadtroda, Germany

declare under our sole responsibility that the product

Category Name	Digital black/white Camera (IEEE 1394)
Model Name:	Marlin F-131B

to which this declaration relates is in conformity with the following standard(s) or other normative document(s)

EN 55022; EN 55024; EN 61000; FCC Class A

Following the provisions of 89/336/EEC directive(s) , amended by Directive 91/263 EEC, 92/31/EEC and 93/68/EEC

Stadtroda, November 20th, 2003

Frank Grube
Managing Director

Allied Vision Technologies GmbH · Taschenweg 2a · 07646 Stadtroda

Telefon: 03 64 28 / 677-0
Telefax
Zentrale: 03 64 28 / 6 77 - 24
Vertrieb: 03 64 28 / 6 77 - 28
eMail: info@alliedvisiontec.com
Internet: www.alliedvisiontec.com
Zertifiziert nach DIN ISO 9001
Zertifikat EN 1994 - 08

DECLARATION OF CONFORMITY

We Allied Vision Technologies GmbH

Taschenweg 2a, 07646 Stadtroda, Germany

declare under our sole responsibility that the product

Category Name	Digital color Camera (IEEE 1394)
Model Name:	Marlin F-131C

to which this declaration relates is in conformity with the following standard(s) or other normative document(s)

EN 55022; EN 55024; EN 61000; FCC Class A

Following the provisions of 89/336/EEC directive(s) , amended by Directive 91/263 EEC, 92/31/EEC and 93/68/EEC

Stadtroda, November 20th, 2003

Frank Grube
Managing Director

15 Index

Advanced Feature Inquiry 153, 154
Advanced features 143, 149, 151
Area of Interest 104, 114, 115
Asynchronous broadcast 99
Bandwidth 109, 116, 118, 126
BAYER demosaicing 85
Binning 81, 82
Black value 62, 65
Brightness 65
Bus_Id 129
Busy Signal 44
Color correction 85, 86
Color information 85
Corrected image 71
Correction data 70, 73
Cycle delay 39
Data packets 48
Data path 50
Data payload size 126
Deferred image transport 101
Deferred Image Transport 162
Environmental conditions 10
Error states 38
Exposure time 29, 96, 100, 106, 115, 155, 156
Extended Shutter 96, 156
FastCapture 55, 101, 103, 162, 163
FireView 29
Flux voltage 39
focal width 13
Format_7 73, 81, 103, 104, 114, 150
Frame rates 14, 15, 16, 17, 18, 19, 20, 21, 22, 23, 116, 118
Free-Run 99
Fval Signal 44
Gain 29, 62, 64, 65, 104
Gamma function 67
HiRose jack 36
HiRose jack pin assignment 37
HiRose plug 37, 41, 165
HoldImg 55, 101, 102, 162, 163
HoldImg mode 102
IEEE 1394 13, 109
IEEE-1394 plug 36
IIDC 13, 29, 48, 49, 57, 91, 96, 97, 105, 107, 108, 114, 118, 128, 129, 134, 150, 151, 155
Input mode 41, 165
Input voltage 39

Input/Output pin control 41, 45, 165, 166
Inputs 8, 36, 37, 39, 40, 41, 59, 165
IntEna signal 44, 166
Interpolation 85
ISO_Enable 97, 98, 99, 107, 129
Jitter 100
LEDs 36, 38
Lookup tables (LUTs) 67, 68, 69, 159, 170
MaxResolution 154
Multi-Shot 98
Node_Id 129
Offset 62, 65, 96, 133, 150
OneShot 97
Output mode 45, 46, 166
Outputs 15, 36, 37, 39, 44
Power 39
RBG to YUV 86
rolling shutter 100
Sequence 104, 105, 107, 108
Sequence control 158
Sequence mode 104, 105, 106, 107, 108
Shading correction 70, 160
Shading images 70, 72, 73, 75, 76, 160, 161, 170
Spectral sensitivity 24, 25, 26, 27, 28
Status LEDs 38
Sub-sampling 83
System components 12
Test images 127, 157
Time response 97
Timebase 96, 154, 155
Triggers 14, 15, 16, 17, 18, 19, 20, 21, 22, 23, 38, 41, 59, 91, 97, 118, 130, 165
TWAIN VIA 29
Video data format 48
Video formats 109, 114
Video modes 109, 110, 111, 112, 113
29
White balance 57, 59